



### Headset Functions

- 1. Power ON your headset:**  
Press and Hold the Function button for about 3 seconds until the blue indicator flashes four times. After powering on, your headset should automatically connect to your last used phone if it is in operating range. If no paired phone is in range or no phone has been paired, the "NoiseHush N450" will enter Standby mode.
  - 2. Power OFF your headset:**  
Press and Hold the Function button until the red indicator rapidly flashes twice.
  - 3. To Answer or End a call:**  
Press the Function button once when there is an incoming call to Answer. Press the Function button once again to end the call.
  - 4. To Reject\* a call:**  
Press and Hold the Function button for about 3 seconds when there is an incoming call.
  - 5. To Redial\* the last call:**  
Press and Hold the Function button for about 3 seconds and then release.
  - 6. To activate Voice Dialing\*:**  
While connected to your phone, rapidly press the Function button once. Voice commands must have been previously recorded into your phone (see your phones user guide)
  - 7. To adjust the Volume:**  
Use your phone Function buttons to adjust your desired volume levels.  
\* To use these functions, your phone/device must support the Bluetooth Handsfree Profile.
- Note:  
To reset N450 simply connect to a charging device.  
Always turn OFF N450 when not in use to conserve battery power.  
Refer to your local safety laws and regulations before using the device.

### Contact Us

For additional help or to purchase accessories such as AC / DC, please visit us at [www.noisehush.com](http://www.noisehush.com)

### LED indicator chart

<b>Power on</b>	Blue indicator blinks 4 times
<b>Power off</b>	Red indicator blinks 4 times
<b>Standby mode</b>	Blue indicator blinks once every 2 seconds
<b>Sniff mode</b>	Blue indicator rapidly blinks twice every 10 seconds
<b>Pairing mode</b>	Red and Blue indicators alternately blink
<b>Active call</b>	Blue indicator rapidly blinks 2 times every 8 seconds
<b>Low battery</b>	All Blue indicators will change to Red
<b>Charging</b>	Red indicator stays ON
<b>Charging complete</b>	Red indicator turns OFF

Note: Sniff mode means your headset has a connection with your phone but is conserving power, and will wake up when any function is activated.

**Pairing NoiseHush N450 Bluetooth headset with your cell phone will create a stored connection in the headset and your Bluetooth cell phone. Pairing has to be done only once, when first connecting to a phone.**

### Charging the Headset:

Before you start, charge your N450 unit by plugging the USB Charger into the USB port on your computer then plug the other end into the headset. The Red LED indicator will light up showing that the unit is being charged. When charging is complete the Red LED indicator will turn off automatically.

### Pairing the Headset:

1. First turn the phone OFF and then back ON again to refresh its memory.
2. Bring the mobile phone to about 30cm from NoiseHush N450 headset.
3. Find the Bluetooth menu in your mobile phone. Turn Bluetooth ON. (Check your mobile phone user guide)
4. With the NoiseHush headset OFF, Press and Hold the Function button for about 6 seconds until the LED flashes Blue to Red.
5. Your headset is now ready to be discovered by your Bluetooth mobile phone.
6. Perform a Bluetooth device discovery on your mobile phone to add a new device. It takes a few seconds to search for and find other Bluetooth devices around you.
7. When Bluetooth devices are found, the phone will display "NoiseHush N450". Scroll to it and press OK to confirm that you want to pair with it.
8. Enter the Passkey "0000" when your phone prompts you. The phone will now pair with the headset.
9. If your Bluetooth phone menu supports it "set as authorized" or "add to trusted devices"
10. Again select the NoiseHush N450 to connect with it. OR, Press the Function button to connect with the phone.
11. If the pairing is not successful, the Headset will return to the standby mode, please repeat the pairing process to try the pairing again.
12. Refer to your phones User Manual for any additional steps.

Note: To conserve battery, NoiseHush N450 will automatically turn off if it's not paired with your phone after 20 minutes.

[www.noisehush.com](http://www.noisehush.com)