

BTH360-S Bluetooth Stereo Headset

User Manual

© 2012 Kinivo LLC. All rights reserved.

Kinivo is a trademark of Kinivo LLC. Bluetooth word mark and the Bluetooth logo are registered trademarks of Bluetooth SIG. All other trade names are registered trademarks of respective manufacturers. This manual may not be copied in any media or form without the written consent of Kinivo LLC.

Kinivo Product Support

Online: http://support.kinivo.com Email: support@kinivo.com

Table of Contents


About DTU260 C


About 61 H300-3	
Overview (Before Use)	3
Charging the headset	4
First time charging	4
Low battery	4
Charge the headphones using the USB cable	4
Warning	5
Using the headset	6
1. Turning the headset on/off	6
2. Pairing headset with Bluetooth devices	6
3. Reconnecting the headset with devices	
4. Wearing the headset	8
5. Making calls	9
6. Playing music	11
7. LED indicator	13
8. Indication tone	14
Care and maintenance	14
• FAQs	15
Specifications	17
Warranty	18
Online Support / Contact Us	19
• •	

About BTH360-S

The **BTH360-S** offers the convenience of bluetooth connectivity and a rechargeable battery without the hassle of wires.

Overview (Before Use)





- 1) Status indicator light
- 2) Charging jack
- 3) Right speaker
- 4) Left speaker

- 5) Built-in microphone
- 6) Volume up/ next song
- 7) Multifunction button (MFB)
- 8) Volume down/ previous song

Charging the headset

First time charging


Before you first use your BTH360-S Bluetooth headset, please charge the battery fully.

Low battery

Low battery power is indicated by three "DONG" tones repeated every 30 seconds and the Red LED status indicator light blinking twice in a row.

Charge the headphones using the USB cable

The charging ports on BTH360-S are designed to prevent water / sweat from entering the headphones. Please use the included cable to charge the headphones from any USB charger.



- 1. Plug USB cable into any computer USB port or USB charger.
- 2. Plug opposite end of USB cable into headset's charging port

RED light on >> Charging

RED light off >> Finished charging

3. It will take about two hours to charge the headset fully.

Warning

The internal battery is recyclable.

Please contact your local electronics recycling program for disposing the headphones in a safe and environment friendly way.



Using the headset

1. Turning the headset on/off

Function	Operation	Indicator light
Turn on	Press multi-function button for about 3-5 seconds. Release when the blue light blinks.	Blinking blue light.
Turn off	Press multifunction button for about 3-5 seconds. Release when the red light blinks.	Blinking red light.

Note:

If the headset can not connect to any devices within 5 minutes of turning on, it will shut off automatically to conserve battery life.

2. Pairing headset with Bluetooth devices

1) How to enter pairing mode

Function	Operation	Indicator light
Enter pairing mode	Make sure the headset is turned off. Press multifunction button (MFB) for about 6-7 seconds. Release MFB when blue and red lights blink alternately.	Blue and red lights blink alternately.

Note:

Pairing mode will last 2 minutes. If the headset can not connect to any other devices within 2 minutes, it will automatically switch to standby mode with blinking blue light.

2) Pairing with one device

Before you use your headset for the first time, you will need to pair it with a Bluetooth-enabled cell phone. Pairing procedure may vary depending on the model of cell phone you use. Please refer to your cell phone user's manual for further information. The general pairing procedure is as follows:

- Please keep the headset and mobile phone within one meter of each other when pairing
- Activate the headset's pairing mode. (Please refer to "How to enter pairing mode" above.)
- Activate your mobile phone's Bluetooth function and search Bluetooth devices within available range. When the phone presents a list of devices found, select "Kinivo BTH360-S" from the list.
- When prompted by your cell phone to enter password or PIN, enter "0000" and press the "Yes" or "Confirm" button to confirm.
- After pairing successfully, choose "Kinivo BTH360-5" from the list of devices shown.
- After the headset is connected successfully its blue light blinks 2-3 times every 4 seconds.

Notes:

- If the pairing is not successful, please turn off the headset, then re-pair according to the steps 1-6 above.
- After your headset and mobile phone are successfully paired, They will remember each other so you will not need to re-pair next time. The headset can remember 8 paired devices. When the number of paired devices exceeds 8, the first device that was paired will be replaced.
- If you want to pair the headset with another device, please follow steps 1-6 above.

3. Reconnecting the headset with devices

- Automatic reconnection
 After headset is turned on, it will try to connect to the most recently connected device.
- Manual connection

If the headset does not connect to a device, please double-click the multifunction button. The headset will try to connect the most recently connected devices.

4. Wearing the headset

Hang the headset on the ears with both hands, as shown in the illustrations below. It is important to use both hands to put on or take off the headset; never pull or push the headset while putting it on or taking it off.

Fig. 3



After putting on the headset, rotate the earplug to get the most comfortable angle.

5. Making calls

Function	Status of the headset	Operation
Cancel call	Calling mode	Short press (press and release) multifunction button once
Answer call	Ringing	Short press multifunction button once Long press (press and hold)
Reject call	Ringing	Multifunction button about 2 seconds. Release when you hear a tone.
End call	Conversation mode	Short press multifunction button once

Volume up	Conversation mode	Short press "+" button
Volume down	Conversation mode	Short press "-" button
Transfer call to Mobile phone	Conversation mode	Long press multifunction button for 2 seconds
Transfer call to headset	Conversation mode	Long press multifunction button for 2 seconds
Microphone mute	Conversation mode	Double-click multifunction button
Cancel mute	Conversation mode (Microphone mute)	Double-click multifunction button
Voice dial	Standby mode (already connected with the device you are using)	Long press multifunction button for 2 seconds
Redial last number	Standby mode (already connected with the device you are using)	Double-click multifunction button
Delete pairing list	Turn off	Press multifunction button and "+" button at the same time for 8 seconds. Release when the blue light and red light are on at the same time for 1.5 seconds.

Warning: Excessive pressure from earphones and headphones can cause hearing loss.

Notes:

- Not all mobile phones support all the functions listed above. Please refer to your mobile phone's user's manual.
- The functions and prompt tones may vary by mobile phone model.
- When the volume is adjusted to maximum or minimum, you will hear a prompt tone.
- On some mobile phones, pressing the headset's answer button may transfer
 the call to the mobile phone. You can switch the call back to the headset by
 using the conversation switch button, or you can switch the call from your
 mobile phone. Please refer to your mobile phone's user's manual for further
 information.

6. Playing music

You can enjoy music wirelessly through the headset by connecting it to a mobile phone or Bluetooth transmitter that supports A2DP.

Function	Status of the headset	Operation
Volume up	Playing music	Short press "+" button

Volume down	Playing music	Short press "-" button
Previous song	Playing music	Long press "+" button for 2 seconds
Next song	Playing music	Long press "-" button for 2 seconds
Pause	Playing music	Short press multifunction button
Play	Paused	Short press multifunction button

Notes:

 By default, some mobile phones will transmit music to the mobile phone's speaker instead of the headset. If this is the case with your phone, select "transmit the sound via Bluetooth" in the settings menu and then choose "Kinivo BTH360-S" as speaker device. The music will then be transmitted to the headset. Please refer to your mobile phone's user's manual for further information.

When the volume is adjusted to maximum or minimum, you will hear a prompt tone.

 If you want to use the headset to select the last/next song or pause/play the song, then your Bluetooth mobile phone or Bluetooth transmitter paired with the headset must support the AVRCP profile. Please refer to the user's manual of your mobile phone or Bluetooth transmitter for further information.

7. LED indicator

1) Charging

LED indicator	Status of the headset
Red light on	Charging
Red light off	Finished charging

2) Pairing with the Bluetooth device

LED indicator	Status of the headset
Red and blue lights blink alternately	Pairing mode
Blue light quick blink - once every 2 seconds	Not connected to a device
Blue light quick blink - three times every 4 seconds	Headphones connected to a Bluetooth device
Blue light quick blink continuously	Calling/incoming call

Blue light quick blink - once every 4 seconds	Conversation mode
Red light quick blink - twice every 30 seconds	Low battery

8. Indication tone

Indication tone	Status of the headset
Continuous indication tone - 2 times every 5 seconds	Conversation mode with microphone muted
Three "dong" warning tones every 30 seconds	Low battery

Care and maintenance

Read the following recommendations carefully before using your BTH360-S headset. Following these, you will be able to enjoy this product for many years.

- Do not charge in damp and steamy conditions. Keep the charging port covered when the headphones are not being charged.
- Keep your headset dry and avoid allowing water to get inside the headset. To

- prevent internal circuitry from damage, do not keep in a damp place.
- Keep the product away from direct sunlight or hot places. High temperatures will shorten the life of electronic devices, destroy the batteries, or distort certain plastic parts.
- Don't let the headset touch hot water.
- Avoid exposure to cold environments. This may damage the internal circuit board
- Don't try to disassemble the product, as it may become damaged.
- Don't let the headset fall onto the floor or other hard surfaces, as this may damage internal circuitry.
- Don't use abrasive chemical cleaners or detergent to clean the product.
- Don't scratch the surface with sharp objects.

In the event that this product does not function properly, please contact

Kinivo technical support at support@kinivo.com

FAQs

1. What does it mean when the red LED blinks twice every 30 seconds?

Battery power is low; battery needs to be recharged.

2. Why is the red LED off when the headset is charging?

- a. Please make sure the charging device is properly connected to the headset.
- b. After a long period of disuse, the headset's battery may run down. In this case, you will need to charge the battery for 30 minutes, and then the red LED will come on and the headset will continue charging.

3. What is the effective range between the headset and a mobile phone?

The maximum range of the headset is 10 meters. The actual range may vary in different environments

4. My mobile phone is searching; why can't it find the headset?

The mobile phone will not find the headset if the headphones are not in pairing mode. Make sure that the headset is in pairing mode - the red and the blue led should be blinking alternatively. They should also be in an effective range.

5. Why can't I hear the voice of the person I am talking to?

- a. Make sure the headset has been switched on;
- b. Make sure the volume is not too low or muted;
- c. Make sure the headset is properly connected to your mobile phone; and
- Make sure the distance between the headset and the cell phone is in the effective range.

6. Why is the voice of the person I am talking to not clear?

- a. Make sure your mobile phone has sufficient signal strength; and
- b. Make sure the headset is in the effective range.

7. Why can't I pause, play, play the previous song, and play the next song from my headset when playing music?

To enable this function, your Bluetooth device must support AVRCP (Audio/Video Remote Control profile).

Notes:

- This device complies with Part 15 of the FCC Rules. Operation is subject
 to the following two conditions: (1) this device may not cause harmful
 interference, and (2) this device must accept any interference received,
 including interference that may cause undesired operation.
- Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Specifications

Bluetooth version	Bluetooth V2.1+EDR
Bluetooth profiles	HSP, A2DP, AVRCP

Talk / Music Time	6 hours
Headset standby time	150 hours
Charging input	DC5.0V 130mA
Headset charging time	Approx 2-3 hours
Dimension	132*134.5*61mm
Weight	Approx 35.3g

Warranty

1 Year Limited Hardware Warranty.

Kinivo hereby warrants to the customer of record that this product is in goodworking condition and free from defects in material or workmanship under normal use for a duration of 1 year after the date of purchase. The product has been tested to meet the highest quality standards in each testing category. In the unlikely event that the product proves to be defective, Kinivo will repair or replace the product free of charge. If replacement is required and if Kinivo then no longer carries the same product, then Kinivo reserves the right to substitute the product with a replacement product of like quality and size, suitable for the intended use. This warranty is limited to repair or replacement of the mentioned product only, is non-transferable and does not extend to any product damaged by misuse, natural disasters or any other circumstances beyond Kinivo's control. The warranty does not cover or provide for the reimbursement or payment of incidental or consequential damage resulting from breach of the limited warranty described above. Except for the limited warranty described above we offer no other warranties expressed or implied, and other than limited warranty expressly contained herein, we hereby disclaim any and all warranties, including without limitation any implied warranties of merchantability, suitability or fitness for a particular purpose.

If your product is not functioning or you have any concerns please contact Kinivo Support before returning the product.

Online Support / Contact Us

Please visit us at <u>support.kinivo.com</u> or <u>www.kinivo.com</u> for support information, downloads and how-to's. You may also reach us via email or live chat (details below).

Kinivo Product Support
Email: support@kinivo.com

Live chat: http://support.kinivo.com



year limited hardware warranty

Kinivo Product Support

Online: http://support.kinivo.com

Email : support@kinivo.com

Made in china





