- 1.1 Basic Operations
- 1.1.1 Power On/ Off and Sleep
- Connect the device to the TV with HD cable, connect device to the power adaptor, Connect mouse, air mouse or other input devices with USB port
- 2. Press power button to start device, power LED turns into blue
- 3. Under the power on mode, long press power button over 10 seconds to power off the device, Power LED turns off
- 4. Under power on mode, press remote control's power button, device is entering into sleep mode. Power LED turns into red
- 5. Under sleep mode, device will be wake when you press remote control's power button, power LED turns from red to blue

1.1.2 Open applications

Use remote control's arrow keys to choose the wanted program, click OK button to open the selected program

1.1.3 Switch in the applications

Click icon in to view recently used programs, click program icon to switch application arbitrarily



1.1.4 Close Applications

Click icon T * to view recently used programs, choose one of them by click and hold, drag it to blank area to close the application



* This function only operated in the condition of Mouse mode

1.1.5 Back To Home Screen

Click icon to return to home screen
Click icon on remote control to return to home screen

1.1.6 Read External Storage Data

Read U Disk

Insert U flash disk or removable hard disk into USB port in the status of power on, icon papears in top left corner of the desktop, open "FileBrowser", the identified USB(A:) will appear under "Local Disk", U disk's operation is available now



Read TF card

Insert TF card into the device in the status of power on, when icon appears in top left corner of the desktop, open "FileBrowser", the identified External Storage Card will appear under "Local Disk", TF card's operation is available now

1.Home Screen → SETTINGS → Network → Select"Wi-Fi"to open WIFI function


2.Choose Hotspot → Input Password→ Connect to the network



1.1.8 Ethernet Function

1.Home Screen→SETTINGS→Network→ Select "Ethernet" to open Ethernet function

2 Insert network cable, network will be connected automatically



1.1.9 Bluetooth Function

Home Screen→ SETTINGS→ Other→ More Setting→ Bluetooth→ ON



Click "Not visible to other Bluetooth devices" , the menu turns to "Visible to all nearby Bluetooth devices", 2 minutes countdown begin



Select the target device within 2 minutes, connection will be done automatically, some devices need to enter pairing code, usually is 0000 or 1234



2.1 Advanced Operations

2.1.1 WLAN Hotspot

Operations on Devices

Home Screen→ SETTINGS→Other→ More Setting→ More...→ Portable hotspot → Select "Portable Wi-Fi hotspot"

Select "Set up Wi-Fi hotspot" to set up "Network SSID", "Security", "Password" parameters



2.1.2 Miracast

Operations on Devices:

Home Screen→ My recommend→ Miracast → Open Miracast service



Operations on other devices (for example MIUI 2) Home Screen→ Settings→ WLAN→ Press menu→ WLAN Display→ Find the devices searched, click invite





Corresponding device will be listed when device begin to search, a pop-up invite window appears, click "accept"



Complete connection. device will display other device




2.1.3 DLNA

Ensure that other devices like Iphone, Android smart phone, etc have opened iMediaShare, and they are in the same local wireless I AN with this device

Operations on Device:

Home Screen→My recommend→Media Center→DLNA DMR→Start DMR→ON



Complete connection, device will display other device's images



2.1.4 AirPlayer

Ensure that apple devices(iPhone,iPad etc)are in the same local wireless LAN with this devices

Operations on Devices:

Home Screen→ My recommend→Media Cente→AirPlayer→Start AirPlayer→ON



Operations on Iphone devices







Through WIFI, multimedia content (Images, music and videos) in Iphone devices can be transferred to TV for playing





2.1.5 Remote Control

Home Screen→SETTINGS→ Advanced→Remote Contro→ON→ Show the IP address



Ensure phone is in the same local wireless LAN with device, install RemotelME.apk and start the program, choose the IP address, then you can control the device (support shifting between remote mode, movie mode, mouse mode and keyboard mode)

