

	Technical d	lata sheet	Product Name San	SantCare-watch		
Colors	Pink, Blue Orange, Green		Model No.	ST-01		
		Specifications			Note	
C P U	Model	MT6260D	by N	MediaTek		
	Cores	Single				
	Frequency	Main Frequency: 360 MHz				
	Architecture	ARM7EJ-S <sup>TM</sup>				
Main Features	LCD Size	0.66 inches OLED	Resolution: 64*48			
	Storage	RAM	32M Bits			
		ROM	32M Bits			
	Body dimensions	57*30*14	Unit: mm		Not including the wristband	
	Dimension of PCBA	Main: 25.6*17.5*1.0	Aux: 25.6*17.5*1.0		Unit: mm, 8 layers	
	O.S.	Nucleus			Provided by MTK	
Detailed Descrip- tion	Ports and interfaces	GSM Antenna	PIFA Antenna, LDS Technology			
		GPS, BT Antenna	Yes			
		Keys	Power On/Off + 3 Side Keys			
		Earphone Jack	No			
		SIM Socket	Micro SIM Socket * 1			
	LCD Module	Screen Size	0.66 inches OLED			
		Resolution	64*48			
		I/O	BPI 8 bits			
		Linking Method	BTB; Board to Board			
	Touch Panel	Activity	No		<u> </u>	
		Driver IC	No			
	Battery	Voltage/Capacity: 3.7V,400mAh, Lithium Polymer		<ol> <li>Non-removable</li> <li>Non-explosive</li> </ol>		
		Stand By Time:	160 Hours with AG	PS	2. INOH-CAPIOSIVE	
			24 Hours with GPS			
	Charger	3 in 1(Earphone/charge/USB)		ack 5 PIN Micro USB		
	Speaker	AAC0916	Single speaker		<b>.</b>	
	Aux Board	GSM communication	2G Antenna		Quad-Band 850/900/1800/1900	
		Data Transmission	GPRS, EDGE		Depends on the network	
	Storage	RAM	32M Bits			
		ROM	32M Bits			
		Expansion Socket	No		<u> </u>	
	Transmission	Bluetooth	4.0 BLE			
	Sensors	Light	Wear-off detector			
		Gravity	Yes			
	Indicator	Signal (GSM/data/GPS)	Yes			
	Interface	Micro USB	Yes			
	Quality Requirements	Waterproof grade: IP65     Hypoallergenic silicon gel.				
	Others	Please check the feature list below for details about Software features.     This product interacts with a smart phones and servers, as described in feature list.				
	USB cable	1 piece			•	
Accesso- ries	Travel Charger	1 piece	110 V. AC / 60 Hz	z or 220 V. AC / 50 Hz.	Depending on geography	
	User Manual	1 piece	Multi-lingual		· ·	



## **Description**

\* The ST-01 is a security phone-watch for kids.

## **Features**

- \* GSM calls to/from pre-stored numbers.
- \* GPS/AGPS tracking.
- \* SOS Alarm.
- \* Long distance Walkie-Talkie.
- \* Bluetooth child companion.
- \* Wear-off sensor.
- \* Collision detector.
- \* Pedometer.
- \* Sever synchronized time.
- \* Waterproof Grade: IP65.
- \* Non-toxic hypoallergenic silica gel.

## Software supported features (smart phone required)

- \* Calls
  - Dial out to up to three family numbers by a long press on the key assigned to the desired number.
  - Receive calls from 8 telephone numbers according the number priority configured in the smart phone.
  - Kid monitor: 2-way voice call from/to smartphone.
- \* Long distance Walkie-talkie
  - Bi-directional real-time voice messages can be exchanged between ST-01 and smart phone, emulating a walkie-talkie. These messages only consumes data volume. Thus no voice charges.
- \* SOS
  - In case of emergency, by pressing the SOS key, the ST-01 will first send an alarm SMS to the three pre-stored family numbers, and then automatically will poll the three family numbers from number 1 to number 3 one by one until the call is attended.
- \* Tracking & Locating
- The tracking location system is formed by ST-01, satellite (GPS), server and the smart phone.
- The ST-01 gets location data from the satellite and triangulates its own position, then proceeds to send it to the server, which stores the data and send the position per request to the authorized smart phone.
- GSM locating through SMS sending is supported.
- Configurable auto-location update period.
- Accurate, balanced and power saving modes.
- \* Geo-fencing
  - Configurable safety area delimitation via smart phone.
  - Alarm notification emitted in case the ST-01 goes outside the safety area.
- \* Status monitor
- If the collision detector is enabled, an alarm will be received by the smart phone in case the ST-01 detects a shock.
- If the wear-off detector is enabled, an alarm will be received by the smart phone in case the ST-01 has been removed from wrist for more than 3 secs.
- Separation sensor via Bluetooth. An alarm is emitted in case of more than 15 meters separation between ST-01 and the smart phone.
  - Low battery alarm.
- \* Exercise monitor
  - Pedometer function (step counter).

**Note:** Up to 8 different ST-01 devices are supported by the app.