



All-In-One

**Jump Starter
Compressor
200W Inverter
12 VDC Power Source
Flexible Light Source**



Specifications

■ Battery Type	Maintenance-Free 12V 17Ah SLA Battery	■ Inverter	200 Watt Continuous
■ Cables	6 Gauge, 28" Cables	■ DC Socket	Two 12 Volt DC Cigarette sockets - 20 Amp maximum
■ Dimensions	W-16.5" X H-10.0" X D- 9.0"	■ Compressor	260 PSI
■ Weight	23 lbs		
■ Overload Protection	20 Amp Re-settable Circuit Breaker		

Features

- Built-in fully automatic internal battery charger with LED "status" indicators
- Heavy duty clamps with copper jaws provide solid connection to either side or top-post batteries
- Durable high impact resistant case
- Easy to read LED battery "status" indicator
- Illuminated ON-OFF inverter switch
- Built-in easy to read pressure gauge
- Thermally protected compressor with auto cutoff and restart to protect compressor from damage due to over-heating
- Long life detachable LED flexible light may be inserted in either of the two DC sockets for greater flexibility
- Inverter has both short circuit and reverse polarity protection
- Re-settable circuit breaker to protect inverter from overload condition
- 18" flexible cloth covered compressor hose

Contact Us:
TF 866 . 892 . 1122
P 469 . 892 . 1122
E sales@upgi.com

UPG No. 71732



www.upgi.com

VR092007