
# Service & Parts Manual

# CD-210 Ice Dispenser

# ICE-O-MATIC.

A **WELBILT** Company

11100 EAST 45TH AVE. DENVER, COLORADO 80239 (303) 371-3737



# ICE-O-MATIC CD-210 DISPENSER

## **TABLE OF CONTENTS**


| SECTION A: GENERAL INFORMATION   |             |
|--|-------------|
| Model Numbering System A-1- Foreword                                     | A-3         |
| Machine Photo and Utility Connections                                    | A-4         |
| SECTION B: INSTALLATION  |             |
| Uncrating, Inspection, and Freight Claim Procedures B-1-Set-up Procedure | -B-2<br>B-3 |
| SECTION C: OPERATION   |             |
| Cleaning Procedures  | C-1         |
| SECTION D: SERVICE   |             |
| Service Diagnosis  | D-1<br>D-2  |
| SECTION E: PARTS   |             |
| Parts Ordering and Warranty Procedures                                   | E-1<br>F-2  |

# ICE-O-MATIC MODEL NUMBERING SYSTEM


The Model Number fully describes the unit. A letter code identifies the model series. A two or three digit number identifies the basic family size and electrical characteristics. A second letter code identifies the type of condenser. Cabinet size is identified by a two digit number. Finish is identified by a letter code.

The following examples illustrate how Model Numbers are developed:


#### **CUBERS**




#### **FLAKERS**




#### REMOTE CONDENSORS




#### BINS



#### FLAKER/DRINK DISPENSER



#### **DISPENSERS**



Other model nomenclature same as Flaker Cuber nomenclature

Electrical characteristics of all units ared coded in the Model Number by a one digit number appearing after the basic family size. The codes is as follows:


| Code Number | *Volts      | **Cycles   | Phase | No. of Service<br>Wires Required |
|-------------|-------------|------------|-------|----------------------------------|
| 0           | 115         | 60         | 1     |                                  |
| 1           | 208-230/115 | 60         | 1 1   | 2                                |
| 2           | 208         | 60         | 1 ;   | 3                                |
| 3           | 230         | 60         | 1 1   | 2                                |
| 4           | 230/115     |            | 1 1   | 2                                |
| 5           |             | <u>e</u> 0 | ] 3 [ | 4                                |
| ě           | 230         | 50         | 1 1   | 2                                |
| 9           | 208-230     | 60         | 1 1   | 2                                |
| <u>'</u>    | 208-230     | 60         | 3     | 2                                |
| 8           | 208-230     | 50-60      | 1 1   | 3                                |

<sup>•</sup> Two voltage values separated by a hyphen (-) means that the unit is capable of operating over this voltage range.

Two voltage values separated by a slant (/) means that both voltages must be supplied at the installation. This is usually done by a neutral wire

# **SERIAL NUMBER FORMAT**

| A - January B - February C - March D - April E - May F - June G - July H - August I - September J - October K - November L - December |                | 3 - 1983<br>4 - 1984<br>5 - 1985<br>6 - 1986<br>7 - 1987<br>8 - 1988<br>9 - 1989<br>0 - 1990 |                            |                   |
|---|----------------|--|----------------------------|-------------------|
| ALL BINS  | -00            |  | MF-400<br>MF-600<br>MF-750 | -30<br>-31<br>-32 |
| RC40  | -01            |  | MF-1000<br>MF-2500         | -33<br>-34        |
| RC60  | -02            |  | MF-5000                    | -35               |
| RC80  | -03            |  | MF-700                     | -36               |
| RC120   | -04            |  |                            |                   |
| C-20  | -11            |  | HD-350                     | -41               |
| C-40  | -12            |  | HD-650                     | -42               |
| C-60  | -13            |  | HD-750                     | -43               |
| C-81  | -14            |  |                            |                   |
| C-121   | -15            |  | FD-550                     | -51               |
| C-10  | -16            |  | 5.050                      |                   |
| F-250   | 21             |  | D-250                      | -61               |
| F-350   | -22            |  | D-350                      | -62               |
| F-600<br>F-750  | -23<br>-24     |  | D-600<br>D-750             | -63<br>-64        |
| F-1000  | -24<br>-25     |  | D-1000                     | -64<br>-65        |
| F-400   | -26            |  | D-400                      | -66               |
| F-700   | -27            |  | D-700                      | -67               |
|   | <del>_ ,</del> |  | DX (used)                  | -99               |




#### **FORWARD**

We, ICE-O-MATIC, present this service manual to aid the service men and users in the installation, operation, and maintenance of your equipment.


If, at any time, you encounter conditions that are not answered in this manual, write or call the service department of ICE-O-MATIC explaining the conditions in detail, giving THE MODEL NUMBER AND SERIAL NUMBER of the unit, and we will give your questions our immediate attention and reply.

ICE-O-MATIC 11100 E. 45th Avenue Denver, Colorado 80239 (303) 371-3737





## DIMENSIONS (Inches) & PLUMBING/ELECTRICAL CONNECTIONS DIAGRAM:



# HOW THE ICE-O-MATIC CD-210 DISPENSER WORKS

The CD-210 is available with either a push button switch, hotel key, or coin mechanism to activate the dispenser. Once the push button switch, (or hotel key, coin mechanism) is depressed, the chute solenoid, and dispense motor are energized. The chute solenoid pulls open the chute damper door, and the dispense motor drives the stainless steel auger and ice is delivered out the ice delivery chute. The machine will continue to dispense ice, as long as the dispense switch is depressed.

## INSTALLATION

#### A. Uncrating & Inspection Procedures

- 1. Inspect exterior of shipping carton and skid for any signs of shipping damage.
- 2. Using a pry bar or large screwdriver, remove all staples from bottom of carton. Do not pry against carton.
- 3. Lift carton straight up, entirely off dispenser. Do not discard carton until satisfactory inspection of dispenser is complete.
- 4. Inspect dispenser cabinet for any signs of shipping damage. Should any damage be noted, follow Freight Claim Procedures on page B-2.
- 5. Gently lay dispenser on its back and remove the four skid mounting bolts.
- 6. Attach the (4) 6" legs, packaged inside dispenser bin.
- 7. Stand the dispenser upright and LEVEL from front to back and side to side.
- 8. Fill out Quality Control Card and return to factory.

## FREIGHT CLAIM PROCEDURES

### -IMPORTANT-

THIS MERCHANDISE HAS BEEN CAREFULLY INSPECTED AND PACKED IN ACCORDANCE WITH THE CARRIER'S PACKING SPECIFICATIONS. RESPONSIBILITY FOR SAFE DELIVERY HAS BEEN ASSUMED BY THE CARRIER. IF LOSS OR DAMAGE OCCURS, YOU AS CONSIGNEE MUST FILE A CLAIM WITH THE CARRIER, AND HOLD CONTAINER FOR CARRIER'S INSPECTION.

#### **CONCEALED LOSS OR DAMAGE**

IF LOSS OR DAMAGE DOES NOT APPEAR UNTIL MERCHANDISE HAS BEEN UNPACKED MAKE A WRITTEN REQUEST FOR INSPECTION BY THE CARRIER WITHIN 15 DAYS OF THE DELIVERY DATE. THEN FILE A CLAIM WITH THE CARRIER.

DO NOT RETURN DAMAGED MERCHANDISE TO US WITHOUT WRITTEN PERMISSION. INSPECT PROMPTLY AND FILE CLAIM WITHOUT DELAY.

#### **VISIBLE LOSS OR DAMAGE**

ANY EXTERNAL EVIDENCE OF LOSS OR DAMAGE MUST BE FULLY DESCRIBED AND NOTED ON YOUR FREIGHT BILL OR EXPRESS RECEIPT AND SIGNED BY THE CARRIER'S AGENT. CLAIM SHOULD THEN BE FILED ON A FORM AVAILABLE FROM THE CARRIER REQUEST.

DO NOT RETURN DAMAGED MERCHANDISE TO ICE-O-MATIC

**FILE YOUR CLAIM AS ABOVE** 

## INSTALLATION

**DANGER:** Electrical shock and/or injury from moving parts inside this machine can cause serious injury. Electrical Supply Voltage must be disconnected while performing the set-up procedure.

#### **B.** Set-up Procedure

NOTE: All installations must conform with local plumbing and electrical codes.

CAUTION: Make certain all power to equipment is off during installation!

- 1. Install the power supply line or cord into the electrical box located on the rear panel. NOTE: All wiring must conform with local codes.
- 2. Install drain line to 3/4" FPT.

IMPORTANT: Run all drain lines separately to an open or trapped drain.

#### Securing Ice Machine To Dispenser

Carefully set the icemaker on top dispenser. Using the (2) mounting straps, and (4)  $\frac{1}{4}$ -20 screws, (packaged in bin area) secure ice machine to dispenser.

#### Installing Ice Machine Cover On Icemaker

Remove 4 side panel front screws (2 on each side). With front of icemaker in place slip ice machine cover over front panel of icemaker. Align mounting holes in ice machine cover with the same screw holes and re-install screws.

|  | ·      |
|--|--------|
|  |        |
|  |        |
|  |        |
|  |        |
|  |        |
|  | .)<br> |
|  |        |
|  |        |
|  |        |
|  |        |
|  |        |

#### CLEANING PROCEDURES

WARNING! WHEN USING CLEANING FLUIDS OR ANY CHEMICALS, RUBBER GLOVES AND EYE PROTECTION SHOULD BE WORN.

- 1. DISCONNECT ELECTRICAL POWER TO ICE MAKER.
- 2. REMOVE ALL ICE FROM BIN.
- 3. DISCONNECT ELECTRICAL POWER TO DISPENSER.
- 4. REMOVE THE FRONT PANEL FROM THE ICE MACHINE FOR ACCESS TO BIN AREA. FOR GREATER ACCESS, REMOVE BLUE SHIELD (EVAPORATOR CURTAIN).
- 5. PREPARE A SOLUTION OF APPROVED ICE MACHINE CLEANER ACCORDING TO LABEL INSTRUCTIONS ON THE CONTAINER.
- 6. USING THE CLEANING SOLUTION AND A NON-METALLIC BRISTLE BRUSH, SCRUB THE INTERIOR OF THE ICE BIN AND THE AUGER.
- 7. RINSE ALL PARTS THOROUGHLY WITH CLEAN WATER.
- 18. WASH THE BIN AND AUGER USING THE FOLLOWING SANITIZING SOLUTION: PREPARE 1-1/2 TO 2 GALLONS OF APPROVED EPA/FDA SOCIUM HYPOCHLORIDE FOOD EQUIPMENT SANITIZER TO FORM A SOLUTION WITH 100 PPM CHLORINE YIELD MINIMUM.
- 9. RETURN THE ICE MAKER AND DISPENSER TO OPERATION.
- 10. CHECK FOR PROPER OPERATION.

9071519-01

|  |  |  | £. | • |
|--|--|--|----|---|
|  |  |  |    |   |
|  |  |  |    |   |
|  |  |  |    |   |
|  |  |  |    |   |
|  |  |  |    |   |
|  |  |  |    |   |
|  |  |  |    |   |
|  |  |  |    |   |
|  |  |  |    |   |
|  |  |  |    |   |
|  |  |  |    |   |
|  |  |  |    |   |

## GENERAL SERVICE INFORMATION

#### SERVICE DIAGNOSIS

#### Condition

### Possible Cause or Remedy

- 1. Dispenser will not deliver ice.
- a. Thoroughly check all wire connections.
- b. Defective chute solenoid.
- c. Defective dispense motor.
- 2. Excessive bridging or clustering of ice.
- a. Extremely low usage of dispenser.

3. Thumping noise.

- b. Water running into dispenser from ice machine
- a. Loose or misaligned chain. To tighten chain, loosen 3 nuts mounting motor bracket to front metal panel and push bottom of motor bracket toward left side of machine. Retighten nuts before running machine.


If misaligned, loosen set screws in sprocket or sprockets, align sprockets. Chain should be parallel to front panel. Tighten set screws.

b. Tighten all nuts firmly. Check nuts on front auger bearing flange.

#### COIN MECHANISM

- 4. Coin Mech does not operate consistently.
- 5. Coin Mech not dispensing enough ice/too much ice.
- 6. Slide goes back but does not take money.
- a. Remove coin-mech timer and check cam. Replace if necessary.
- a. Replace existing cam with appropriate size cam.
- a. Remove timer and arrange wires to allow enough clearance for the slide to operate correctly.

# **CD-210 WIRING DIAGRAM**





## **PARTS SECTION**

# When Ordering Parts Please Specify Model and Serial Number

| MILE HIGH EQUIPMENT  | DEM              | VER, COL | DRADO 80   | 239 U.S.A.   |
|--|------------------|----------|------------|--------------|
| MODEL  | SERIAL NO        |          |            |              |
| VOLTS  | Нz               | Ph.      | WIF        | ve           |
| COMPRESSOR   | F.L.A.           |          | _LRA_      |              |
| AUGER  |                  |          |            |              |
| FAN  |                  | DES      | IGN PRES   | SURES        |
| MARVEST  |                  | X        | PSI        | BARS         |
| PUMP   |                  | 141      |            |              |
| BIH DISPENSER  |                  | ro       | ***        |              |
| MINIMUM CIRCUIT AMPACITY   |                  | <u> </u> |            | LJ           |
| MAXIMUM BRANCH CIRCUIT FUSE SIZE<br>OR HACR TYPE CIRCUIT BREAKER | · <del></del>    |          | <b>(1)</b> | ATAL         |
| BEVERAGE FAUCET AMPS   |                  |          |            |              |
| USE WITH ICE-O-MATIC REMOTE CONDENSER MODEL NO                   |                  |          |            |              |
| TOTAL BYSTEM REFRIGERANT CHARGE: TYPE:                           | Oz:              | ¢        | Preme:     |              |
| MILE HIGH EQUIPMENT COMPANY                                      | DE               | ENVER CO | LORADO     | 90239 U.S.A. |
| MODEL  | SERIAL<br>MUMBER |          |            |              |

# CD-210 PARTS SECTION

### CABINET PARTS

| INDEX<br>NUMBER | DESCRIPTION                 | PART<br>NUMBER | NUMBER<br>REQUIRED<br>PER<br>MACHINE | REMARKS                                  |
|-----------------|-----------------------------|----------------|--------------------------------------|--|
| 1               | Front Panel                 |                | 1                                    |  |
|                 |                             | 9051250-01     |                                      |  |
|                 | Coin                        | 9051250-02     | 1                                    |  |
|                 | Kev                         | 9051250-03     |                                      |  |
|                 | Ving Card                   | 9051250-04     | 1                                    |  |
|                 | Decal-Push Button           | 9071389-01     | 1                                    |  |
|                 | False Front                 | 9051185-01     | 1                                    | Opt. assy.                               |
| 2               | Push Button Switch          | 9101141-01     | 1                                    | Opt. assy.                               |
| 3               | Leg Set                     | 9021001-03     | 1                                    | Set of 4                                 |
| ELECT           | RICAL COMPONENT             | S              |                                      |  |
| 1               | Dispense Motor              | 9161082-01     | 1                                    |  |
| 2               | Auger                       | 9131158-01     | 1                                    |  |
| 3               | Chute Solenoid              |                | 1                                    |  |
| 4               | Solenoid Mounting           | 9131223-01     | 1                                    |  |
| -               | Cover                       |                |                                      |  |
| 5               | Solenoid Tension            | 9021061-01     | 1                                    |  |
| •               | Spring                      |                |                                      |  |
| 6               | Linkage, Discharge<br>Chute | 9131222-01     | 1                                    | Connecting                               |
| 7               | Contact Block               | 9101141-02     | 1                                    | Link Solenoid<br>On Dispense             |
| 8               | Contactor                   | 9101002-03     | 1                                    | Switch                                   |
| 9               |                             | 9101152-01     | 1                                    |  |
| 10              | Overload Heater             | 9101152-01     | 1                                    |  |
| DRIVE           | SYSTEM                      |                |                                      |  |
| 1               | Chain                       | 6101001-02     | 1                                    |  |
| 2               |                             | 3012240-01     | 1                                    |  |
| 3               | Connecting Link             | 9111009-02     | 1                                    | #40 Single                               |
| 4               | Sprocket                    | 9111007-08     | ī                                    | 12 Tooth                                 |
| 5               | Sprocket                    | 9111007-09     | î                                    | 14 Tooth                                 |
| 6               | Motor Mounting              | 2021417-01     | ī                                    | 11 100011                                |
|                 | Bracket                     |                | _                                    |  |
| 7               | Key Square                  | 9021028-01     | 1                                    | $3/16 \times 3/4$                        |
| 8               | Bushing Assembly            | 9121036-01     | 1                                    | -, -, -, -, -, -, -, -, -, -, -, -, -, - |
| 9               | Bearing                     | 9121040-01     | 1                                    |  |
| 9A              | Bearing Flange Set          | 9121040-02     | 1                                    |  |
| 10              | Grommet                     | 9051002-09     | . 1                                  | $3/4 \times 1/16$                        |
| 1 l             | Ice Chute Assembly          | 2021419-01     | 1                                    |  |
| 12              | Ice Chute Gasket            | 9051263-01     | 1                                    |  |
| 13              | Ice Deflector               | 3011924-01     | 1                                    |  |
| 1.4             | Drain Fitting Assy.         | 2041454-01     | 1                                    |  |