



DVD-C500
DVD-C550
DVD-C550K

คุณมีการใช้งาน คุณมีผู้ใช้

ทุกจินตนาการ ล้วนเป็นจริงได้
ขอขอบพระคุณที่เลือกซื้อผลิตภัณฑ์ชั้นชูงชิ้นนี้
หากต้องการได้รับบริการที่ครบถ้วนยิ่งขึ้น
โปรดลงลงทะเบียนผลิตภัณฑ์ของคุณที่เว็บไซต์

www.samsung.com/global/register



ENERGY STAR
AK68-01883A



ไทย

หมายเหตุ

- แผ่นดิสก์เหล่านี้ไม่สามารถเล่นกับเครื่องเล่นที่ได้
 - DVD-ROM
 - CD-ROM
 - CDI
 - CDGs เล่นดีสิ่งเด่นนี้ไม่สามารถ
 - DVD-R, +R
 - CD-RW
 - DVD+RW, -RW (หมด V)
- เครื่องเล่นในสามารถเล่นแผ่น CD-R, CD-RW และ DVD-R บางแผ่นได้ เช่นจานชนวนของแผ่นดิสก์ที่รองรับในการบันทึก

การป้องกันการตัดออก

แผ่น DVD สามารถปกป้องข้อมูลเพื่อป้องกันการตัดออกได้ด้วยเหตุผล คุณควรตรวจสอบเครื่องเล่น DVD ของคุณซึ่งต้องมีฟังก์ชันป้องกันการตัดออก โดยไม่ผ่าน VCR (เครื่องเปลี่ยนวิดีโอ) การซื้อมือถือ DVD เป็นผลให้การตัดออกซึ่งจึงอาจเกิดขึ้น สำหรับการซื้อตัวเครื่อง VCR เป็นผลให้การตัดออกฟังก์ชันนี้รวมเอาเทคโนโลยีข้างหน้าสุดที่สุดที่ได้รับความนิยมของโดยทั่วไป ทรัพย์และลิขสิทธิ์ของ Rovi Corporation อยู่ภายใต้กฎหมายของบริษัท Rovi Corporation และจังหวะที่มีน้ำเสียงที่ต้องการ สำหรับการซื้อตัวเครื่องที่มีฟังก์ชันนี้ ทาง Rovi Corporation ได้รับอนุญาตจาก Rovi Corporation และได้ออกยุทธศาสตร์ที่จะบังคับใช้ในทุกๆ แผ่นที่จัดทำขึ้น และในกรณีที่จำกัด แต่ที่นั่นด้วยได้รับอนุญาตเป็นอย่างแน่นอน Rovi Corporation ที่มีความสามารถในการจัดการห้องน้ำของกลุ่มนี้ที่ไม่สามารถเข้าถึงได้

การรับรอง DivX



DivX, DivX Certified

ผู้รับรองทราบว่า โทรศัพท์ความคุ้มครองทุกเครื่องไม่ได้ที่นั่นก็ได้กับผลิตภัณฑ์ และขอติดป้ายไว้ในงาน คงภาพในกรณีที่เกิดปัญหาเรียกเก็บค่าไฟในระบบไปรษณีย์และสแกนกับบันไดร์รูม 576, 720, 720 และลิขสิทธิ์ของ Rovi Corporation ให้ผู้ใช้สิ้นสุด บทบาทที่สำคัญที่สุดในระบบ 'จานชนวน' คุณควรรู้ 'คุณควรรู้' หากมีค่ามากเทียบกับเครื่องรับโทรศัพท์น้ำ น้ำเครื่องเล่น DVD รุ่น 576, 720, 1080p โปรดติดต่อศูนย์บริการลูกค้าของชั้นนำ "

คำอธิบาย

ตัวควบคุมที่แผ่นด้านหน้า

DVD-C500



เครื่องหมายบนแผ่นดิสก์

	หมายเลขอุปกรณ์ภาคในการเล่น
	แผ่นดิสก์ดอลบี้ดิจิตอล
	แผ่นดิสก์ stereo
	แผ่นดิสก์เสียงแบบดิจิตอล
	แผ่นดิสก์ DTS
	แผ่นดิสก์ MP3

DVD-C550



DVD-C550K



1. ถาดวางแผ่นดิสก์

วางแผ่นดิสก์ที่นี่

2. DISPLAY

ตัวแสดงสถานะการทำงานจะแสดงที่นี่

3. OPEN/CLOSE (A)

กดเพื่อเปิดและปิดถาดวางแผ่นดิสก์.

4. STOP (■)

หยุดการเล่นแผ่นดิสก์

5. PLAY/PAUSE (►||)

กดเพื่อเปิดและปิดถาดวางแผ่นดิสก์

6. POWER ON/OFF (○)

เมื่อปิด เมื่อเปิด/ปิดเครื่องเล่น

7. USB Host (DVD-C550/DVD-C550K)

ต่ออุปกรณ์ไฟฟ้าติดต่อ, ตัวว่าง空闲, หรืออุปกรณ์ สื่อเก็บข้อมูลที่สามารถดูดอ่านได้

8. รับสัมผัสสัมภาระในโทรศัพท์ (DVD-C550K)


ใช้เพื่อรับสัมผัสถึงสีของโน้ตโทรศัพท์ เมื่อต้องการใช้ปุ่มให้กดเข้าไป หนนูนไปทางซ้ายหรือขวาเพื่อควบคุมระดับสี

9. MIC 1/2 (DVD-C550K)


เชื่อมต่อโน้ตโทรศัพท์สำหรับพักผ่อนความราโอย่าง

ส่วนต่าง ๆ ของรีโมทคอนโทรล


DVD-C500



DVD-C550




DVD-C550K




D. ชื่อ端子ในปั๊มระบบเสียง (แอมป์ลิฟาย 2 ชั้นเนล, แอมป์ลิฟายที่สนับสนุนระบบเสียงแบบ ดอลบีดิจิตอล, MPEG2 หรือ DTS)

- ใช้สายเสียง (เชื่อมต่อของเสียง AUDIO (เสียงและขาว) OUT หรือ 5.1 CH (หน้าซ้าย-ขวา) ที่แผงด้านหลังของเครื่องเสียง DVD ไปยังช่องเสียง AUDIO (เสียงและขาว) IN ของแอมป์ลิฟาย. ของเสียงเสียงดิจิตอลใช้สาย Dolby Digital Out (ไม่ในไฟ) ให้เชื่อมต่อของเสียง DIGITAL AUDIO OUT (COAXIAL) ที่ด้านหลังของเครื่องเสียง DVD ไปยังช่องเสียง DIGITAL AUDIO IN (COAXIAL) ของแอมป์ลิฟาย
- ใช้สายสัญญาณวิดีโอ เชื่อมต่อของเสียงเล่น VIDEO, COMPONENT OUT ที่ด้านหลังของเครื่องเสียง DVD ไปยังช่องเสียง VIDEO, COMPONENT IN ของโทรทัศน์ของคุณ.
- เปิดเครื่องเสียง DVD, โทรทัศน์ และแอมป์ลิฟาย
- กดปุ่มเลือกสัญญาณเข้าบันทุมอโนลิฟาย เพื่อเลือก external input <สัญญาณเข้าภายนอก> เพื่อที่จะฟังเสียงจากเครื่องเสียง DVD อ่านคู่มือที่แนบมาพร้อมกับพัฟฟ์ของคุณ (เพื่อตั้งค่าสัญญาณเสียงของแอมป์ลิฟาย



E. การเชื่อมต่อห้องแอมป์ลิฟายเครื่องเสียงแบบ 5.1 ชั้นแนล (DVD-C550K)

- ใช้สายเสียง (เชื่อมต่อของเสียง AUDIO (เสียงและขาว) OUT 5.1 CH (หน้าซ้าย-ขวา) ที่แผงด้านหลัง ของเครื่องเสียง DVD ไปยังช่องเสียง AUDIO (เสียงและขาว) IN ของโทรทัศน์.)
- ใช้สายสัญญาณวิดีโอ เชื่อมต่อของเสียงเล่น VIDEO, COMPONENT OUT ที่ด้านหลังของเครื่องเสียง DVD ไปยังช่องเสียงเสียง VIDEO, COMPONENT IN ของโทรทัศน์ของคุณ.
- เปิดเครื่องเสียง DVD, โทรทัศน์ และแอมป์ลิฟาย
- กดปุ่มเลือกสัญญาณเข้าบันทุมอโนลิฟาย เพื่อเลือก external input <สัญญาณเข้าภายนอก> เพื่อที่จะฟังเสียงจากเครื่องเสียง DVD อ่านคู่มือที่แนบมาพร้อมกับพัฟฟ์ของคุณ (เพื่อตั้งค่าสัญญาณเสียงของแอมป์ลิฟาย



การทำงานพื้นฐาน

การเล่นแผ่นดิสก์

ก่อนเล่น

- เปิดโทรศัพท์ของคุณ และตั้งค่าให้ใช้ัญญาณวิดีโอดำเนินการกดปุ่ม TV/VIDEOบนรีโมทคอนโทรลของโทรศัพท์.
- ถ้าคุณต้องรับเสียงภาษาไทย ให้เปิดระบบเสียงของคุณและเลือกสัญญาณเสียงเข้าที่ถูกต้อง.

หลังจากที่สัญญาณเครื่องเสียงแล้ว ในครั้งแรกคือกดปุ่ม POWER ของ DVD หน้าจอจะปรากฏขึ้น : ถ้าคุณต้องรับเสียงภาษาไทยให้กดปุ่ม **A/V** นาน กดปุ่ม **ENTER**. (หน้าจอจะเปลี่ยนไปตามภาษาที่ใช้งานอาจเปลี่ยนแปลงไปตามครั้งที่คุณเปิดหรือปิดเครื่อง) ถ้าคุณไม่ได้ตั้งภาษาไว้ ภาษาที่ใช้งานอาจเปลี่ยนแปลงไปตามครั้งที่คุณเปิดหรือปิดเครื่อง ตั้งแต่ที่ ให้แน่ใจว่าคุณได้เลือกภาษาที่คุณต้องการใช้ หลังจากที่เลือกภาษาของเมนูแล้ว คุณสามารถเปลี่ยนแปลง ภาษาได้โดยกดปุ่ม **■/▶** ที่แผงด้านหน้าของเครื่องเสียง ค้างไว้เป็นเวลาหากกว่า 5 วินาที ในขณะที่ไม่ได้ใช้แผ่นดิสก์ไว้ในเครื่อง จากนั้นพิมพ์ค่าคง **SELECT MENU LANGUAGE** จะปรากฏขึ้นอีกครั้ง ซึ่งคุณสามารถเรียกภาษาที่คุณเลือกใช้ได้

การใช้ฟังก์ชัน Search และ Skip

ระหว่างการเล่น คุณสามารถดักท่าผ่านแต่ละบท หรือแทรกได้อ่ายาวๆ หรือใช้ฟังก์ชันขั้น เพื่อกระโดดไปยังบทต่อไปได้

การค้นหาบท หรือแทรก

ระหว่างการเล่น กดปุ่ม **SEARCH (◀◀ หรือ ▶▶)** บนรีโมทคอนโทรลเป็นเวลานานกว่า 1 วินาที

DVD	2X, 4X, 8X, 16X, 32X
CD	2X, 4X, 8X, 16X, 32X
VCD	4X, 8X,

หมายเหตุ

- คุณสามารถใช้ฟังก์ชันนี้ได้เมื่อคุณต้องการดูตัวอย่างความงาม รีวิว หรือเรียนรู้ในการเล่น.
- คุณจะไม่ได้ยินเสียงในระหว่างโหมดการค้นหา (ยกเว้น CD).

การข้ามแทรก

ระหว่างการเล่น กดปุ่ม (**◀◀ หรือ ▶▶**).

- ในขณะที่กำลังเล่น DVD ถ้าคุณกดปุ่ม **Skip (▶▶)** เครื่องจะเล่นข้ามไปยังบทต่อไป ถ้าคุณกดปุ่ม **Skip (◀◀)** เครื่องจะข้ามไปยังจุดเริ่มต้นของบท การกดเพิ่มอีกครั้ง จะเลื่อนไปยังจุดเริ่มต้นของบทก่อนหน้า
- ในขณะที่กำลังเล่น VCD ถ้าคุณกดปุ่ม **Skip (▶▶)** เครื่องจะข้ามไปเล่นแทรกถัดไป ถ้าคุณกดปุ่ม **Skip (◀◀)** เครื่องจะเริ่มเล่นยังจุดเริ่มต้นของแทรก การกดเพิ่มอีกครั้ง จะเลื่อนไปยังจุดเริ่มต้นของแทรกก่อนหน้า
- ถ้าแทรกมีความยาวเกิน 15 นาทีในขณะที่กำลังเล่น VCD และ คุณกดปุ่ม **▶▶** เครื่องจะถอยหลังไป5นาที

การใช้ฟังก์ชัน Display

ในขณะที่กำลังเล่น DVD/VCD/MPEG4

1. ระหว่างการเล่น กดปุ่ม **TOOLS** บนรีโมทคอนโทรล
2. กดปุ่ม **▲/▼** เพื่อเลือกรายการที่ต้องการ.
3. กดปุ่ม **◀▶** เพื่อทั่วไปการต่อตัวที่ต้องการ.
4. ในกรณีที่ต้องการหายไป กดปุ่ม **TOOLS** อีกครั้ง

ฟังก์ชันเมื่อใช้ฟังก์ชันแสดงผล (Display) ถูกแสดงในตารางด้านล่าง:

	ในการเข้าใช้งานคำบรรยายที่ต้องการ เมื่อมีภาษาพยัญชนะแต่บุคคลว่าหนึ่งเรื่อง ตัวอย่างเช่น ถ้าภาษาในหนังสือภาษาไทยตั้งแต่ DVD มากกว่าหนึ่งเรื่องของภาษาตั้งแต่ละเรื่องจะแสดง เช่น
	แผ่น DVD ส่วนมากจะถูกนับที่ 1 ไว้เป็นบท เพื่อที่จะได้สามารถค้นหาและเลื่อนไปยัง ส่วนที่คุณต้องการซึ่งต้องตั้งค่าให้ต่อไปนี้
	อนุญาตให้เล่นภาษาพยัญชนะใดๆ ที่ต้องการคุณต้องป้อนเวลาเพิ่มเติมเพื่อเป็นค่าอ้างอิง ฟังก์ชันการค้นหาด้วยเวลาไม่ทำงานบนแผ่นดิจิตอล บันทึก
	หมายถึงภาษาของงานเดิมเริ่ง ให้เวลาอย่างช่วงเวลาที่ต้องการคุณต้องป้อนเวลาเพิ่มเติมเพื่อเป็นค่าอ้างอิง แผ่นดิจิตอล DVD สามารถช่วยตัดสินใจได้ถึง 8 ภาษา
	ความภาษาที่มีอยู่ในหนังสือที่ต้องการ คุณสามารถเลือกภาษาของคำบรรยาย หรือหากคุณไม่ต้องการคุณสามารถตั้งค่าให้แสดงหน้าจอได้ แผ่นดิจิตอล DVD สามารถคิดคำบรรยายที่ต้องการได้ถึง 32 ภาษา
	ฟังก์ชันบันทุมุมของ EZ ใช้เพื่อเปลี่ยนอัตราส่วนภาพใน DVD.
	ฟังก์ชัน ZOOM ใช้เพื่อเปลี่ยนอัตราส่วนภาพ DVD
	เพื่อเข้าใช้งานฟังก์ชัน Angle ที่ต้องการ ติสก์ DVD บางแผ่นมีฟังก์ชัน Angle มาจากว่าภาษาอื่นๆ ฟังก์ชัน Bookmark ช่วยให้คุณสามารถค้นหาแทรคหรือบทจาก DVD หรือ VCD ได้โดยง่ายและรวดเร็ว (ปั๊มนูน)

การใช้เมนู Disc และ Title Menu

ระหว่างการเล่นแผ่นดิสก์ DVD ให้กดปุ่ม **DISC MENU/TITLE MENU** บนรีโมท คอนโทรล

หมายเหตุ

- ขึ้นอยู่กับแผ่นดิสก์ เมนูแผ่น <Disc Menu>/ เมนูหนัง <Title Menu> อาจไม่เท่ากัน
- มองจากนี้ คุณสามารถใช้ เมนูแผ่น <Disc Menu> โดยใช้ปุ่ม **DISC MENU** บนรีโมทคอนโทรลต่อไป
- เมนูหนัง <Title Menu> จะแสดงเฉพาะเมื่อมีภาษาพยัญชนะตั้งแต่ 2 เรื่องขึ้นไปอยู่ในแผ่นดิสก์เท่านั้น

เล่นซ้ำ

เล่นซ้ำแทรค บท เรื่อง ส่วนที่เลือก (A-B) หรือทั้งแผ่นดิสก์.

ในขณะที่กำลังเล่น DVD/VCD

1. กดปุ่ม **REPEAT** บนรีโมทคอนโทรล หน้าจอ Repeat จะแสดงดังนี้
2. กดปุ่ม **REPEAT** หรือ **▲/▼** เพื่อเปลี่ยนโหมดการเล่น. DVD จะเล่นซ้ำที่ลับหน้าเรื่อง.
 - Chapter (บท) : เล่นซ้ำบทที่กำลังเล่นอยู่

- Title (เรื่อง) : เล่นซ้ำเรื่องที่กำลังเล่นอยู่
- ปีต

การใช้ฟังก์ชัน A-B Repeat

- 1 ระหว่างการเล่น กดปุ่ม **REPEAT A-B** บนรีโมทคอนโทรล
2. กดปุ่ม **REPEAT A-B** ที่จุดที่คุณต้องการให้การเล่นซ้ำหยุด (A).
3. กดปุ่ม **REPEAT A-B** ที่จุดที่คุณต้องการให้การเล่นซ้ำหยุด (B).

2. ในการกลับไปเล่นตามปกติ ให้กดปุ่ม **REPEAT A-B** จนกว่าหน้าจอจะแสดงผลเล่นซ้ำ : ปิด (Off)

หมายเหตุ

- เล่นซ้ำ A-B ช่วยให้คุณตั้งค่าจุด (B) โดยตรงหลังจากที่คุณตั้งค่าจุด (A).
- ชั้นอยู่กับแผ่นดิสก์ พังก์ชันการเล่นซ้ำ อาจไม่ทำงาน

เล่นแบบช้า

คุณสมบัตินี้ช่วยให้คุณเล่นซ้ำโดยใช้ความเร็วลดลงในจากที่ประกอบด้วย ที่พ้า การเดินรำ การเล่นเครื่องดนตรีฯลฯ เพื่อคุณจะได้ น้ำเสียงที่ดีขึ้น สำหรับศิลปินเหล่านี้โดยยังคงอิทธิพลมากขึ้น

ในขณะที่กำลังเล่น DVD

1. ระหว่างการเล่น กดปุ่ม **PAUSE (II)**.
2. กดปุ่ม **SEARCH (◀▶)** ค้างไว้ เพื่อเลือกความเร็ว การเล่นจะเร็ว 1/2, 1/4, 1/8 และ 1/16 of เท่าของความเร็วปกติในระ ทว่าที่เล่นโดย PAUSE

ฟังก์ชันชั้นสูง

การปรับอัตราส่วนภาพ (มุมมอง EZ)

ในการเล่นโดยใช้อัตราส่วนภาพ (DVD)

1. ระหว่างการเล่น กดปุ่ม **EZ VIEW** บนรีโมทคอนโทรล
2. กดปุ่ม **EZ VIEW** หรือ **▲/▼** เพื่อเลือกขนาดของแผ่น แล้วตั้งค่าที่คุณต้องการ บนรีโมทคอนโทรลจะแสดงผลในรูปแบบเปลี่ยนแปลง สำหรับภาพที่คุณต้องการที่มีการเปลี่ยนแปลง
3. กดปุ่ม ออก **EXIT** เพื่อออกจากมุมมอง EZ.

สำคัญสำหรับใช้โทรศัพท์มือถือ 16:9

สำหรับแผ่นดิสก์ที่มีอัตราส่วนภาพ 16:9

- Wide Screen
- Screen Fit
- Zoom Fit

สำหรับแผ่นดิสก์ที่มีอัตราส่วนภาพ 4:3

- Normal Wide
- Screen Fit
- Zoom Fit
- Vertical Fit

สำคัญสำหรับใช้โทรศัพท์มือถือ 4:3

สำหรับแผ่นดิสก์ที่มีอัตราส่วนภาพ 4:3

- 4:3 Letter Box
- 4:3 Pan Scan
- Screen Fit
- Zoom Fit
- Normal Screen
- Screen Fit
- Zoom Fit

หมายเหตุ

ฟังก์ชันอาจมีการตั้งค่าจากผู้ผลิตของแผ่นดิสก์

การเลือกภาษาของเสียงพากย์

คุณสามารถเลือกภาษาของเสียงพากย์ที่ต้องการได้อีก 1 ภาษาเพิ่มเติมด้วยปุ่ม AUDIO การใช้ปุ่ม AUDIO (DVD/VCD/MPEG4)

1. ระหว่างการเล่น กดปุ่ม AUDIO. เมื่อเลือกภาษาของเสียงโดยกดปุ่ม เสียง AUDIO หรือ ▲/▼.
 - อาจงเสียงพากย์ จะเปลี่ยนแทนกันทุกครั้งที่กดปุ่ม
2. ใน การลบไฟล์ ให้กดปุ่ม EXIT

หมายเหตุ

- พังกันชั้นขึ้นอยู่กับภาษาของเสียงพากย์ที่มีการเข้ารหัสไว้บันทึกดิสก์ และอาจไม่ทำงาน
- แผ่นดิสก์ DVD สามารถสื่อถึง 8 ภาษา

การเลือกภาษาของคำบรรยาย

คุณสามารถเลือกคำบรรยายที่ต้องการได้อีก 1 ภาษาเพิ่มเติมด้วยปุ่ม SUBTITLE.

การใช้ปุ่ม SUBTITLE (DVD/MPEG4)

1. ระหว่างการเล่น กดปุ่ม SUBTITLE.
2. กดปุ่ม SUBTITLE หรือ ▲/▼ เพื่อเลือกภาษา แตะลงที่คุณกดปุ่ม คำบรรยาย SUBTITLE หรือ ▲/▼ ภาษาจะเปลี่ยนแปลง.
3. ใน การลบไฟล์ ให้กดปุ่ม EXIT

หมายเหตุ

- ภาษาของคำบรรยายจะเปลี่ยนตัวหัวข้อ.
- คุณลองเปลี่ยนคำบรรยายที่ต้องการในเมนู Disc Menu ของแผ่นดิสก์ กดปุ่ม DISC MENU
- พังกันชั้นขึ้นอยู่กับว่ามีคำบรรยายให้มีการเข้ารหัสไว้บันทึกดิสก์ และ อาจไม่ทำงานในแผ่น DVD ทุกแผ่น
- แผ่นดิสก์ DVD สามารถสื่อถึง 32 ภาษา

การเปลี่ยนมุมกล้อง

เมื่อแผ่น DVD ประกอบด้วยมุมกล้องหลายมุมในจักษุของคุณสามารถใช้ปุ่มชั้น ANGLE ได้.

การใช้ปุ่มชั้น ANGLE (DVD)

ถ้าแผ่นดิสก์ประกอบด้วยมุมกล้องหลายมุม คำว่า ANGLE จะปรากฏหน้าจอ

1. ระหว่างการเล่น หรือขณะที่อยู่ในหน้าจอหลัก ให้กดปุ่ม TOOLS บนรีโมทคอนโทรล
2. กดปุ่ม ▲/▼ เพื่อเลือก กดปุ่ม ◀/▶ หรือกด ภาษาที่ชื่อที่บันทึกหมายเลขอื่นๆ บนรีโมทคอนโทรล เพื่อเลือกมุมที่ต้องการ

การใช้ปุ่มชั้น Bookmark

คุณสมบัตินี้อนุญาตให้คุณทำที่คั่นส่วนของ DVD หรือ VCD เพื่อที่คุณจะ สามารถค้นหา ส่วนนี้ในภายหลังได้อย่างรวดเร็ว

การใช้ปุ่มชั้น Bookmark (DVD/VCD)

1. ระหว่างการเล่น หรือขณะที่อยู่ในหน้าจอหลัก คำว่า MARKER ให้กดปุ่ม MARKER บนรีโมทคอนโทรล
2. เมื่อปุ่มปิงอุปกรณ์ที่คุณต้องการทำเครื่องหมาย กดปุ่ม ▲/▼ หรือ ◀/▶ จากนั้นกดปุ่ม MARKER คุณสามารถทำเครื่องหมายในแผ่นดิสก์ได้สูงสุด 12 จุด

หมายเหตุ

- ชื่อยูกับแผ่นดิสก์ ปุ่มชั้น Bookmark อาจไม่ทำงาน

การเรียกจากที่ทำเครื่องหมายไว้

1. ระหว่างการเล่น กดปุ่ม MARKER บนรีโมทคอนโทรล
2. กดปุ่ม ▲/▼ หรือ ◀/▶ เพื่อเลือกจากที่ทำเครื่องหมายไว้
3. กดปุ่ม PLAY (▶) เพื่อเข้าไปยังจุดที่ทำเครื่องหมายไว้

การลบ Bookmark

1. ระหว่างการเล่น กดปุ่ม MARKER บนรีโมทคอนโทรล
2. กดปุ่ม ▲/▼ หรือ ◀/▶ เพื่อเลือกหมายเลขอื่นที่คุณต้องการลบ
3. กดปุ่ม ENTER เพื่อลบหมายเลขอื่น

การใช้ฟังก์ชัน Zoom

การใช้ฟังก์ชัน Zoom (DVD/VCD)

1. ระหว่างการเล่น หรือขณะที่อยู่ในโหมดดูวิดีโอ ให้กดปุ่ม TOOLS หรือ ZOOM บนรีโมทคอนโทรล
2. กดปุ่ม ▲/▼ เพื่อเลือก จากนั้นกดปุ่ม ENTER เพื่อเลือก จากนั้นกดปุ่ม ENTER เพื่อซูมขยายในระดับ X1, X2, X3, X4.

คลิปเมนูสำหรับ MP3/WMA/ JPEG/MPEG4/CD เพลง

CD เพลง หรือแผ่นดิสก์ที่มีไฟล์ MP3/WMA/JPEG ประกอบด้วยเพลง และ/หรือภาพค้างๆ สามารถอุปกรณ์ไฟล์เดียวได้ ดังนั้น ด้วยการใส่ไฟล์ลงในไฟล์ เดียวค้างๆ นั้น เมื่อเปิดก็สามารถพิเศษ化ได้ เช่น สามารถพิเศษ化ไฟล์ลงในไฟล์เดียวแล้ว ปฎิบัติตามขั้นตอนดังนี้ :

1. เปิดตัวความผ่านเพื่อตั้งค่าไฟล์ลงในไฟล์เดียว
2. ปิดค่าตัด และแนบไฟล์เดียวลง (Parent Folder Menu) จะปรากฏชื่อ (ภาษาและสังกัดของไฟล์เดียวที่ตั้งค่าไว้) ไฟล์เดียวที่ตั้งค่าไว้เป็นไฟล์เดียว (Peer)
3. กดปุ่ม ◀/▶ เพื่อเลือกไฟล์เดียวลง (Parent) ในการเลือกของคุณ แล้วกด ENTER. จุดประสงค์จะเป็นไฟล์เดียวที่ตั้งค่าไว้เป็นไฟล์เดียว (Peer) เก็บไฟล์เดียวที่เป็นไฟล์เดียวที่ตั้งค่าไว้ (Peer) ไว้ในไฟล์เดียวลง (Parent).



การเลือกไฟล์เดอร์

คุณสามารถเลือกไฟล์เดอร์ได้ทั้งในโหมด Stop หรือ Play

- ในการเลือกไฟล์เดอร์
 - กดปุ่ม RETURN เพื่อไปยังไฟล์เดอร์แม่ หรือกดปุ่ม ▲/▼ เพื่อเลือก ".." และกด ENTER เพื่อไปยังไฟล์เดอร์แม่
- ในการเลือกไฟล์เดอร์
 - กดปุ่ม ▲/▼ เพื่อเลือกไฟล์เดอร์ที่ต้องการจากนั้นกด ENTER
- ในการเลือกไฟล์เดอร์
 - กดปุ่ม ▲/▼ เพื่อเลือกไฟล์เดอร์ที่ต้องการ เพื่อเลือก ENTER

การเล่น MP3/WMA/CD เพลง

1. เปิดตัวความผ่านเพื่อตั้งค่า วางแผนดิสก์ลงบนภาค ปิดค่าตัด
2. กดปุ่ม ◀/▶ เพื่อเลือก เมนู เพลง (Music) จากนั้นกดปุ่ม ENTER. กดปุ่ม ▲/▼ เพื่อเลือก จากนั้นกดปุ่ม ENTER. กดปุ่ม ▲/▼ เพื่อเลือกไฟล์เพลง กด ENTER เพื่อเริ่มเล่นไฟล์เพลง

การเล่นซ้ำ/สูม

กดคุณ REPEAT เพื่อเปลี่ยนโหมดการเล่น ซึ่งจะมีโหมด 4 โหมดได้แก่ Off, Track, Folder และ Random.

- Off <ปิด> (==): การเล่นปกติ
- Track <แทร็ค> (□): เล่นไฟล์ปัจจุบันซ้ำ
- Folder <แฟ้ม> (■): เล่นไฟล์เดียวกับปัจจุบันซ้ำ
- Random <การเล่นสุ่ม> (△): ไฟล์ในแฟ้มสุ่มๆ กัน

ในการเล่นต่อคอมปิวเตอร์ ให้กดคุณ REPEAT จะกว่าหน้าจอจะแสดงผลเล่นซ้ำ : ปิด (Off)

ไฟล์ MP3/WMA บน CD-R

เมื่อถูกต้องไฟล์ MP3 หรือ WMA ไว้บนแผ่น CD-R โปรดคำนึงถึงสิ่งต่อไปนี้

- ไฟล์ MP3 หรือ WMA ของคุณควรเป็นรูปแบบ ISO 9660 หรือ JOLIET ไฟล์MP3หรือ WMA รูปแบบ ISO 9660 และ Joliet นั้นใช้งานได้กับระบบ DOS และ Windows ของ Microsoft และกับระบบMacของ Apple รูปแบบนี้เป็นที่นิยมที่ขั้นตอนมากที่สุด
- เมื่อเลือกไฟล์ MP3 หรือ WMA อย่าใช้ตัวอักษรที่ 8 ตัว และให้ป้อน “mp3, wma” เป็นภาษา ถูกของไฟล์ที่ต่อไปนี้ Title.mp3 หรือ Title.wma เมื่อต้องป้อนให้แนบไว้จากไฟล์ตัวอักษร 8 ตัวหัวใจนี้ยกเว้น ไม่ว่าข้อความภาษาใดที่แนบให้กับไฟล์เดียวจากไฟล์ตัวอักษรที่ต่อไปนี้จะต้องมีรูปแบบ (.//.=+).
- ใช้อัตราการถ่ายโอนการขยายขนาดอย่างต่อเนื่อง 128Kbps (เมื่อบันทึกไฟล์ MP3) โดยที่รูปแบบแล้ว คุณภาพเสียงของไฟล์ MP3 นั้นขึ้นอยู่กับอัตราการถ่ายโอนภาษา/ขยายขนาดที่คุณเลือกใช้ การที่จะให้ได้รูปแบบที่ CD ต้องใช้ตัวถ่ายภาษาสุ่มน้ำเล็กๆ/ตัวจัด秩 ซึ่งมีการแปลงเป็นรูปแบบ MP3 อ่านต่ออย่างต่อเนื่อง 128Kbps ทั้งนี้ ทั้งนี้ 160Kbps อย่างไรก็ตาม การเลือกอัตราที่สูงกว่า เช่น 192Kbps นั้นให้ได้เสียงมีคุณภาพดีขึ้น ในทางตรงกันข้าม ไฟล์ที่มีอัตราการขยายขนาดต่ำกว่า 128Kbps จะไม่สามารถเล่นได้อย่างเหมาะสม
- ใช้อัตราการถ่ายโอนการขยายขนาดอย่างต่อเนื่อง 64Kbps (เมื่อบันทึกไฟล์ WMA) โดยที่รูปแบบแล้ว คุณภาพเสียงของไฟล์ WMA นั้นขึ้นอยู่กับอัตราการถ่ายโอนภาษา/ขยายขนาดที่คุณเลือกใช้ การที่จะให้ได้รูปแบบที่ CD ต้องใช้ตัวถ่ายภาษาสุ่มน้ำเล็กๆ/ตัวจัด秩 ซึ่งมีการแปลงเป็นรูปแบบ WMA อ่านต่ออย่างต่อเนื่อง 64Kbps จงหาก ทั้งนี้ 192Kbps ไฟล์ที่มีอัตราการขยายขนาดต่ำกว่า 64Kbps หรือสูงกว่า 192Kbps จะไม่สามารถเล่นได้ถูกต้อง
- อย่างที่สองของไฟล์ MP3 ที่มีการบันทึกของตัวเอง ไฟล์ “ที่ไม่ใช่ไฟล์ซึ่งมีการบันทึกของตัวเอง” ไฟล์เหล่านี้จะถูกลบโดยไฟล์ที่ต่อไปนี้ ไฟล์ “ไฟล์ซึ่งมีการบันทึกของตัวเอง” ต่อไปนี้ Windows Media (เครื่องหมายการค้าจดทะเบียนของ Microsoft Inc) และ SDMI (เครื่องหมายการค้าจดทะเบียนของ SDMI Foundation) คุณไม่สามารถคัดลอกไฟล์เหล่านี้ได้
- **สำลัก:** ค่าแนะนำต่อไปนี้ ไม่ได้เป็นเครื่องบ่งบอกว่าค่าที่เริ่มต้น DVD จะเล่นไฟล์ MP3 ได้ หรือบันทึกคุณภาพเสียงที่ต้องไฟล์ คุณควรทราบว่า เทคโนโลยีนี้อาจถูก และวิธีการบันทึกไฟล์ MP3 บนแผ่น CD-R นั้นทำให้ไม่สามารถเล่นไฟล์เหล่านี้เครื่องเล่น DVD ของคุณได้ (ในบางกรณีจะได้เสียงที่มีคุณภาพลดลง หรือเครื่องเล่นไม่สามารถรับรู้ไฟล์ได้)
- เครื่องเล่นนี้ สามารถเล่นไฟล์ได้สูงสุด 500 ไฟล์ และไฟล์เดียวได้ 500 ไฟล์เดียวต่อแผ่น

เล่นไฟล์ MPEG 4

ไฟล์ซึ่งสามารถเล่น MPEG4

- ไฟล์ AVI ใช้เพื่อเก็บข้อมูลเสียงและภาพ เฉพาะไฟล์รูปแบบ AVI ที่มีนามสกุล “.avi” เท่านั้นที่สามารถเล่นได้
1. เปิดค่าความผันผวนติดตั้ง วางผ่านติดตั้งลงขนาด ปิดค่า.
 2. กดคุณ ▲/▶ เพื่อเลือก เม뉴 วิดีโอ (Video) จากนั้นกดปุ่ม ENTER. กดคุณ ▲/▼ เพื่อเลือกไฟล์ avi (DivX/Xvid) จากนั้นกดคุณ ENTER. กดคุณ ▲/▼ จากนั้นกดคุณ ENTER

เล่นซ้ำ

1. กดคุณ REPEAT จากนั้นกดปุ่ม ▲/▼ หรือ ENTER เพื่อเปลี่ยนโหมดการเล่น ซึ่งจะมีโหมด 3 โหมดได้แก่ Off, Title, Folder.
 - Folder <แฟ้ม>: เล่นไฟล์เดียวปัจจุบันซ้ำ
 - Title <เรื่อง>: เล่นซ้ำเรื่องที่กำลังเล่นอยู่
2. ระหว่างการเล่น กดคุณ REPEAT A-B บนรีโมทคอนโทรล
3. กดคุณ REPEAT A-B ที่ต้องต้องการให้การเล่นซ้ำหยุด (A).
4. กดคุณ REPEAT A-B ที่ต้องต้องการให้การเล่นซ้ำหยุด (B).
 - ในการกลับไปเล่นตามปกติ ให้กดคุณ REPEAT A-B จนกว่าหน้าจอจะแสดงผลเล่นซ้ำ : ปิด (Off)

หมายเหตุ

- เล่นซ้ำ A-B ช่วยให้คุณตั้งค่าจุด (B) โดยตรงหลังจากที่คุณตั้งค่าจุด (A).

ค่าอิหม่าฟังก์ชัน MPEG4

ฟังก์ชัน	ค่าอิหม่า
ข้าม (◀◀ หรือ ▶▶)	ระหว่างการเล่น กดปุ่ม ▲◀◀ หรือ ▶▶ เพื่อไปยังแทร็คต่อไปหรือก่อนหน้า
ค้นหา (◀◀ หรือ ▶▶)	ระหว่างการเล่น กดปุ่ม SEARCH (◀◀ หรือ ▶▶) และกดอีกครั้ง เพื่อค้นหาด้วยความเร็วที่สูงขึ้น ใช้ในการค้นหาในไฟล์ AVI ด้วย ความเร็วที่สูงขึ้น (2X, 4X, 8X, 16X, 32X)
เลื่อนภาพช้า	ใช้ในการหันหางไฟล์ AVI ด้วยความเร็ว ที่ต่ำลง. (1/2, 1/4, 1/8, 1/16)
ค้นหา	X1/X2/X3/X4 ปกติ ตามลักษณะ

- พงก์ชั้นเพล่าหน้าจอไม่ทำงาน หันซึ่งอยู่กับไฟล์ MPEG4

ไฟล์ AVI บน CD-R

เครื่องเล่นสามารถเล่นรูปแบบการบันทึกวิดีโอต่อไปนี้ภายในไฟล์รูปแบบ AVI ได้:

- เมื่อไฟล์ DivX 3.11
- เมื่อไฟล์ DivX 4 (ที่ใช้ไฟล์ MPEG-4 ธรรมชาติ)
- เมื่อไฟล์ DivX 5 (ไฟล์ไฟล์ MPEG-4 ธรรมชาติ บวกกับคุณสมบัติเพิ่มเติม เช่น เสียงพร้อมตัวพากย์ นอกจากนี้ Qpel และ GMC ด้วย)
- เมื่อไฟล์ที่สอดคล้องกับ Xvid MPEG-4.

DVD-RW & DVD+R

รูปแบบที่รองรับสำหรับไฟล์ DivX:

- รูปแบบ DivX พื้นฐาน DivX3.11 / 4.12/ 5.x
- Xvid (MPEG-4 compliant video codec) และ DivX Pro

รูปแบบไฟล์ : *.avi, *.div, *.divx.

DivX5
720 x 480 @30fps
720 x 576 @25fps
: อัตราบิตสูงสุด : 4Mbps

ข้อความเดือนที่อาจเกิดขึ้นระหว่างการพยายามเล่นไฟล์ DivX ได้แก่:

1. ไม่ได้รับอนุญาต
 - ไฟล์ซึ่งร่วงตัวเอง
2. Codec ไม่รองรับ
 - ไฟล์ที่มีประเพณี, เวอร์ชันของ Codec (เช่น MP4, AFS และ codec อื่นๆ ที่ไม่ถูกอนุญาต)
 - ไม่ได้รับการรองรับจากเครื่องเล่นนี้
3. ความละเอียดไม่รองรับ
 - ไม่รองรับไฟล์ที่มีความละเอียดสูงกว่าข้อกำหนดเฉพาะของเครื่องเล่น.

หมายเหตุ

- ความละเอียดที่สามารถรองรับ DVD-C500/C550/C550K คือสูงถึง 720 x 480 ที่ 30 เฟรม/ 720 x 576 ที่ 25 เฟรม
- เครื่องเล่นนี้ บันทึกการเขียน CD-R/RW ในมาตรฐาน MPEG4 ที่สอดคล้องกับ รูปแบบ ISO9660

การเล่นไฟล์สื่อโดยใช้คุณสมบัติ USB Host (DVD-C550/DVD-C550K)

คุณสามารถเพลิดเพลินกับไฟล์เสียง เช่น ภาพ ภาพนิ่ง และเสียงดนตรี ที่บันทึกใน เครื่องเล่น MP3, หน่วยความจำ USB หรือกล้องดิจิตอลที่มีคุณภาพเสียงระดับสูงได้ ด้วยการเชื่อมต่ออุปกรณ์สื่อสารกับพอร์ต USB ของเครื่องเล่น DVD กำไรใช้คุณสมบัติ USBHOST

1. ต่ออุปกรณ์ USB ไฟล์เพลง USB ที่ค้างหน้าเครื่อง
2. จัดแสดง เมนู USB (USB Menu) ปรากฏขึ้น กดปุ่ม **</>** เพื่อเลือก เมนู จากนั้นกดปุ่ม **ENTER**.
3. กดปุ่ม **▲/▼** เพื่อเลือกไฟล์ในอุปกรณ์ USB กด **ENTER** เพื่อเปิดไฟล์.

หมายเหตุ

- แต่ละรังสีที่กดปุ่ม USB บนรีโมทคอนโทรล กระบวนการเลือกอุปกรณ์ USB จะประยุกต์ขึ้น.
- “USB” จะปรากฏที่หน้าจอ
- ข้อมูลที่บันทึกไว้จะถูกแสดงตามรายการของคลิป เวลาให้ผลลัพธ์หน้าจอ USB จะใช้งานตามกว่าการใช้แผ่น CD หรือ DVD
- หน้าจอ USB MENU จะประยุกต์หน้าจอที่ไฟล์และลูปไฟฟ้าที่บันทึกไว้
- ค่ามีต่อค่าอุปกรณ์ การกดปุ่ม DVD จะทำให้ค่าตั้งค่าของเมนู USB และไฟล์ลดต่ำลง

การนำอุปกรณ์ USB ออกจากบ่างปลดล็อก

1. กดปุ่ม DVD เพื่อตั้งไฟล์ที่จะแสดงผลลัพธ์ หรือโหมดดีสก์
2. กดปุ่ม STOP (■)
3. ถอดสาย USB ออก

ขั้นตอนหน้า / ถอนยังลัง

ระหว่างการรีบบูต กดปุ่ม (**</>/>>**)

- เมื่อไฟล์ถูกกดปุ่ม **>>>** ไฟล์เมื่อคุณกดปุ่มนี้ ไฟล์ดังไปจะถูกยกเลิก
- เมื่อไฟล์ถูกกดปุ่ม **<<<** ไฟล์เมื่อคุณกดปุ่มนี้ ไฟล์ก่อนหน้าจะถูกยกเลิก

การเล่นอย่างรวดเร็ว

หากต้องการเล่นแผ่นด้วยความเร็วที่สูงขึ้น กด (**<>/>>**) ระหว่างการเล่น

- แต่ละครั้งที่กดคุณปุ่มไปเรื่อยๆ ความเร็วในการเล่นจะเปลี่ยนแปลงดังนี้ : 2X → 4X → 8X → 16X → 32X.

อุปกรณ์ที่สามารถใช้งานร่วมกันได้

1. อุปกรณ์ USB ที่สนับสนุน USB Mass Storage v1.0 (อุปกรณ์ USB ที่ ทำงานเป็นตัวเก็บแบนก์บันทึกอุปกรณ์ใน Windows (2000 ขึ้นไป) โดยไม่ต้องติดตั้งไดรเวอร์เพิ่มเติม)
2. เครื่องเล่น MP: เครื่องเล่น MP3 ประเภท HDD และแฟลช
3. กล้องดิจิตอล: กล้องที่สนับสนุน USB Mass Storage v1.0
 - ก้อนไฟฟ้าที่ทำงานเป็นตัวเก็บแบนก์บันทึกอุปกรณ์ใน Windows (2000 ขึ้นไป) โดย ไม่ต้องติดตั้งไดรเวอร์เพิ่มเติม
4. ไฟฟ้า USB Flash: อุปกรณ์ที่สนับสนุน USB 2.0 หรือ USB 1.1
 - คุณภาพเพื่อความหลากหลายของคุณภาพการเล่นไฟฟ้าอุปกรณ์ ด้วย USB 1.1
5. ตัวควบคุม USB: ตัวควบคุม USB แบบ U ช่อง และตัวควบคุม USB แบบหลายช่อง
 - ตัวควบคุม USB อาจนำไปใช้ร่วมกับส่วนที่บันทึกไว้ในไฟล์ของคุณในเบื้องต้น ผ่านลิ้นชัก
 - หากคุณติดตั้งอุปกรณ์หน่วยความจำหลายช่องในตัวควบคุมไฟฟ้า ช่อง คุณอาจประสบปัญหาได้
6. หากคุณใช้ลักษณะ USB เครื่องงานของไฟฟ้าในอุปกรณ์ USB ตั้งกล่าว
 - ไฟฟ้าสนับสนุน CBI (ควบคุม/ลุก/ชักจังหวะ)
 - ไฟฟ้าสนับสนุนกล้องดิจิตอลที่ใช้ไฟฟ้าเดียว TPI หรือต้องมีการติดตั้ง โปรแกรมเพื่อเขียนต่อคู่กับไฟฟ้า
 - ไฟฟ้าสนับสนุนบุญภรรภ์ที่ใช้ระบบไฟล์แบบ NTFS (สนับสนุนเฉพาะ ระบบไฟล์แบบ FAT 16/32 (ความสามารถจัดสรรไฟล์แบบ 16/32) เท่านั้น)
 - เครื่องเล่น MP3 บางรุ่น อาจไม่ทำงานเมื่อเชื่อมต่อหัวน้ำดิจิตอลกับหัวที่ หันน้ำ ซึ่งอยู่บนหน้าจอดูซึ่งรองรับไฟฟ้า
 - ในส่วนสนับสนุนไฟฟ้า USB HOST (เอสต์ USB) หากเชื่อมต่อ กับ หลอดกันไฟที่ถูกบอนไฟล์ล็อกความโดยใช้ไฟฟ้าโปรแกรมที่ผู้ผู้ดูแลรับ สลากหัวเครื่อง
 - อย่างไรก็ตาม กับไฟล์แบบ MTP (ไฟฟ้าต่อตัวไฟฟ้าในสื่อของบุญภรรภ์) ที่ เปิดไว้งาน วันนี้
 - พึงกันไฟฟ้า USB ของผลิตภัณฑ์ที่ไม่ได้สนับสนุนอุปกรณ์ USB ทั้งหมด

การตัดข้อมูลซีดี (DVD-C550/DVD-C550K)

คุณสมบัติที่ช่วยให้คุณสามารถตัดออกไฟล์เสียงจากตัวไฟล์ USB เป็นรูปแบบ MP3 ได้ เปิดเมนูของแท็บ กวนแบบซีดีเพลง (CD DA) บนหน้าจอ แล้วปั๊บค่าตัด ต่ออุปกรณ์ USB กับช่อง USB ที่ค้างหน้าเครื่องเล่น หน้าจอจะประยุกต์ขึ้น. กดปุ่ม DVD.

1. ในขณะที่เครื่องอยู่ในโหมดดูด้วยกดปุ่ม **TOOLS** เพื่อแสดงหน้าจอ **Ripping**.
2. กดปุ่ม **▲/▼** เพื่อเลือก เพื่อเลือกไฟล์ที่ปรารถนา, จากนั้นกดปุ่ม **ENTER** (ป้อน) เพื่อเลือกไฟล์ทั้งหมดที่ต้องการ.
 - หากต้องการยกเลิกการตัดออกไฟล์ทั้งหมดสำหรับคัดลอก กดปุ่ม ENTER (ป้อน) อีกครั้ง.
3. กดปุ่ม **◀** หรือ **▶** เพื่อเลือก เมนู Ripping เริ่ม จากนั้นกดปุ่ม **ENTER** เมนู Ripping มีหน้าตาดัง ดังนี้:
 - แบบ (เรียบ/ปกติ)
 - บิตเดร็ค กด **ENTER** (ป้อน) เพื่อเปลี่ยน 128kbps → .192kbps → 128kbps...
 - ภาษา ล็อกอิน กด **ENTER** (ป้อน) เพื่อเปลี่ยนระหว่างภาษาปกติ (สูงสุด 4)
 - เลือก - ไม่เลือก กด **ENTER** เพื่อเปลี่ยนจาก Select all (เลือกทั้งหมด) หรือ Select none (ไม่เลือกเลย).
 - เริ่มตัดซ้อม กด **ENTER** (ป้อน) เพื่อริบบั้นของการตัดซ้อม

หมายเหตุ

- เมื่อต้องการยกเลิกการตัดลอกที่ดำเนินการอยู่ ให้กดปุ่ม **ENTER**
- ในการกดปุ่มไปยังหน้าจอ CD DA ให้กดปุ่ม **TOOLS** อีกครั้ง.
- เมื่อการตัดลอกซึ่ดีล็อกของหน้าจอประมวลผล เครื่องจะหยุด ใหม่เดือนโดยอัตโนมัติ
- เลapse แนะนำซีดีเพลง (CD DA) เท่านั้นที่สามารถใช้กับ การตัดข้อมูลได้
- ปุ่ม USB จะไม่ทำงานระหว่างที่คุณอยู่ในเมนู Ripping.
- ไม่สนับสนุนฟังก์ชัน CD Ripping สำหรับอุปกรณ์เครื่องเล่น MP3 บางชนิด

การเล่น CD ภาพ

1. เลือกไฟล์ เครื่องที่ต้องการ.
2. กดปุ่ม **▲/▼** เพื่อเลือกไฟล์ภาพในเมนูคลิป จากนั้นกดปุ่ม **ENTER**

หมายเหตุ

- กดปุ่ม **STOP** เพื่อตั้งไฟล์ไปยังเมนูคลิป
- ในขณะที่กำลังเล่น CD ภาพของไก้ตัก เครื่องจะเล่น จะ ดูภาพโดยตรง โดยไม่ ดูเมนูคลิป

Rotation

- กดปุ่ม **TOOLS** เพื่อเลือก Rotate (หมุน) จากนั้นกดปุ่ม **ENTER**
- แต่ละครั้งที่กดปุ่ม **</>** ภาพจะหมุนตามเข็มนาฬิกาไป 90 องศา
- แต่ละครั้งที่กดปุ่ม **▲** ภาพจะกลับไปยังโอลัฟฟ์ เพื่อแสดงภาพกระจาก
- แต่ละครั้งที่กดปุ่ม **▼** ภาพจะกลับไปยังด้านขวา เพื่อแสดงภาพกระจาก

Zoom

- กดปุ่ม **TOOLS** เพื่อเลือก Zoom (ขยายภาพ) จากนั้นกดปุ่ม **ENTER**
- แต่ละครั้งที่กดปุ่ม **▼** ภาพจะถูกขยายใหญ่ขึ้น ใหม่ชื่อ: X1-X2-X3-X4-X1.

Slide Show

- เมื่อกดปุ่ม Play (เล่น) ที่ไฟล์ Jpg การแสดงผลจะเป็น โหมดเต็มจอและแสดงสไลด์โชว์โดยอัตโนมัติ

หมายเหตุ

- ชื่อนายกับชื่อนางของไฟล์ รูปภาพเวลาในการแสดง ภาพแต่ละภาพจะแตกต่างจากช่วงเวลาที่ตั้งไว้
- ถ้าคุณไม่กดปุ่มใด ๆ ไฟล์จะรีบูตโดยอัตโนมัติ ในเวลา 10 วินาทีตามค่าเริ่มต้น

การเล่น CD ภาพ ส่านรับ HD-JPEG

ต้องต่อสัญญาณ HDMI ความละเอียดควรอยู่ที่ 720p/1080i/ 1080p และ HD-JPEG ควรอยู่ที่โหมด HD.

1. เลือกไฟล์เดอร์ที่ต้องการ
2. กดปุ่ม **▲/▼** เพื่อเลือกไฟล์ภาพในเมนูคลิป จากนั้นกดปุ่ม **ENTER**
 - กดปุ่ม STOP (■) เพื่อกลับไปยังเมนูคลิป
 - ในขณะที่กำลังเล่น CD ภาพของไกด์เก็ต เครื่องจะเล่นจะแสดงภาพ โดยตรง โดยไม่แสดงเมนูคลิป
- **Rotation**
กดปุ่ม **TOOLS** เพื่อเลือก Rotate (หน้าจอ) จากนั้นกดปุ่ม **ENTER** กดปุ่ม **◀/▶** เพื่อหมุนหน้าจอ 90 องศาไปทางซ้าย/ขวา.
- **Skip Picture**
กดปุ่ม **|◀| หรือ |▶|** เพื่อเลือกภาพก่อนหน้าหรือถัดไป
- **Slide Show**
กดปุ่ม **PLAY (▶)** เพื่อเริ่มต้นฟังก์ชัน SLIDE
กดปุ่ม **PAUSE (II)** เพื่อหยุดฟังก์ชัน

หมายเหตุ

- ขึ้นอยู่กับขนาดของไฟล์ ระยะเวลาในการแสดงภาพ แต่ละภาพอาจแสดงได้จากรอบเวลาที่ตั้ง
- ภาพอาจมีผลลัพธ์ในหน้าที่เล็กกว่า ขึ้นอยู่กับขนาดภาพ เมื่อแสดงภาพในโหมด HD-JPEG
- คุณสมบัติ “BD Wise” เป็น “Off” (ปิด) ในกรณีการเล่นไฟล์ภาพ JPEG ที่มีขนาดใหญ่กว่า 750 x 480 พิกเซล

การเล่น MP3-JPEG

คุณสามารถเล่นไฟล์ JPEG โดยใช้เพลงเป็นฉากหลังได้

1. กดปุ่ม **▲/▼** เพื่อเลือกไฟล์ MP3 ในเมนูคลิป จากนั้น กดปุ่ม **ENTER**.
เมื่อดูรายการลับไปที่จุดแสดงผลบน กดปุ่ม **RETURN** หรือ เมนู **MENU**.
2. กดปุ่ม **◀/▶** เพื่อเลือกไฟล์ เมนู รูปปาน (Photo) จากนั้นกดปุ่ม **ENTER**.
กดปุ่ม **▲/▼** เพื่อเลือกไฟล์ JPEG ในเมนูคลิป จากนั้น กดปุ่ม **ENTER**.
- เพลงจะเริ่มในสูญญากาศตอนนั้น
3. กดปุ่ม **Stop** เมื่อคุณต้องการหยุดการเล่น

หมายเหตุ

- MP3 และ JPEG ต้องอยู่ในแผ่นเดียวกัน

แผ่นดิสก์ JPEG บน CD-R

- เผาไฟล์ที่มีนามสกุล “.jpg” และ “.JPEG” เท่านั้นที่สามารถเล่นได้
- ดำเนินไปที่ดีดตัวเดลติค จะใช้เวลาจำนวนมากในการเรียบแบบ และไฟล์ ที่บันทึกไว้ภายในไฟล์อาจไม่สามารถเล่นได้
- เผาไฟล์ JPEG บนแผ่นดิสก์ CD-R ไฟล์ JPEG ในรูปแบบ ISO 9660 หรือ Joliet เท่านั้นที่สามารถเล่นได้
- ไฟล์ของไฟล์ JPEG ไม่สามารถมีความพยายามกัน 8 ตัวอักษรและ ไม่ควรมีซึ่งกันว่าง หรือตัวอักษรพิเศษใดๆ บรรจุอยู่ค. /= +).
- เผาไฟล์ดิสก์ที่มีการซึ้งแบบลัดตัวเลื่อนที่ต้องนึ่งกันเท่านั้น ที่สามารถเล่นได้สำหรับส่วนว่าในแผ่นดิสก์มีตัวเลื่อนที่ต้องนึ่งกันเท่านั้น
- CD ที่นึ่งแผ่นสามารถอ่านได้สูงสุดเพียง 500 ภาพเท่านั้น
- ในขณะที่กำลังเล่น CD ภาพของโกล์ดี้ เพาะไฟล์ JPEG ในไฟล์เดอร์ภาพเท่านั้นที่สามารถเล่นได้
- CD ภาพของโกล์ดี้ :ไฟล์ JPEG ในไฟล์เดอร์ภาพสามารถเล่น ให้โดยอัตโนมัติ
- CD ภาพของโกล์ดี้ : คำศัพท์ต่อการคุกคาม ให้เลือกไฟล์ JPEG ในเมนูคลิป
- CD ภาพของฟูจิ : เค้าโครงต่อการคุกคาม ให้เลือกไฟล์ JPEG ในเมนูคลิป
- CD ภาพของ QSS : เครื่องจะเล่นจากไฟล์ QSS ได้
- ถ้าจำนวนไฟล์แน่นพื้นที่ 1 แผ่นมีมากกว่า 500 ไฟล์ เครื่องจะเล่นจะเล่นไฟล์ JPEG ได้เพียง 500 ไฟล์เท่านั้น
- ถ้าจำนวนไฟล์แน่นพื้นที่ 1 แผ่นมีมากกว่า 500 ไฟล์เดอร์ เครื่องจะเล่นจะเล่นไฟล์ JPEG
ในไฟล์เดอร์ที่เพียง 500 ไฟล์เดอร์เท่านั้น

[10]

ฟังก์ชัน คาราโอเกะ (DVD-C550K)

ฟังก์ชัน คาราโอเกะ

สำคัญการทำงาน

1. ค่าต่อไปนี้เป็นเพียงตัวอย่างเดียว สำหรับ หน้า หรือแบบฟิตฟาย
2. ค่าในโทรศัพท์มือถือ ไม่จำเป็นต้องใช้ MIC เสียงคุณภาพ ฟังก์ชัน karaoke <คาราโอเกะ> ที่สามารถใช้งานได้

Mic Volume and การควบคุมเสียง

1. เล่นแผ่นดิสก์ Karaoke ที่บรรจุเพลงหลักของการฟัง.
 - กดปุ่ม **KARAOKE (V)** จากนั้นกดปุ่ม **▲/▼** หรือเลือก **VOL** (ระดับ เสียง) หรือ **KEY** (กุญแจ) .
2. กดปุ่ม **◀/▶** เพื่อเลือกรายการที่ต้องการ.

หมายเหตุ

- ถ้าคุณต้องการเสียงแท้ (เสียงแหลม หรือเสียงหอน) ในขณะที่ใช้คุณลักษณะ Karaoke ให้ย้ายไมโครโฟนออก จากที่ติดหูของเจ้าของ หรือครอบตัว บลีฟิงของไมโครโฟน หรือล้อโพลจ.
- ในขณะที่ใช้คุณลักษณะ Karaoke ไม่สามารถใช้ไฟล์ MP3, WMA, DTS และ LPCM ทั้งหมด Karaoke จะไม่ทำงาน
- เมื่อไฟล์ที่แนบมาอยู่ ลักษณะติดต่อจะถูกตัดออกจะ ใจท่องงาน
- ลักษณะเสียงไม่เปลี่ยนแปลง จะมาจากลักษณะเสียงของว่าที่เจ้าของเสียง เช่น 5.1CH จะถูกเปลี่ยนเป็นเสียง 2 CH โดยอัตโนมัติ สถานะนี้เป็นสถานะปกติเมื่อเปลี่ยนไปได้ ว่าแต่ละคอมพิวเตอร์ในเครือข่าย

การเปลี่ยนเมนูการตั้งค่า

การใช้เมนูการตั้งค่า

เมนู Setup ช่วยให้คุณปรับแต่งเครื่องเสียง DVD ของคุณ โดยคุณสามารถเลือกภาษา ที่ต้องการใช้, ตั้งค่าระบบต่างๆ ตามที่ต้องการ หรือเปลี่ยนโหมดหดหู่ หรือแม้แต่ปรับแต่งเครื่องเสียงให้ตรงกับชนิดของหน้าจอโทรทัศน์ที่คุณมี.

1. ในขณะที่เครื่องเสียงเปิด คุณลักษณะ **SETUP** กดปุ่ม **MENU** บนรีโมทคอนโทรล. กดปุ่ม **◀/▶** เพื่อเลือก **SETTINGS** (การตั้งค่า) จากนั้นกดปุ่ม **ENTER**
2. กดปุ่ม **▲/▼** เพื่อเลือก **Setup** <การตั้งค่า> จากนั้นกดปุ่ม **▶** หรือ **ENTER**
3. กดปุ่ม **▲/▼** เพื่อเข้าไปในหัวที่ให้หน้าจอการตั้งคุณสมบัติ ตัวๆ. กดปุ่ม **▶** หรือ **ENTER** เพื่อเข้าไปยังคุณสมบัติของ
4. ในการทำให้หน้าจอการตั้งค่าหายไป ให้กดปุ่ม **RETURN** อีกครั้ง

การตั้งค่าตัวเลือกการแสดงผล

ตัวเลือกของการตั้งค่า ดังนี้ ใช้เพื่อให้คุณตั้งค่าฟังก์ชันตัว นาฬิกาแบบต่างๆ ของเครื่องเสียง

1. ในขณะที่เครื่องเสียงเปิด คุณลักษณะ **DISPLAY** กดปุ่ม **MENU** บนรีโมทคอนโทรล. กดปุ่ม **◀/▶** เพื่อเลือก **SETTINGS** (การตั้งค่า) จากนั้นกดปุ่ม **ENTER**
2. กดปุ่ม **▲/▼** เพื่อเลือก **DISPLAY <แสดง ผล>** จากนั้นกดปุ่ม **▶** หรือ **ENTER**.
3. กดปุ่ม **▲/▼** เพื่อเลือกรายการที่ต้องการ จากนั้นกดปุ่ม **▶** หรือ **ENTER**

การตั้งค่า BD Wise

เมื่อเครื่องเล่นเชื่อมต่อเก็บไว้ชิ้นส่วน “BD Wise” คุณสามารถเพลิดเพลินกับคุณภาพสูงสุดของภาพ โดยการตั้งค่าฟังก์ชัน “BD Wise” เป็น “On” (ปิด)

1. ในขณะที่เครื่องเล่นอยู่ในโหมดดูหนัง กดปุ่ม MENU บนรีโมทคอนโทรล. กดปุ่ม **◀/▶** เพื่อเลือก **SETTINGS** (การตั้งค่า) จากนั้นกดปุ่ม **ENTER**
2. กดปุ่ม **▲/▼** เพื่อเลือก **DISPLAY <แสดง ผล>** จากนั้นกดปุ่ม **▶** หรือ **ENTER**.
3. กดปุ่ม **▲/▼** เพื่อเลือก **BD WISE** จากนั้นกดปุ่ม **▶** หรือ **ENTER**
กดปุ่ม **▲/▼** เพื่อเลือก เปิด **<ON>/ปิด <OFF>** จากนั้นกดปุ่ม **ENTER**

หมายเหตุ

- ตัวเลือกนี้สามารถเปลี่ยนแปลงได้เมื่อเชื่อมต่อช่องบันทุณ BD Wise เท่านั้น
- ถ้ามีอยู่ใช้โทรศัพท์ของคุณ เพื่อทราบว่าโทรศัพท์ของคุณสนับสนุนระบบโปรดักซ์ฟิล์มหรือไม่ ถ้ามีการสนับสนุนโปรดักซ์ฟิล์ม ก็ให้ห้ามค่าแนะนำในการตั้งค่าโปรดักซ์ฟิล์มของคุณเมื่อใช้โทรศัพท์ในระบบเมนูของโทรศัพท์นั้น
- ถ้าต้องการให้ตัวเลือก **Video Output <ตัวโดยสารที่ทุกอย่างทุกตัวทั้งหมด>** หันหน้าจอจากจอเดิมให้ได้ ความละเอียดที่ใช้ตัวรับสัญญาณออก HDMI ต้องยกโทรศัพท์หรือโปรดักซ์ฟิล์มที่ต้องอยู่ในระยะเดียวกันของคุณ
- เมื่อความละเอียดสูงเป็นไปได้ในระหว่างที่เล่น อาจใช้ เวลาสองเทึ่งสามวินาทีเพื่อให้ภาพปกติปรับ หายใจ
- หากต้องตั้งค่าความละเอียดสัญญาณออก HDMI เป็น **720p, 1080i** หรือ **1080p** สัญญาณออก HDMI จะให้ คุณภาพของภาพเพิ่มขึ้น
- คุณควรตั้ง “BD Wise” เป็น “Off” (ปิด) ในกรณีการเล่นไฟล์ภาพ JPEG ที่มีขนาดใหญ่กว่า **750 x 480** พิกเซล

① กาง

- ไม่มี (None)
- ใหญ่ (Large)
- เด็ก (Small)

② เสียงจากทาง

- ไม่มี (None)
- ใหญ่ (Large) (ข้างล่างข้างบน)
- เด็ก (Small) (ข้างบนข้างล่าง)

การตั้งค่าภาพ

ลักษณะเสียงทดสอบจะวนไปตามเข็มนาฬิกา เริ่มต้นจากลำโพงหน้า (ซ้าย)
ปรับความสมดุลของช่องเสียงเพื่อให้ลำโพงเสียงออกมาเท่ากันในห้องของท่าน.
หน้า (ซ้าย) → กาง → ข้างขวา → หน้า (ขวา) → รอบทิศทาง (ขวา) → รอบทิศทาง (ซ้าย)

หมายเหตุ

- เมื่อเล่นแผ่นที่มีเสียง MPEG ตามการเลือกบิตสตรีม รับแคบก็เสียงอาจไม่ส่ง สัญญาณเสียงออกโดยที่ไม่รับเครื่องรับ AV
- เมื่อเล่นแผ่นแผ่นดิจิตอล DTS จะไม่มีสัญญาณเสียงนาฬิกาออกออก
- เมื่อ PCM Down sampling <PCM ดาวน์ซэмปลิ่ง> ถูกตั้งค่าเป็น Off <ปิด>
 - แผ่นดิสก์บางแผ่นจะถูกลดลงเป็นเสียงลงผ่านสัญญาณออกดิจิตอล

HDMI

- ถ้าโทรศัพท์ของคุณไม่สามารถใช้งานกับรูปแบบนี้ลัด แขนเหล็กที่บีบขนาดได้ (ดอลบี้ดิจิตอล, DTS, MPEG), คุณควรตั้ง Digital Audio เป็น PCM
- ถ้าโทรศัพท์ของคุณไม่สามารถใช้งานกับอัตราแซมบลิง LPCM ที่เกิน 48kHz ให้ คุณควรตั้ง PCM Down เป็น On

ผลิตภัณฑ์ได้รับการอนุญาตจาก Dolby Laboratories “Dolby” และสัญลักษณ์ D คือ เป็นเครื่องหมายการค้าของ Dolby Laboratories
“DTS” และ “DTS Digital Out” เป็นเครื่องหมายการค้าของ Digital Theater Systems, Inc.

การตั้งค่าตัวเลือกของเสียง

- ค่าเลือกของเสียง อยู่ภายใต้หัวข้อค่าปรับผู้ใช้ แสดงสถานะของเสียงให้ ออคคล้องกับระบบเสียงที่กำลังใช้งานอยู่
1. ในขณะที่เครื่องเล่นอยู่ในโหมดดูหนัง กดปุ่ม MENU บนรีโมทคอนโทรล. กดปุ่ม **◀/▶** เพื่อเลือก **SETTINGS** (การตั้งค่า) จากนั้นกดปุ่ม **ENTER**
 2. กดปุ่ม **▲/▼** เพื่อเลือก **AUDIO <เสียง>** จากนั้นกดปุ่ม **▶** หรือ **ENTER**
 3. กดปุ่ม **▲/▼** เพื่อเลือกการตั้งค่า จากนั้นกดปุ่ม **▶** หรือ **ENTER**.

การตั้งค่าตัวเลือกของเสียง (DVD-C550K)

1. ในขณะที่เครื่องเล่นอยู่ในโหมดดูหนัง กดปุ่ม MENU บนรีโมทคอนโทรล. กดปุ่ม **◀/▶** เพื่อเลือก **SETTINGS** (การตั้งค่า) จากนั้นกดปุ่ม **ENTER**
2. กดปุ่ม **▲/▼** เพื่อเลือก **AUDIO <เสียง>** จากนั้นกดปุ่ม **▶** หรือ **ENTER**
3. กดปุ่ม **▲/▼** เพื่อเลือก **SPEAKER SETUP** (การตั้งค่าลำโพง) จากนั้นกดปุ่ม **▶** หรือ **ENTER**
4. กดปุ่ม **▲/▼/◀/▶** เพื่อเลือกหัวขอต้องการ จากนั้นกดปุ่ม **ENTER** เพื่อตั้งค่าลำโพง

การตั้งค่าต่อไปนี้ : หัวขอ L,R (เด็ก) กากบาท(เด็ก) เสียงรอบทิศทาง(เด็ก). เสียงบนภาคกลาง(เด็ก) ที่จะต้องกับเครื่อง

- ① หัวขอ (FL, FR)
 - ใหญ่ (Large)
 - เด็ก (Small)

กำหนดค่าอีพชันระบบ (System)

1. ในขณะที่เครื่องเล่นอยู่ในโหมดดูหนัง กดปุ่ม MENU บนรีโมทคอนโทรล. กดปุ่ม **◀▶** เพื่อเลือก **SETTINGS** (การตั้งค่า) จากนั้นกดปุ่ม **ENTER**
2. กดปุ่ม **▲▼** เพื่อเลือก **SYSTEM** (ระบบ) จากนั้นกดปุ่ม **▶** หรือ **ENTER**
3. กดปุ่ม **▲▼** เพื่อเลือกรายการที่ต้องการ จากนั้นกดปุ่ม **▶** หรือ **ENTER**

การตั้งค่า Anynet+(HDMI-CEC)

Anynet+ คือฟังก์ชันที่สามารถใช้ไฟฟ้าในห้องเดียวกันได้เช่นเดียวกับเครื่องเสียงที่ต่อเข้ากับเครื่องเสียงโดยใช้สาย HDMI (การตั้งค่าที่ต้องรับ Anynet+ เท่านั้น)

ตัวเลือก Anynet+(HDMI CEC) ช่วยให้คุณตั้งค่าฟังก์ชัน HDMI ของเครื่องเล่นได้ เช่น On (เปิด) เมื่อคุณตั้งค่า DVD C500/C550/C550K กับที่ต้องรับ Anynet+.

1. ในขณะที่เครื่องเล่นอยู่ในโหมดดูหนัง กดปุ่ม MENU บนรีโมทคอนโทรล. กดปุ่ม **◀▶** เพื่อเลือก **SETTINGS** (การตั้งค่า) จากนั้นกดปุ่ม **ENTER**
2. กดปุ่ม **▲▼** เพื่อเลือก **SYSTEM** (ระบบ) จากนั้นกดปุ่ม **▶** หรือ **ENTER**
3. กดปุ่ม **▲▼** เพื่อเลือก **Anynet+(HDMI-CEC)** จากนั้นกดปุ่ม **▶** หรือ **ENTER**
4. เลือก Anynet+(HDMI-CEC) ในที่ “On (เปิด)” ที่เครื่องเล่น DVD ของคุณ จากนั้นกด **ENTER**
5. ตั้งฟังก์ชัน Anynet+ ที่ต้องของคุณ (ดูรายละเอียดในหน้าที่ “วิธีการรับ ข้อมูลเพิ่มเติม”)
 - เมื่อคุณกดปุ่ม Anynet+ ที่รีโมทคอนโทรล เมนู OSD ด้านล่างจะปรากฏขึ้น

หมายเหตุ:

- เมื่อกดปุ่ม **PLAY** (เล่น) ที่เครื่องในขณะที่หนังหรือหน้าจอของทีวีจะเปลี่ยนเป็นหน้าจอสานักงาน
- หากคุณเล่น DVD เมื่อทีวีถูกตั้งค่าให้วางมือ
- หากคุณเล่น DVD จะตั้งค่าโดยอัตโนมัติ
- หากคุณเปลี่ยน HDMI ไปเป็นแหล่งสัญญาณอื่น (คอมโพสิต, คอมโพเนนต์, ...ฯลฯ) ในทีวีขณะที่เล่นแผ่น DVD เครื่องเล่น DVD จะหยุดการทำงาน และเครื่องเล่น DVD อาจจะยังคงเล่นแผ่น DVD ต่อไป ขึ้นอยู่กับการนำทางที่แผ่น DVD รองรับ

การตั้งค่าคุณสมบัติของภาษา

ค่าคุณสมบัติของภาษาของเครื่องเล่น เมนูตั้งค่าภาษาของคุณ ลักษณะและค่าบรรยายของหน้า การตั้งค่าเหล่านี้จะถูกเรียกว่าโดยอัตโนมัติทุกครั้งที่คุณเปลี่ยนภาษา

1. ในขณะที่เครื่องเล่นอยู่ในโหมดดูหนัง กดปุ่ม MENU บนรีโมทคอนโทรล. กดปุ่ม **◀▶** เพื่อเลือก **SETTINGS** (การตั้งค่า) จากนั้นกดปุ่ม **ENTER**
2. กดปุ่ม **▲▼** เพื่อเลือก **LANGUAGE <ภาษา>** จากนั้นกดปุ่ม **▶** หรือ **ENTER**
3. กดปุ่ม **▲▼** เพื่อเลือกภาษาที่ต้องการ จากนั้นกดปุ่ม **▶** หรือ **ENTER**

หมายเหตุ

- ในการตั้งค่าเมนูภาษาต่างๆที่หายไป ให้กดปุ่ม MENU
- ถ้าภาษาที่เลือกไม่ได้บันทึกอยู่บนแผ่นติดกับภาษาที่บันทึกไว้ ต้องตั้งค่าใหม่
- เลือก “ตั้งค่า <Original>” ถ้าต้องการให้ภาษา รีเซ็ตของช่วงเวลาที่หากเปลี่ยนภาษาต้องเปลี่ยนตัวอักษร
- เลือก “อัตโนมัติ <Automatic>” ถ้าต้องการให้ภาษา ข้อต่อไปที่เลือกเป็นภาษาสำหรับเครื่องบรรยายเป็นภาษา ภาษาที่เลือก

กำหนดค่าอีพชันความปลอดภัย (Security)

ฟังก์ชันการควบคุมโดยผู้ปกครองทำงานร่วมกับแผ่น DVD ที่มีการกำหนดระดับของภาพยนตร์ เอาไว้ซึ่งช่วยให้คุณสามารถควบคุมชุดของ DVD ที่ครอบครัวของคุณจะดูได้ มีระดับของภาพยนตร์ทั้งหมด 8 ระดับนั้นแต่ละระดับ

การตั้งค่าเรียนรู้ภาษา และการเปลี่ยนรหัสผ่าน

1. ในขณะที่เครื่องเล่นอยู่ในโหมดดูหนัง กดปุ่ม MENU บนรีโมทคอนโทรล. กดปุ่ม **◀▶** เพื่อเลือก **SETTINGS** (การตั้งค่า) จากนั้นกดปุ่ม **ENTER**
2. กดปุ่ม **▲▼** เพื่อเลือก **SECURITY <ความปลอดภัย>** จากนั้นกดปุ่ม **▶** หรือ **ENTER**.
 - บันทึกรหัสผ่านของคุณ.
3. กดปุ่ม **▲▼** เพื่อเลือก **PARENTAL <ตรวจสอบ>/CHANGE PASSWORD <เปลี่ยนรหัสผ่าน>** จากนั้นกดปุ่ม **▶** หรือ **ENTER**
4. กดปุ่ม **▲▼** เพื่อเลือก บช่องภาพยนตร์ที่คุณต้องการ **ENTER**
 - e.g) เข้า การตั้งค่าที่เป็น Kids Safe (บังคับเด็ก)
 - ถ้าอย่าง เช่น ถ้าคุณเลือกใช้ช่องเด็ก Kids Safe (บังคับเด็ก) แผ่นติด ก็มีระดับเป็น 2 หรือสูงกว่า จะไม่ สามารถเปิด
5. บันทึกรหัสผ่านของคุณ. ค่าที่ต้องรีเซ็ต พินท์ 0000. จากนั้นพิมพ์รหัสผ่านใหม่ รหัสผ่านใหม่ต้องเป็นเลขอีกที่ไม่ใช่ 0000 เพื่อเปลี่ยนฟังก์ชันควบคุมของผู้ปกครอง. บันทึกรหัสผ่านของคุณม่อนรหัสผ่านใหม่ของคุณ

ระดับความปลอดภัย (Security Level) :

- บังคับเด็ก (KID SAFE)
- G (ผู้ชมทั่วไป) : เหมาะกับผู้ชมทุกอายุ
- PG (แนะนำให้ใหญ่ในการรับชมของผู้บุคคลอื่น) : เนื้อหาบางอย่างอาจไม่เหมาะสมกับเยาวชน.
- PG 13 (ผู้บุคคลของจริงมีระดับวัยอย่างอื่น) : เนื้อหาบางอย่างอาจไม่เหมาะสมสำหรับเด็กอายุต่ำกว่า 13
- PGR (ควรรับชมการรับชมของผู้บุคคลอื่น) :
- อาจไม่เนื้อหาที่ไม่เหมาะสมสำหรับเด็กและเยาวชน แต่ขอแนะนำให้ผู้ชมใช้วิจารณญาณในการชม และผู้บุคคลของจริงที่บังคับเด็กจะไม่สามารถดูซึ่งกันไม่ได้.
- R (จำกัด) : ผู้ชมต้องอายุต่ำกว่า 17 ต้องมีผู้ใหญ่ดูแลด้วย
- NC17 (NC-17) : ห้ามเด็กอายุต้องตั้งแต่ 17 ปีลงไป.
- ผู้ใหญ่ (ADULT)

หมายเหตุ

- ถ้าคุณตั้งค่า ผ่านของคุณ ให้อ่านหัวข้อ “มีรหัสผ่าน” ในคู่มือการแก้ไขปัญหา

กำหนดค่าอ้อพชันทั่วไป (General)

1. ในขณะที่เครื่องเล่นอยู่ในโหมดดูยูด กดปุ่ม MENU บนรีโมทคอนโทรล. กดปุ่ม **◀/▶** เพื่อเลือก **SETTINGS** (การตั้งค่า) จากนั้นกดปุ่ม **ENTER**
2. กดปุ่ม **▲/▼** เพื่อเลือก **GENERAL** (ทั่วไป) จากนั้นกดปุ่ม **▶** หรือ **ENTER**
3. กดปุ่ม **▲/▼** เพื่อเลือกรายการที่ต้องการ จากนั้นกดปุ่ม **▶** หรือ **ENTER**

กำหนดค่าอ้อพชันสนับสนุน (Support)

อ้อพชันสนับสนุน (Support) ช่วยให้คุณตรวจสอบข้อมูลทางาน ของเครื่องเล่น DVD ของคุณ เช่น รหัสไมเดล เวอร์ชันของซอฟต์แวร์ สามารถดูหน้าเบลชิตสีกันชนได้ที่ด้านหลังของเครื่องเล่น DVD ของคุณ

1. ในขณะที่เครื่องเล่นอยู่ในโหมดดูยูด กดปุ่ม MENU บนรีโมทคอนโทรล. กดปุ่ม **◀/▶** เพื่อเลือก **SETTINGS** (การตั้งค่า) จากนั้นกดปุ่ม **ENTER**
2. กดปุ่ม **▲/▼** เพื่อเลือก **SUPPORT** (การสนับสนุน) จากนั้นกดปุ่ม **▶** หรือ **ENTER**
3. เลือก **PRODUCT INFORMATION** (ข้อมูล ผลิตภัณฑ์) จากนั้นกดปุ่ม **▶** หรือ **ENTER**

ข้อมูลอ้างอิง

การแก้ไขปัญหา

ก่อนที่จะนำเครื่อง โปรดบริการซ่อมแซม (แก้ไขปัญหา) โปรดตรวจสอบสิ่งต่อไปนี้ก่อน.

ปัญหา	การดำเนินการ
ไม่สามารถเล่นเสียงระบบ 5.1 บนเครื่องเล่น DVD ต้องดูอยู่บนแผงบล็อกไฟที่หน้าจอ	<ul style="list-style-type: none">• เชิญ 5.1 แซนด์และผลิตี้มาได้เฉพาะ เมื่อระบบของคุณสอดคล้องตามเงื่อนไขดังนี้:<ol style="list-style-type: none">1) เครื่องเล่น DVD ต้องดูอยู่บนแผงบล็อกไฟที่หน้าจอ2) แผ่นดิสก์ต้องบันทึกด้วยเชิง 5.1 แซนด์• ตรวจสอบว่าแผ่นดิสก์ที่จะเล่น มีลักษณะ “5.1 ch” ที่ด้านนอกหรือไม่• ตรวจสอบว่ามีการซื้อเมมโมรี่บล็อกไฟที่หน้าจอ แลระบบเสียงทำงานอย่างเหมาะสมหรือไม่• ใน SETUP Menu <เมนูการตั้งค่า> ค่า Audio Output <สัญญาณเสียงออก> ถูกตั้งเป็น Bitstream <บิตสตรีม> หรือไม่?
หน้าจอถูกกลืนล็อก	<ul style="list-style-type: none">• กดปุ่ม ■/▶/II เป็นเวลามากกว่า 5 วินาทีเมื่อในมีแผ่นดิสก์อยู่ในเครื่อง การตั้งค่าทั้งหมดจะถูกเรียกคืนกลับเป็นค่าโรงงาน
สีมีที่ส่วน	<ul style="list-style-type: none">• กดปุ่ม ■/▶/II เป็นเวลามากกว่า 5 วินาทีเมื่อในมีแผ่นดิสก์อยู่ในเครื่อง การตั้งค่าทั้งหมดรวมถึงแสงสีจะถูกกลืนล็อก เป็นค่าโรงงาน อย่าดำเนินการเช่นนี้ ยกเว้นกรณีที่จำเป็นจริงๆ เท่านั้น
ไม่มีสัญญาณออก HDMI	<ul style="list-style-type: none">• ตรวจสอบลักษณะของขา HDMI ไว้หรือไม่• ตรวจสอบการซื้อเมมโมรี่บล็อกไฟที่หน้าจอ HDMI และแจ็ค HDMI บนเครื่องเล่น DVD• ถ้าหากหัวสัญญาณเครื่องเล่น DVD ที่หัวความละเอียด 480p/576p/720p/1080i/1080p หรือไม่
หน้าจอสัญญาณออก HDMI มีปีกติด	<ul style="list-style-type: none">• ถ้าเกิดสัญญาณรบกวนบนหน้าจอ หมายความว่าโทรศัพท์มือถือสัมภาระ HDMI (การป้องกันนี้หากติดล็อกแบบวีดีโอ)
สัญญาณออก HDMI กระดูก	<ul style="list-style-type: none">• ตรวจสอบว่ามีการตั้งค่าระบบโทรศัพท์มือถืออย่างถูกต้อง• อาการที่หน้าจօกระดูก อาจเกิดขึ้นเมื่อตัวไฟร์มีตุกแมปลงจาก 50Hz เป็น 60Hz สำหรับสัญญาณออก HDMI (อินเตอร์ไฟร์มัลติมีเดียความละเอียดสูง) 720P/1080i/1080p• โปรดอ่านคู่มือผู้ใช้งานโทรศัพท์มือถือของคุณ

ข้อมูลจำเพาะ

Memo

ที่ว่าง	ความต้องการพลังงาน	AC 110-240V ~ 50/60 Hz
	ความสัมประสิทธิ์พลังงาน	6 W
	น้ำหนัก	DVD-C500 : 1.2 กก.
		DVD-C550/DVD-C550K : 1.5 กก.
	ขนาด	DVD-C500 : 360มม. (ก) X 207มม. (ล) X 42มม. (ส)
		DVD-C550/DVD-C550K : 430มม. (ก) X 207มม. (ล) X 42มม. (ส)
	ช่วงอุณหภูมิขณะทำงาน	+5°C ถึง +35°C
	ช่วงความชื้นขณะทำงาน	10 % ถึง 75 %
สัญญาณ ภาพออก	คอมโพลิคิวต์โอ	1 เมชันแนล : 1.0 Vp-p (โหลด 75 Ω)
	คอมโพเนนต์วีดีโอ	Y : 1.0 Vp-p (โหลด 75 Ω) Pr : 0.70 Vp-p (โหลด 75 Ω) Pb : 0.70 Vp-p (โหลด 75 Ω)
	HDMI	480p/576p, 720p, 1080i, 1080p
สัญญาณ เสียงออก	ชุดเอ่าเด็ฟทูด	RCA
	ระดับเอ่าเด็ฟสูงสุด	2Vrms
	ความถี่การตอบสนอง	20 Hz ถึง 20 kHz
	เอ่าเด็ฟเสียงดิจิตอล	ชุดต่อโอดิอกซิล (S/PDIF)
	5.1 แชนแนล (DVD-C550K)	F/L, F/R, R/L, R/R, CT, S/W

Memo

គិតគម្រោងស្ថាបន្ទីត

គិតគម្រោងស្ថាបន្ទីត អាជ្ញាតដែលបានរៀបចំឡើងសម្រាប់ភាគីទាំងអស់ គិតគម្រោង គិតគម្រោងស្ថាបន្ទីត SAMSUNG customer care center

Region	Area	Contact Center	Web Site
North America	Canada	1-800-SAMSUNG (726-7864)	www.samsung.com/ca
	Mexico	01-800-SAMSUNG (726-7864)	www.samsung.com/mx
	U.S.A	1-800-SAMSUNG (726-7864)	www.samsung.com/us
Latin America	Argentina	0800-333-3733	www.samsung.com/ar
	Brazil	0800-124-421, 4004-0000	www.samsung.com/br
	Chile	800-SAMSUNG (726-7864)	www.samsung.com/cl
	Nicaragua	00-1800-5077267	www.samsung.com/latin
	Honduras	800-7919267	www.samsung.com/latin
	Costa Rica	0-800-507-7267	www.samsung.com/latin
	Ecuador	1-800-10-7267	www.samsung.com/latin
	El Salvador	800-6225	www.samsung.com/latin
	Guatemala	1-800-299-0013	www.samsung.com/latin
	Jamaica	1-800-234-7267	www.samsung.com/latin
	Panama	800-7267	www.samsung.com/latin
	Puerto Rico	1-800-3180	www.samsung.com/latin
Europe	Rep. Dominica	1-800-751-2676	www.samsung.com/latin
	Trinidad & Tobago	1-800-SAMSUNG (726-7864)	www.samsung.com/latin
	Venezuela	0-800-100-5303	www.samsung.com/latin
	Colombia	01-800011212	www.samsung.com.co
	Belgium	02 201 2418	www.samsung.com/be (Dutch) www.samsung.com/be_fr (French)
	Czech Republic	800-SAMSUNG (800-726786)	www.samsung.com/cz
	Denmark	8-SAMSUNG (7267864)	www.samsung.com/dk
Europe	Finland	30-6227 515	www.samsung.com/fi
	France	01 4863 0000	www.samsung.com/fr
	Germany	01805-1-SAMSUNG (726-7864 € 0,14/Min)	www.samsung.de
	Hungary	06-800-SAMSUNG (726-7864)	www.samsung.com/hu
	Iceland	800-SAMSUNG (726-7864)	www.samsung.com/ie
	Luxembourg	02 261 03 710	www.samsung.com/lu
	Netherlands	0900-SAMSUNG (0900-7267864) (€ 0,10/Min)	www.samsung.com/nl
	Norway	3-SAMSUNG (7267864)	www.samsung.com/no
	Poland	0 801-SAMSUNG (172678), 022-607-93-33	www.samsung.com/pl
	Portugal	80802-SAMSUNG (726-7864)	www.samsung.com/pt
	Slovakia	8000-SAMSUNG (726-7864)	www.samsung.com/sk
	Spain	902-1-SAMSUNG (902 172 678)	www.samsung.com/es
CIS	Sweden	0771 726 7864 (SAMSUNG)	www.samsung.com/se
	U.K.	0845 SAMSUNG (7267864)	www.samsung.com/uk
	Eire	0181 717 100	www.samsung.com/ie
	Austria	0810-SAMSUNG (7267864, € 0,07/min)	www.samsung.com/at
	Switzerland	0848-SAMSUNG (7267864, CHF 0,08/min)	www.samsung.com/ch www.samsung.com/ch_fr (French)
	Russia	8-800-555-55-55	www.samsung.ru
	Kazakhstan	8-10-800-500-55-500	www.samsung.com/kz_ru
Asia Pacific	Uzbekistan	8-10-800-500-55-500	www.samsung.com/kz_ru
	Kyrgyzstan	00-800-500-55-500	
	Tajikistan	8-10-800-500-55-500	
	Ukraine	8-800-502-0000	www.samsung.ua www.samsung.com/ua_ru
	Belarus	810-800-500-55-500	
	Moldova	00-800-500-55-500	
	Lithuania	8-800-77777	www.samsung.comlt
Asia Pacific	Latvia	800-7267	www.samsung.comlv
	Estonia	800-7267	www.samsung.comee
	Australia	1300 582 603	www.samsung.com.au
	New Zealand	0800 SAMSUNG (0800 726 786)	www.samsung.com/nz
	China	400-810-5838, 010-6475 1880	www.samsung.com/cn
	Hong Kong	3698-4698	www.samsung.com/hk www.samsung.com/hk_en/
	India	3030 8282, 1800 110011, 1800 3000 8282	www.samsung.com/in
	Indonesia	0800-112-8888	www.samsung.com/id
	Japan	0120-327-527	www.samsung.com/jp
	Malaysia	1800-88-9999	www.samsung.com/my
Middle East & Africa	Philippines	1-800-10-SAMSUNG (726-7864), 1-800-3-SAMSUNG (726-7864), 1-800-9-SAMSUNG (726-7864), 02-5805777	www.samsung.com/ph
	Singapore	1300 8282 1800 110011 (726-7864)	www.samsung.com/sa
	Thailand	1800-29-3232 02-689-3232	www.samsung.com/th
	Taiwan	0800-329-999	www.samsung.com/tw
	Vietnam	1 800 588 889	www.samsung.com/vn
Middle East & Africa	Turkey	442 77 11	www.samsung.com/tr
	South Africa	0860-SAMSUNG (726-7864)	www.samsung.com/za
	U.A.E	800-SAMSUNG (726-7864), 8000-4726	www.samsung.com/ae



DVD-C500
DVD-C550
DVD-C550K

DVD Player

User Manual

imagine the possibilities

Thank you for purchasing this Samsung product.

To receive more complete service, please register your product at

www.samsung.com/global/register



Precautions

1. Setting up

- Refer to the identification label located on the rear of your player for its proper operating voltage.
- Install your player in a cabinet with adequate ventilation holes. (7~10cm). Do not block ventilation holes on any of the components for air circulation.
- Do not push the disc tray in by hand.
- Do not stack components.
- Be sure to turn all components off before moving the player.
- Before connecting other components to this player, be sure to turn them off.
- Be sure to remove the disc and turn off the player after use, especially if you are not going to use it for a long time.
- The mains plug is used as a disconnect device and shall stay readily operable at any time.

2. For your safety

- This product utilizes a laser. Use of controls or adjustments or performance of procedures other than those specified herein may result in hazardous radiation exposure.
- Do not open covers and do not repair your self. Refer servicing to qualified personal.

3. Caution

- Your player is not intended for industrial use but for domestic purposes. Use of this product is for personal use only.
- Apparatus shall not be exposed to dripping or splashing and no objects filled with liquids, such as vases, shall be placed on the apparatus.
- Exterior influences such as lightning and static electricity can affect normal operation of this player. If this occurs, turn the player off and on again with the POWER button, or disconnect and then reconnect the AC power cord to the AC power outlet. The player will operate normally.
- When condensation forms inside the player due to sharp changes in temperature,

the player may not operate correctly. If this occurs, leave the player at room temperature until the inside of the player becomes dry and operational.

4. Disc

- Do not clean disc using record-cleaning sprays, benzene, thinner, or other volatile solvents that may cause damage to the disc surface.
- Do not touch the disc's bottom. Hold by the edges or by one edge and the hole in the center.
- Wipe the dirt away gently; never wipe a cloth back and forth over the disc.

5. Environmental info

- The battery used in this product contains chemicals that are harmful to the environment.
- So, dispose the batteries in the proper-manner, according to federal, state, and local regulations.

The product unit accompanied this user manual is licenced under certain intellectual property rights of certain third parties. This licence is limited to private non-commercial use by end-user consumers for licenced contents. No rights are granted for commercial use. The licence does not cover any product unit other than this product unit and the licence does not extend to any unlicenced product unit or process conforming to ISO/OUR 11172-3 or ISO/OUR 13818-3 used or sold in combination with this product unit. The licence only covers the use of this product unit to encode and/or decode audio files conforming to the ISO/OUR 11172-3 or ISO/OUR 13818-3. No rights are granted under this licence for product features or functions that do not conform to the ISO/OUR 11172-3 or ISO/OUR 13818-3.

CAUTION: USE OF ANY CONTROLS, ADJUSTMENTS, OR PROCEDURES OTHER THAN SPECIFIED HEREIN MAY RESULT IN HAZARDOUS RADIATION EXPOSURE

Table of contents

Precautions	2
Setup	
General Features	2
Description	3
Tour of the Remote Control.....	3
Connections	
Choosing a Connection	4
Basic Functions	
Playing a Disc	5
Using the Search and Skip Functions	5
Using the Display Function	6
Using the Disc and Title Menu	6
Repeat Play	6
Slow Play	6
Advanced Functions	
Adjusting the Aspect Ratio (EZ View)	6
Selecting the Audio Language	7
Selecting the Subtitle Language	7
Changing the Camera Angle.....	7
Using the Bookmark Function	7
Using the Zoom Function	7
Clips Menu for MP3/WMA/JPEG/MPEG4/CD Audio.....	7
Folder Selection	7
MP3/WMA/CD Audio Playback	7
MPEG4 Playback	8
Playing Media Files using the USB HOST feature (Only DVD-C550/DVD-C550K)	9
CD Ripping (Only DVD-C550/DVD-C550K)	9
Picture CD Playback	9
Picture CD Playback for HD-JPEG	10
Karaoke Functions (Only DVD-C550K)	
Karaoke Functions	10
Changing Setup Menu	
Using the Setup Menu	10
Setting Up the Display Options	10
Setting Up the Audio Options	11
Setting Up the System Options	12
Setting Up the Language Features	12
Setting Up the Security Options	12
Setting Up the General Options	13
Setting Up the Support Options	13
Reference	
Troubleshooting	13
Specifications	14

Setup

General Features

Excellent Sound

Dolby Digital, a technology developed by Dolby Laboratories, provides crystal clear sound reproduction.

Screen

Both regular and widescreen(16:9) pictures can be viewed.

Slow Motion

An important scene can be viewed in slow motion.

1080p Playback

This player upconverts regular DVDs for playback on 1080p TVs.

Parental Control (DVD)

The parental control allows users to set the necessary level to prohibit children from viewing harmful movies such as those with violence, adult subject matter, etc.

Various On-Screen Menu Functions

You can select various languages (Audio/Subtitle) and screen angles while enjoying movies.

Progressive Scan

Progressive scanning creates an improved picture

with double the scan lines of a conventional interlaced picture

EZ VIEW (DVD)

Easy View enables picture adjustment to match your TV's screen size (16:9 or 4:3).

Digital Photo Viewer (JPEG)

You can view Digital Photos on your TV.

Repeat

You can repeat a song or movie simply by pressing the REPEAT button

MP3/WMA

This unit can play discs contain MP3/WMA files.

MPEG4

This unit can play MPEG4 formats within an avi file. HDMI (High Definition Multimedia Interface)
HDMI reduces picture noise by allowing a pure-digital video/audio signal path from the player to your TV.

CD Ripping (Only DVD-C550/DVD-C550K)

This feature lets you to copy audio files from disc to USB device into MP3 format. (Only Audio CD (CD DA)).

Note

- Discs which cannot be played with this player.
 - DVD-ROM
 - CD-ROM
 - CDI
 - CDGs play audio only, not graphics.
- Ability to play back may depend on recording conditions.
 - DVD-R, +R
 - CD-RW
 - DVD+RW, -RW (V mode)
- The unit may not play certain CD-R, CD-RW and DVD-R due to the disc type or recording conditions.

COPY PROTECTION

Many DVD discs are encoded with copy protection. Because of this, you should only connect your DVD player directly to your TV, not to a VCR. Connecting to a VCR results in a distorted picture from copy-protected DVD discs.

This product incorporates copyright protection technology that is protected by methods claims of certain U.S. patents and other intellectual property rights owned by Rovi Corporation and other rights owners. Use of this copyright protection technology must be authorized by Rovi Corporation, and is intended for home and other limited viewing uses only unless otherwise authorized by Rovi Corporation. Reverse engineering or disassembly is prohibited.

PROGRESSIVE SCAN OUTPUTS (576p, 720p, 1080p)

"CONSUMERS SHOULD NOTE THAT NOT ALL HIGH DEFINITION TELEVISION SETS ARE FULLY COMPATIBLE WITH THIS PRODUCT AND MAY CAUSE ARTIFACTS TO BE DISPLAYED IN THE PICTURE. IN CASE OF 576, 720, 1080 PROGRESSIVE SCAN PICTURE PROBLEMS, IT IS RECOMMENDED THAT THE USER SWITCH THE CONNECTION TO THE 'STANDARD DEFINITION' OUTPUT. IF THERE ARE QUESTIONS REGARDING YOUR TV SET COMPATIBILITY WITH THIS MODEL 576p, 720p, 1080p DVD PLAYER, PLEASE CONTACT SAMSUNG'S CUSTOMER SERVICE CENTER."

Description

Front Panel Controls

DVD-C500



Disc Markings

	Play Region Number
	CDV
	CDI
	CDGs play audio only, not graphics.
	Ability to play back may depend on recording conditions.
	DVD-R, +R
	CD-RW
	DVD+RW, -RW (V mode)
	The unit may not play certain CD-R, CD-RW and DVD-R due to the disc type or recording conditions.

Region Number

Both the DVD player and the discs are coded by region. These regional codes must match in order for the disc to play. If the codes do not match, the disc will not play.

The Region Number for this player is described on the rear panel of the player.

DivX Certification



DivX, DivX Certified, and associated logos are trademarks of DivXNetworks, Inc and are used under license. "DivX Certified to play DivX video, including premium content."

DVD-C500




DVD-C550K




- 1. DISC TRAY**
Place the disc here.
- 2. DISPLAY**
Operation indicators are displayed here.
- 3. OPEN/CLOSE (Δ)**
Press to open and close the disc tray.
- 4. STOP (■)**
Stops play.
- 5. PLAY/PAUSE (▶■)**
Play or pause the disc.
- 6. POWER ON/OFF (○)**
Turn on/off and the player is turned on/off.
- 7. USB HOST (Only DVD-C550/
DVD-C550K)**
Connect digital still camera, MP3 player, memory stick, Card reader other removable storage devices.
- 8. MICROPHONE VOLUME
(Only DVD-C550K)**
Use to adjust microphone volume level. Use the button by pressing it. Turn it to the left or right to control the volume.
- 9. MIC 1/2 (Only DVD-C550K)**
Connect Microphone for karaoke functions.

Tour of the Remote Control


DVD-C500



DVD-C550



DVD-C550K



- DVD POWER Button**
Turns the power on or off.
- DVD Button**
Use to select the DVD player for operation.
- TV Button**
Use to select a Samsung TV for operation.
- EZ VIEW Button**
Lets you easily adjust the aspect ratio of a picture according to the screen size of your TV (16:9 or 4:3).
- MARKER Button**
- REPEAT Button**
Allows you to repeat play a title, chapter, track, or disc.
- DISC MENU Button**
Brings up the Disc menu.
- INFO Button**
Used to displays playback info banner.
- TV VOL (+, -) Buttons**
Controls volume.
- SKIP Buttons (◀◀/▶▶)**
Use to skip the title, chapter or track.
- STOP Button (■)**
- MENU Button**
Brings up the DVD player's menu.
- ENTER/△/▽, ▲/▶ Buttons**
This button functions as a toggle switch.
- TOOLS Button**
Displays the current disc mode. It also lets you access the Display function.
- OPEN/CLOSE (▲) Button**
To open and close the disc tray.
- HDMI SEL. Button**

Connections

Choosing a Connection

The following shows examples of connections commonly used to connect the DVD player with a TV and other components.

Before Connecting the DVD Player

- Always turn off the DVD player, TV, and other components before you connect or disconnect any cables.
- Refer to the user's manual of the additional components you are connecting for more information on those particular components.

A. Connecting to a TV (For Video)

1. Using video/audio cables, connect the VIDEO (yellow)/AUDIO (red and white) OUT terminals or 5.1CH (Front L-R) on the rear of the DVD player to the VIDEO (yellow)/AUDIO (red and white) IN terminals of TV.
2. Turn on the DVD player and TV.
3. Press the input selector on your TV remote control until the Video signal from the DVD player appears on the TV screen.

Note

- **Noise may be generated if the audio cable is too close to the power cable.**
- If you want to connect to an Amplifier, please refer to the Amplifier connection page.
- The number and position of terminals can vary depending on your TV set. Please refer to the user's manual of the TV.
- If there is one audio input terminal on the TV, connect it to the [AUDIO OUT][left] (white) terminal of the DVD player.
- If you press the VIDEO SEL. button when DVD Player is in stop mode or no disc is inserted, the Video Output mode changes in the following sequence: I-SCAN → P-SCAN

17. **USB Button (Only DVD-C550/DVD-C550K)**
ZOOM Button (Only DVD-C500)
Enlarge the DVD Picture.
18. **VIDEO SEL. Button**
Changes video output mode.
19. **REPEAT A-B Button**
Allows you to repeat play a chosen section (A-B) on a disc.
20. **SUBTITLE Button**
21. **TITLE MENU Button**
Brings up the Title menu.
22. **AUDIO/TV SOURCE Button**
Use this button to access various audio functions on a disc. Use this button to select an available TV source (mode TV).
23. **PAUSE Button (II)**
Pauses disc play.
24. **SEARCH Buttons (◀◀/▶▶)**
Allows you to search forward/backward through a disc.
25. **TV CH (△, ▽) Buttons**
Channel selection.
26. **PLAY Button (▶)**
Begins disc play.
27. **RETURN Button**
Returns to a previous menu.
28. **EXIT Button**
Exits the on-screen menu.
29. **KARAOKE (Y) Button (Only DVD-C550K)**
Use to begin Karaoke functions.

B. Connection to a TV (Interlace/Progressive)

1. Using component video cables, connect the **COMPONENT VIDEO OUT** terminal on the rear of the DVD player to the **COMPONENT IN** terminal of TV.
2. Using the audio cables, connect the **AUDIO (red and white) OUT** terminals or 5.1CH (Front L-R) on the rear of the DVD player to the **AUDIO (red and white) IN** terminals of TV. Turn on the DVD player and TV.
3. Press the input selector on your TV remote control until the Component signal from the DVD player appears on the TV screen.
4. Set the Video Output to **I-SCAN/P-SCAN** in the Display Setup menu. You can use the **VIDEO SEL.** button to change the Video Output mode.

Note

- What is "Progressive Scan"?
Progressive scan has twice as many scanning lines as the interlace output method has. Progressive scanning method can provide better and clearer picture quality.

C. Connecting to a TV with DVI/HDMI Jack

1. Using the HDMI-DVI/HDMI-HDMI cable , connect the **HDMI OUT** terminal on the rear of the DVD player to the **DVI/HDMI IN** terminal of your TV.
2. Using the audio cables, connect the **AUDIO (red and white) OUT** terminals or 5.1CH (Front L-R) on the rear of the DVD player to the **AUDIO (red and white) IN** terminals of your TV. Turn on the DVD player and TV.
3. Press the input selector on your TV remote control until the DVI/HDMI signal from the DVD player appears on your TV screen.

HDMI VIDEO Specifications

When you press the **HDMI SEL.** button, 480p, 576p, 720p, 1080p, 1080i are selected in order. The first press of the **HDMI SEL.** button brings up the current resolution.

The second press allows you to change the HDMI output resolution.

- Depending on your TV, certain HDMI output resolutions may not work.
- Please refer to the user's manual of your TV.
- If HDMI or HDMI-DVI cable is plugged into TV, the DVD player's output is set to HDMI/DVI within 10 seconds.
- If you set the HDMI output resolution 720p,1080p or 1080i, HDMI output provides better picture quality.
- If you connect an HDMI cable between Samsung TV and this DVD player, you can operate this DVD player using your TV remote control. This is only available with Samsung TVs that support Anynet+(HDMI-CEC).
- If your TV has an  logo, then it will  Supports the Anynet+ Function.

• HDMI (High Definition Multimedia Interface)

HDMI is an interface to enable the digital transmission of video and audio data with just a single connector.Using HDMI, the DVD player transmits a digital video and audio signal and displays a vivid picture on a TV having an HDMI input jack.

• HDMI connection description HDMI connector

- Both uncompressed video data and digital audio data (LPCM or Bit Stream data).- Though the player uses a HDMI cable, the player outputs only a pure digital signal to the TV.
- If TV does not support HDCP (High-bandwidth Digital content protection), snow noise appears on the screen.

• Why does Samsung use HDMI?


Analog TVs require an analog video/audio signal. However, when playing a DVD, the data transmitted to a TV is digital. Therefore either a digital-to-analog converter (in the DVD player) or an analog-to-digital converter (in the TV) is required. During this conversion, the picture quality is degraded due to noise and signal loss. DVI technology is superior because it requires no D/A conversion and is a pure digital signal from the player to your TV.

• What is the HDCP?

HDCP (High-bandwidth Digital Content Protection) is a system for protecting DVD content outputted via DVI from being copied. It provides a secure digital link between a video source (PC, DVD, etc) and a display device (TV, projector . etc). Content is encrypted at the source device to prevent unauthorized.


D. Connection to an Audio System (2 Channel Amplifier, Dolby Digital, MPEG2 or DTS Amplifier)

- Using the audio cables, connect the **AUDIO (red and white) OUT** terminals or 5.1CH (Front L-R) on the rear of the DVD player to the **AUDIO (red and white) IN** terminals of the Amplifier. If using a coaxial cable, connect the **DIGITAL AUDIO OUT (COAXIAL)** terminal on the rear of the DVD player to the **DIGITAL AUDIO IN (COAXIAL)** terminal of the Amplifier.
- Using the video signal cable(s), connect the **VIDEO, COMPONENT or HDMI OUT** terminals on the rear of the DVD player to the **VIDEO, COMPONENT or DVI IN** terminals of your TV
- Turn on the DVD player, TV, and Amplifier.
- Press the input select button of the Amplifier to select **external input** in order to hear sound from the DVD player. Refer to your Amplifier's user manual to set the Amplifier's audio input.



E. Connection to a 5.1CH Analog Amplifier (Only DVD-C550K)

- If using audio cables for 5.1 CH Analog Amplifier connect the **5.1CH ANALOG AUDIO OUT** terminals on the rear of the DVD player to the **5.1CH ANALOG AUDIO IN** terminals of the 5.1CH Analog Amplifier.
- Using the video signal cable(s), connect the **VIDEO, COMPONENT or HDMI OUT** terminals on the rear of the DVD player to the **VIDEO, COMPONENT or DVI IN** terminals of your TV
- Turn on the DVD player, TV, and Amplifier.
- Press the input select button of the Amplifier to select **external input** in order to hear sound from the DVD player. Refer to your Amplifier's user manual to set the Amplifier's audio input.



Basic functions

Playing a Disc

Before Play

- Turn on your TV and set it to the correct Video Input by pressing TV/VIDEO button on the TV remote control.
- If you connected an external Audio System, turn on your Audio System and set it to the correct Audio Input.

After plugging in the player, the first time you press the DVD POWER button, this screen comes up. If you want to select a language, press the **▲/▼** button, and then press the **ENTER** button. (This screen will only appear when you plug in the player for the first time.) If the language for the startup screen is not set, the settings may change whenever you turn the power on or off. Therefore, make sure that you select the language you want to use. Once you select a menu language, you can change it by pressing the **■/▶/◀** button on the front panel of the unit for more than 5 seconds with no disc in the unit. Then the **SELECT MENU LANGUAGE** window appears again where you can reset your preferred language.

Using the Search and Skip Functions

During play, you can search quickly through a chapter or track, and use the skip function to jump to the next selection.

Searching through a Chapter or Track

During play, press the **SEARCH (◀◀ or ▶▶)** button on the remote control for more than 1 second.

DVD	2X, 4X, 8X, 16X, 32X
CD	2X, 4X, 8X, 16X, 32X
VCD	4X, 8X

Note

- The speed marked in this function may be different from the actual playback speed.
- No sound is hearing during search mode (Except CD).

Skipping Tracks

During play, press the **SKIP (◀◀ or ▶▶)** button.

- When playing a DVD, if you press the **SKIP (▶▶)** button, it moves to the next chapter. If you press the **SKIP (◀◀)** button, it moves to the beginning of the chapter. One more press makes it move to the beginning of the previous chapter.
- When playing a VCD, if you press the **SKIP (▶▶)** button, it moves to the next track. If you press the **SKIP (◀◀)** button, it moves to the beginning of the track. One more press makes it move to the beginning of the previous track.
- If a track exceeds 15 minutes when playing a VCD and you press the **▶▶** button, it moves forward 5 minutes. If you press the **◀◀** button, it moves to the beginning of the track. One more press makes it move to the beginning of the previous track.

Using the Display Function

When Playing a DVD/VCD/MPEG4

1. During play, press the **TOOLS** button on the remote control.
2. Press the **▲/▼** buttons to select the desired item.
3. Press the **◀/▶** buttons to make the desired setup.
3. To make the screen disappear, press the **TOOLS** button again.

The functions when using the Display function are listed in the table below.

	To access the desired title when there is more than one in the disc. For example, if there is more than one movie on a DVD, each movie will be identified.
	Most DVD discs are recorded in chapters so that you can quickly find a specific passage.
	Allows playback of the film from a desired time. You must enter the starting time as a reference. The time search function does not operate on some disc.
	Refers to the language of the film soundtrack. In the example, the soundtrack is played in English 5.1CH. A DVD disc can have up to eight different soundtracks.
	Refers to the subtitle languages available in the disc. You will be able to choose the subtitle languages or, if you prefer, turn them off from the screen. A DVD disc can have up to 32 different subtitles.
	User will be able to choose EZ-View type.
	Press enter to activate the Zoom function.
	To access the desired Angle function. Some DVD disc are have more than one recorded angle.

Using the Disc and Title Menu

During the playback of a DVD disc, press the **DISC MENU/TITLE MENU** button on the remote control.

Note

- Depending on a disc, the Disc Menu/Title Menu may not work.
- You can also use the Disc Menu, using the **DISC MENU** button on the remote control.
- Title Menu will only be displayed if there are at least two titles in the disc.

Repeat Play

Repeat the current track, chapter, title, a chosen section (A-B), or all of the disc.

When playing a DVD/VCD

1. Press the **REPEAT** button on the remote control. Repeat screen appears.
2. Press the **REPEAT** or **▲/▼** button to change playback mode. DVD repeats play by chapter or title
 - Chapter : repeats the chapter that is playing.
 - Title : repeats the title that is playing.
 - Off.

Using the A-B Repeat function

1. Press the **REPEAT A-B** button on the remote control.
2. Press the **REPEAT A-B** button at the point where you want repeat play to start (A).
3. Press the **REPEAT A-B** button at the point where you want the repeat play to stop (B).
3. To return to normal play, press the **REPEAT A-B** button until the display shows Repeat : Off.

Note

- A-B REPEAT allows you to set point (B) directly after point (A) has been set.
- Depending on a disc, the Repeat function may not work.

Slow Play

This feature allows you slowly to repeat scenes containing sports, dancing, musical instruments being played etc., so you can study them more closely.

When playing a DVD

1. During play, press the **PAUSE (II)** button.
2. Press the **SEARCH (◀◀/▶▶)** button to choose the play speed between 1/2, 1/4, 1/8 and 1/16 of normal during PAUSE mode.

Advanced functions

Adjusting the Aspect Ratio (EZ View)

To play back using aspect ratio (DVD)

1. During play, press the **EZ VIEW** button on the remote control.
2. Press the **EZ VIEW** or **▲/▼** buttons to select the screen size. Each time you press the **EZ VIEW** or **▲/▼** buttons, the screen size changes. For graphics of the screen sizes and lists of the sequences in which the sizes change, see the next column.
3. Press the **EXIT** button to exit EZ View.

If you are using a 16:9 TV

For 16:9 aspect ratio discs

- WIDE SCREEN
- SCREEN FIT
- ZOOM FIT

For 4:3 aspect ratio discs

- Normal Wide
- SCREEN FIT
- ZOOM FIT
- Vertical Fit

If you are using a 4:3 TV

For 16:9 aspect ratio discs

- 4:3 Letter Box
- 4:3 Pan Scan
- SCREEN FIT
- ZOOM FIT

For 4:3 aspect ratio discs

- Normal Screen
- SCREEN FIT
- ZOOM FIT

Note

This function may behave differently depending on the type of disc.

Selecting the Audio Language

You can select a desired audio language quickly and easily with the AUDIO button.

Using the AUDIO button (DVD/VCD/MPEG4)

1. During play, Press the **AUDIO** button. Change the audio language by pressing the **AUDIO** or **▲/▼** button.
 - The audio languages are represented by abbreviations.
2. To remove the **AUDIO** icon, press the **EXIT** button.

Note

- This function depends on audio languages are encoded on the disc and may not work.
- A DVD disc can contain up to 8 audio languages.

Selecting the Subtitle Language

You can select a desired subtitle quickly and easily with the SUBTITLE button.

Using the SUBTITLE button (DVD/MPEG4)

1. During play, Press the **SUBTITLE** button.
2. Press the **SUBTITLE** or **▲/▼** button to change the language. Each time you press the **SUBTITLE** or **▲/▼** button, the language changes.
3. To remove the **SUBTITLE** icon, press the **EXIT** button.

Note

- The subtitle languages are represented by abbreviations.
- You have to change the desired subtitle in the Disc Menu, according to discs. Press the **DISC MENU** button.
- This function depends on what subtitles are encoded on the disc and may not work on all DVDs.
- A DVD disc can contain up to 32 subtitle languages.

Changing the Camera Angle

When a DVD contains multiple angles of a particular scene, you can use the ANGLE function.

Using the ANGLE function (DVD)

If the disc contains multiple angles, the ANGLE appears on the screen.

1. During play, press the **TOOLS** button on the remote control.
2. Press the **▲/▼** buttons to select icon. When the angle screen is displayed, press the **◀/▶** buttons on the remote control to select the desired angle option.

Using the Bookmark Function

This feature lets you bookmark sections of a DVD or VCD (Menu Off mode) so you can quickly find them at a later time.

Using the Bookmark Function (DVD/VCD)

1. During play, press the **MARKER** button on the remote control.
2. When you reach the scene you want to mark, press the **◀/▶** or **▲/▼** buttons, and then press **MARKER** button. Up to 12 scenes may be marked at a time.

Note

- Depending on a disc, the Bookmark function may not work.

Recalling a Marked Scene

1. During play, press the **MARKER** button on the remote control.
2. Press the **◀/▶** or **▲/▼** buttons to select a marked scene.
3. Press the **PLAY (▶)** button to skip to the marked scene.

Clearing a Bookmark

1. During play, press the **MARKER** button on the remote control.
2. Press the **◀/▶** or **▲/▼** buttons to select the bookmark number you want to delete.
3. Press the **ENTER** button to delete a bookmark number.

Using the Zoom Function

Using the Zoom Function (DVD/VCD)

1. During play or pause mode, press the **TOOLS** or **ZOOM** button on the remote control.
2. Press the **▲/▼** buttons to select icon, then press the **ENTER** button to zoom in X1,X2,X3,X4.

Clips Menu for MP3/WMA/JPEG/MPEG4/CD Audio

CD Audio or discs with MP3/WMA/JPEG/MPEG4 contain individual songs and/or pictures that can be organized into folders as shown below. They are similar to how you use your computer to put files into different folders.



To go access these folders and the files in them, follow these steps :

1. Open the disc tray. Place the disc on the tray.
2. Close the tray. The tray closes and the Parent Folder Menu screen appears (top screen image.) Parent folders contain all the Peer folders that have the same kind of content: music, video, photos, etc.
3. Press the **◀/▶** buttons to select the Parent folder of your choice, and then press the **ENTER**. A screen displaying the Peer folders appears. The Peer folders contain all the folders with the same kind of content (video, music, photos, etc.) that are in the Parent folder.

Folder Selection

The folder can be selected both in Stop or Play mode.

- **To select the Parent Folder**
Press the **RETURN** button to go to parent folder, or press the **▲/▼** buttons to select ".." and press **ENTER** to go to the parent folder.
- **To select the Peer Folder**
Press the **▲/▼** buttons to select the desired folder, then press **ENTER**.
- **To select the Sub-Folder**
Press the **▲/▼** buttons to select the desired folder, then press **ENTER**.

MP3/WMA/CD Audio Playback

1. Open the disc tray. Place the disc on the tray. Close the tray.
2. Press the **◀/▶** buttons to select a Music Menu then press **ENTER**. Press the **▲/▼** buttons to select a song file then press the **ENTER**. Press the **▲/▼** buttons to begin playback of the song file then press **ENTER**.

Repeat/Random playback

Press the REPEAT button to change the playback mode. There are four modes, such as Off, Track, Folder and Random.

- Off (→): Normal Playback
- Track (□): Repeats the current song file.
- Folder (■): Repeats the song files which have the same extension in the current folder.
- Random (↔): Song files which have the same extension will be played in random order.

To resume normal play, press the REPEAT button until the Repeat : Off.

CD-R MP3/WMA file

When you record MP3 or WMA files on CD-R, please refer to the following.

- Your MP3 or WMA files should be ISO 9660 or JOLIET format.

ISO 9660 format and Joliet MP3 or WMA files are compatible with Microsoft's DOS and Windows, and with Apple's Mac. This format is the most widely used.

- When naming your MP3 or WMA files, do not exceed 8 characters, and enter ".mp3, .wma" as the file extension. General name format : Title.mp3, or Title.wma. When composing your title, make sure that you use 8 characters or less, have no spaces in the name, and avoid the use of special characters including: (.,/,=,+).

- Use a decompression transfer rate of at least 128 Kbps when recording MP3 files.

Sound quality with MP3 files basically depends on the rate of compression/decompression you choose.

Getting CD audio sound requires an analog/digital sampling rate, that is conversion to MP3 format, of at least 128 Kbps and up to 160 Kbps. However, choosing higher rates, like 192 Kbps or more, only rarely give better sound quality. Conversely, files with decompression rates below 128 Kbps will not be played properly.

- Use a decompression transfer rate of at least 64Kbps when recording WMA files.

Sound quality with WMA files basically depends on the rate of compression/decompression you choose.

Getting CD audio sound requires an analog/digital sampling rate, that is conversion to WMA format, of at least 64Kbps and up to 192Kbps. Conversely, files with decompression rates below 64Kbps or over 192Kbps will not be played properly. Sampling rate that can be supported for WMA files is > 30Khz.

- Do not try recording copyright protected MP3 files.

Certain "secured" files are encrypted and code protected to prevent illegal copying. These files are of the following types: Windows Media™ (registered trade mark of Microsoft Inc) and SDMI™ (registered trade mark of The SDMI Foundation). You cannot copy such files.

- Important:

The above recommendations cannot be taken as a guarantee that the DVD player will play MP3 recordings, or as an assurance of sound quality. You should note that certain technologies and methods for MP3 file recording on CD-Rs prevent optimal playback of these files on your DVD player (degraded sound quality and in some cases, inability of the player to read the files).

- This unit can play a maximum of 500 files and 500 folders per disc.

MPEG4 Playback

MPEG4 Play Function

AVI files are used to contain the audio and video data. Only AVI format files with the ".avi" extensions can be played.

1. Open the disc tray. Place the disc on the tray. Close the tray.
2. Press the ▲/▼ buttons to select a Videos Menu , then press the ENTER. Press the ▲/▼ to select an avi file (DivX/XviD) then press the ENTER. Press the ▲/▼ and then press the ENTER button.

Repeat and Repeat A-B playback

1. Press the REPEAT button , then press REPEAT or ▲/▼ buttons to change playback mode. There are 3 modes, such as Off, Folder and Title.

- Folder : repeats the AVI files which have the same extension in the current folder.
- Title : repeats the title that is playing.
- Off : No Repeat mode.

2. Press the REPEAT A-B button on the remote control.

3. Press the REPEAT A-B button to set the point where you want repeat play to start (A).

4. Press the REPEAT A-B button again at the point where you want the repeat play to stop (B).

- To return to normal play, press the REPEAT A-B button until the display shows Repeat : Off.

Note

- A-B REPEAT allow you to set point (B) directly after point (A) has been set.

MPEG4 Function Description

Function	Description
Skip (◀◀ or ▶▶)	During play, press the ▲◀◀ or ▶▶ button, it moves to next or previous track.
Search (◀◀ or ▶▶)	During play, press the SEARCH (◀◀ or ▶▶) button and press again to search at a faster speed. Allows you to search at a faster speed in an AVI file. (2X, 4X, 8X, 16X, 32X)
Slow Motion Play	Allows you to search at a slower speed in an AVI file. (1/2, 1/4, 1/8, 1/16)
ZOOM	X1/X2/X3/X4/Normal in order

- These functions may not work depending on MPEG4 file.

CD-R AVI fileThis

unit can play the following video compression formats within the AVI file format:

- DivX 3.11 contents
- Div 4 contents (Based on MPEG-4 Simple Profile)
- Div 5 contents (MPEG-4 simple profile plus additional features such as bi-directional frames. Qpel and GMC are also supported.)
- XviD MPEG-4 compliant Contents.

DVD-RW & DVD+R

Format that support for DivX file :

- Basic DivX format DivX3.11 / 4.12 / 5.x
- Xvid (MPEG-4 compliant video codec) and DivX Pro
- File format : *.avi, *.div, *.divx.

This unit supports all resolutions up to maximum below.

DivX5
720 x 480 @30fps
720 x 576 @25fps:
Maximum bitrate : 4Mbps

Possible warning messages that may appear when trying to play DivX/AVI files are :

1. No Authorization
 - File with bad registration code.
2. Unsupported Codec
 - Files with certain Codec Types, Versions (ex. MP4, AFS and other proprietary codecs) are not supported by this player.
3. Unsupported Resolution
 - Files containing resolutions higher than the player's specification are not supported.

Note

- The resolution that can be supported by DVD-C500/C550/C550K model up to 720 x 480 @30frames/ 720 x 576 @25 frames.
- This unit supports CD-R/RW written in MPEG4 in accordance with the "ISO9660 format".

Playing Media Files Using the USB Host feature (Only DVD-C550/DVD-C550K)

You can enjoy the media files such as pictures, movies and tunes saved in an MP3 player, USB memory or digital camera in high audio by connecting the storage device to the USB port of the DVD Player.

Using the USB HOST feature

1. Connect the USB device to the USB port on the front of the unit.
2. The USB Menu screen appears. Press the **◀/▶** button to select Menu, then press **ENTER**.
3. Press the **▲/▼** buttons to select a file in the USB device. Press **ENTER** to Open the file.

Note

- Each time the USB button on the remote control is pressed, a frame of the USB device selection will appear.
- "USB" appears on the display screen.
- Depends on the file size and clip duration, loading time on USB may take longer than using CD or DVD media.
- USB MENU screen appears on the TV screen and the saved file is played.
- If there is a Disc in the unit pressing the DVD button will make the player exit the USB menu and load the disc.

Safe USB Removal

1. Press the DVD button to return to disc mode or the main screen.
2. Press the STOP (■) button
3. Remove the USB cable.

Skip Forward/Back

During playback, press the (**◀◀/▶▶**) button.

- When there is more than one file, when you press the **▶▶** button, the next file is selected.
- When there is more than one file, when you press the **◀◀** button, the previous file is selected.

Fast playback

To play back the disc at a faster speed, press (**◀◀/▶▶**) during playback

- Each time you press either button, the playback speed will change as follows : 2X → 4X → 8X → 16X → 32X.

Compatible Devices

1. USB devices that support USB Mass Storage v1.0.(USB devices that operate as a removable disk in Windows (2000 or later) without additional driver installation.)
2. MP3 Player: Flash type MP3 player.
3. Digital camera: Cameras that support USB Mass Storage v1.0.
 - Cameras that operate as a removable disk in Windows (2000 or later) without additional driver installation.
4. USB Flash Drive: Devices that support USB2.0 or USB1.1.
 - You may experience a difference in playback quality when you connect a USB1.1 device.
5. USB Card Reader: One slot USB card reader and Multi slot USB card reader
 - Depending on the manufacturer, the USB card reader may not be supported.
 - If you install multiple memory devices into a multi card reader, you may experience problems.
6. If you use a USB extension cable, the USB device might not be recognized.
- CBI (Control/Bulk/Interrupt) is not supported.
- Digital Cameras that use PTP protocol or require additional program installation when connected to a PC are not supported.
- A device using NTFS file system is not supported. (Only FAT 16/32 (File Allocation Table 16/32) file system is supported.)
- Some MP3 players, when connected to this product, may not operate depending on the sector size of their file system.
- The USB HOST function is not supported if a product that transfers media files by its manufacturer-specific program is connected.
- Does not operate with Janus enabled MTP(Media Transfer Protocol) devices.
- The USB host function of this product does not support all USB devices.

CD Ripping (Only DVD-C550/DVD-C550K)

This feature allows you to copy audio files from a disc to a USB device in MP3 format.

Open the discs tray. Place the Audio CD(CD DA) disc on the tray, and close the tray. Connect the USB device to the USB port on the front of the unit. Press the DVD button.

1. Press the **TOOLS** button to display the Ripping screen.
2. Press the **▲/▼** buttons, then press the **ENTER** button to select files for ripping.
 - To deselect files, press **ENTER** button again.
3. Press the **◀** and **▶** button to select **START**, then press the **ENTER** button begin ripping.
The Ripping menu contain the following buttons :
 - Mode (Fast/Normal)
 - Bitrate, press **ENTER** to change : 128kbps → 192kbps → 128kbps ...
 - Standard : 128kbps
 - Better Quality : 192kbps
 - Device selection, press **ENTER** to change between partitions on the USB device (max 4).
 - Select - Unselect, press **ENTER** to change from Select all (files) or Select none.

Note

- To cancel copying in progress, press the **ENTER** button.
- To return to CDDA screen, press the **TOOLS** button again.
- When the CD ripping being processed the player will automatic in play mode.
- Ripping process is 2.6 times of normal speed.
- Only the Audio CD(CD DA) discs can be ripped.
- The USB button does not work while you're in the Ripping menu.
- CD ripping function may not supported for some MP3 players device.

Picture CD Playback

1. Select the desired folder.
2. Press the **▲/▼** buttons to select a Picture file in the clips menu and then press the **ENTER** button.

Note

- Press the STOP button to return to the clips menu.
- When playing a Kodak Picture CD, the unit displays the Photo directly, not the clips menu.

Rotation

- Press the **TOOLS** button to select Rotate, and then press the **ENTER** button.
- Each time the **◀/▶** buttons are pressed, the picture rotates 90 degrees clockwise.
- Each time the **▲** button is pressed, the picture will reverse to the upside down to show a mirror image.
- Each time the **▼** button is pressed, the picture will reverse to the right side to show a mirror image.

Zoom

- Press the **TOOLS** button to select Zoom, and then press the **ENTER** button.
- Each time **ENTER** button is pressed, the picture is enlarged. Zoom mode : X1-X2-X3-X4-X1.

Slide Show

- When you press the PLAY at JPEG file, it will go to full screen mode and automatically slide show.

Note

- Depending on a file size, the amount of time between each picture may be different from the manual.
- If you don't press any button, the slide show will start automatically in about 10 seconds by default.

Picture CD Playback for HD-JPEG

Must connect to HDMI. Resolution should be 720p/1080i/ 1080p, and HD-JPEG should be in HD mode.

1. Select the desired folder.

2. Press the **▲/▼** buttons to select a Picture file in the clip menu and then press the **ENTER** button.

- Press the **STOP (■)** button to return to the clips menu.

- When playing a Kodak Picture CD, the unit displays the Photo directly, not the clips menu.

Rotation

Press the **TOOLS** button to select Rotate, and then press the **ENTER** button. Press the **◀/▶** button to rotate the screen 90 degrees to the left/right.

Skip Picture

Press the **◀◀** or **▶▶** button to select previous or next picture.

Slide Show

Press the **PLAY (▶)** button to start SLIDE function.

Press the **PAUSE (■)** button to stop SLIDE function.

Note

- Depending on a file size, the amount of time between each picture may be different from the set interval time.
- The image may be displayed at a smaller size depending on the picture size when displaying images in HD-JPEG mode.
- It is recommended to set the "BD Wise" to "Off" In case of playback JPEG image file bigger than 720 X 480 pixel size.

MP3-JPEG Playback

You can play JPEG using music as a background.

1. Press the **▲/▼** buttons to select an MP3 file in the clips menu and then press the **ENTER** button.

To return to the menu screen, Press the **RETURN** or **MENU** buttons.

2. Press the **◀/▶** buttons to select Photos Menu, and then press the **ENTER** button.

Press the **▲/▼** buttons to select a JPEG file in the clips menu and then press the **ENTER** button.

- Music will play from the beginning

3. Press Stop button when you want to stop the playback.

Note

MP3 and JPEG files have to be on the same disc.

CD-R JPEG Disc

- Only files with the ".jpg" and ".JPG" extensions can be played.
- If the disc is not closed, it will take longer to start playing and not all of the recorded files may be played.
- Only CD-R discs with JPEG files in ISO 9660 or Joliet format can be played.
- The name of the JPEG file may not be longer than 8 characters and should contain no blank spaces or special characters (./+=).
- Only a consecutively written multi-session disc can be played. If there is a blank segment in the multi-session disc, the disc can be played only up to the blank segment.
- A maximum of 500 images can be stored on a single CD.
- Kodak Picture CDs are recommended.
- When playing a Kodak Picture CD, only the JPEG files in the pictures folder can be played.
- Kodak Picture CD: The JPEG files in the pictures folder can be played automatically.
- Konica Picture CD: If you want to see the Picture, select the JPEG files in the clips menu.
- Fuji Picture CD: If you want to see the Picture, select the JPEG files in the clips menu.
- QSS Picture CD: The unit may not play QSS Picture CD.
- If the number of files in 1 Disc is over 500, only 500 JPEG files can be played.
- If the number of folders in 1 Disc is over 500, only JPEG files in 500 folders can be played.

Karaoke functions (Only DVD-C550K)

Karaoke Functions

Operation Sequence

1. Connect the Mixed Audio Out terminals with the TV or Amplifier.

2. Connect Mic into Mic jack. When a MIC is connected, the karaoke functions can be used.

Mic Volume and Key Control

1. Playback the Karaoke Disc containing the wanted songs.

- Press the **KARAOKE (▼)** button, and then press **▲/▼** to select **VOL** or **KEY**.

2. Press the **◀/▶** buttons to change the desired item.

Note

- If you hear feedback(squealing or howling) while using the karaoke feature, move the microphone away from the speakers or turn down the microphone volume or the speaker volume.
- When playing MP3, WMA, DTS and LPCM disc, the karaoke functions will not operate.
- When the MIC is connected, Digital Out does not work.
- The MIC sound outputs only from Analog Audio Out.
- If MIC is connected to the MIC jack on the front panel, 5.1CH audio will be changed in to 2 CH audio automatically, this condition can't be change unless the MIC is plugged out.

Changing setup menu

Using the Setup Menu

The Setup menu lets you customize your DVD player by allowing you to select various language preferences, set up a parental level, even adjust the player to the type of television screen you have.

1. With the unit in Stop mode, press the **MENU** button on the remote control. Press the **◀/▶** buttons to select **SETTINGS**, then press the **ENTER** button.
2. Press the **▲/▼** buttons to select a Setup Menu, then press the **►** or **ENTER** to bring up the sub-menu.
3. Press the **▲/▼** buttons to select a sub-menu option, then press the **►** or **ENTER**.
4. To make the setup screen disappear after setting up, press the **RETURN** button.

Setting Up the Display Options

Display options enable you to set various video functions of the player.

1. With the unit in Stop mode, press the **MENU** button. Press the **◀/▶** buttons to select **SETTINGS**, then press the **ENTER** button.
2. Press the **▲/▼** buttons to select **DISPLAY**, then press the **►** or **ENTER** button.
3. Press the **▲/▼** buttons to select the desired item, then press the **►** or **ENTER** button.

Setting Up the BD Wise

When the player is connected to a SAMSUNG TV which supports "BD Wise", you can enjoy optimized Picture Quality by setting the "BD Wise" function as "On".

1. With the unit in Stop mode, press the **MENU** button. Press the **◀/▶** buttons to select **SETTINGS**, then press the **ENTER** button.
2. Press the **▲/▼** buttons to select **DISPLAY**, then press the **▶** or **ENTER** button.
3. Press the **▲/▼** buttons to select **BD WISE**, then press the **▶** or **ENTER** button.
Press the **▲/▼** buttons to select **ON/OFF**, then press the **ENTER** button.

Note

- This option can be changed only when TV support BD Wise.
- Consult your TV User's Manual to find out if your TV supports Progressive Scan. If Progressive Scan is supported, follow the TV User's Manual regarding Progressive Scan settings in the TV's menu system.
- If Video Output is set incorrectly, the screen may be blocked.
- The resolutions available for HDMI output depend on the connected TV or projector. For details, see the user's manual of your TV or projector.
- When the resolution is changed during playback, it may take a few seconds for a normal image to appear.
- If you set the HDMI output resolution 720p, 1080p or 1080i, HDMI output provides better picture quality.
- It is recommended to set the "BD Wise" to "Off" in case of playback JPEG image file bigger than 720 X 480 pixel size.

② Center

- None
- Large
- Small

③ Surround (SL, SR)

- None
- Large (Rear/Side)
- Small (Rear/Side)

Setting up Test

The test output signals come clockwise starting from the Front Speaker(L).

Adjust Channel Balance so that speakers output equally in your room.

FRONT(L) → CENTER → SUBWOOFER → FRONT(R) → SURROUND(R) → SURROUND(L)

Note :

- When play a disc that has MPEG Audio and you have Bitstream selected in the Audio Options menu, the Digital Audio jack may not output audio
- There is no analogue audio output when you play a DTS sound disc.
- Even when PCM Down sampling is Off
 - Some discs will only output down sampled audio through the digital outputs.

HDMI

- If your TV is not compatible with compressed multi-channel formats (Dolby Digital, DTS, MPEG), you should set Digital Audio to PCM.
- If your TV is not compatible with LPCM sampling rates over 48kHz, you should set PCM Down sampling to On.

Manufactured under license from Dolby Laboratories. "Dolby" and the double-D symbol are trademarks of Dolby Laboratories.

"DTS" and "DTS Digital Out" are trademarks of Digital Theater Systems, Inc.

Setting Up the Audio Options

Audio Options allows you to setup the audio device and sound status settings depending on the audio system in use.

1. With the unit in Stop mode, press the **MENU** button. Press the **◀/▶** buttons to select **SETTING**, then press the **ENTER** button.
2. Press the **▲/▼** buttons to select **AUDIO**, then press the **▶** or **ENTER** button.
3. Press the **▲/▼** buttons to select the desired item, then press the **▶** or **ENTER** button.

Surround Sound Speaker Setup (Only DVD-C550K)

1. With the unit in Stop mode, press the **MENU** button. Press the **◀/▶** buttons to select **SETTINGS**, then press the **ENTER** button.
2. Press the **▲/▼** buttons to select **AUDIO**, then press the **▶** or **ENTER** button.
3. Press the **▲/▼** buttons to select **SPEAKER SETUP**, then press the **▶** or **ENTER** button.
4. Press the **▲/▼/◀/▶** buttons to select the desired item, then press the **ENTER** button to set the speaker.

The default settings : FRONT L, R (Small), CENTER (Small), SURROUND (Small). Select the size of the speakers to be connected.

① Front (FL, FR)

- Large
- Small

Setting Up the System Options

- With the unit in Stop mode, press the **MENU** button. Press the **◀/▶** buttons to select **SETTINGS**, then press the **ENTER** button.
- Press the **▲/▼** buttons to select **SYSTEM**, then press the **▶** or **ENTER** button.
- Press the **▲/▼** buttons to select the desired item, then press the **▶** or **ENTER** button.

Setting Up the Anynet+(HDMI-CEC)

Anynet+ is a function that can be used to operate the unit using a Samsung TV remote control, by connecting the DVD C500/C550/C550K to a SAMSUNG TV using a HDMI Cable. (This is only available with SAMSUNG TVs that support Anynet+).

Select On when you connect the DVD C500/C550/C550K with Samsung TV that support Anynet+.

- With the unit in Stop mode, press the **MENU** button. Press the **◀/▶** buttons to select **SETTINGS**, then press the **ENTER** button.
- Press the **▲/▼** buttons to select **SYSTEM**, then press the **▶** or **ENTER** button.
- Press the **▲/▼** buttons to select **ANYNET+ (HDMI-CEC)**, then press the **▶** or **ENTER** button.
- Set the Anynet+(HDMI-CEC) to "On" on your DVD Player, then press the **ENTER** button.
- Set the Anynet+ function at your TV. (See the TV instruction manual for more information.).
 - When you press Anynet+ button on the TV remote control, the below OSD will appear.

Note

- By pressing the **PLAY** button of the unit while watching TV, the TV screen will change to the play screen.
- If you play a DVD when the TV power is off, the TV will power On.
- If you turn the TV off, the DVD Player will power off automatically.
- If you change the HDMI to other sources (Composite, Component,... etc) in TV while playing the DVD disc, the DVD Player will stop playing.

Note

- The language is selected and the screen returns to Language Setup menu.
- To make the setup menu disappear, press the **MENU** button.
- If the selected language is not recorded on the disc, the original pre-recorded language is selected.
- Select "Original" if you want the default soundtrack language to be the original language the disc is recorded in.
- Select "Automatic" if you want the subtitle language to be the same as the language selected as the audio language.
- Some discs may not contain the language you select as your initial language; in that case the disc will use its original language setting.

Setting Up the Security Options

The Parental Control function works in conjunction with DVDs that have been assigned a rating, which helps you control the types of DVDs that your family watches. There are up to 8 rating levels on a disc.

Setting Up the Rating Level and Changing the Password

- With the unit in Stop mode, press the **MENU** button. Press the **◀/▶** buttons to select **SETTINGS**, then press the **ENTER** button.
- Press the **▲/▼** buttons to select **SECURITY**, then press the **▶** or **ENTER** button. Enter your password.
- Press the **▲/▼** buttons to select **PARENTALCHANGE /PASSWORD**, then press the **▶** or **ENTER** button.
- Press the **▲/▼** buttons to select rating level you want, then press the **ENTER** button.
 - e.g) Setting up in **KID SAFE**
 - For example, if you select the Kids Safe level, discs that contain level 2 or higher will not play.
- Enter your password. If this is the first time, enter 0000. Then, enter a new password. The new password must be a number other than 0000 to activate the parental control function. Then, re-enter the new password.

Security Levels :

- KID SAFE**
- G (General Audiences) : All Ages Admitted**
- PG (Parental Guidance suggested) : Some material may not be suitable for young children.**
- PG 13 (PG-13 Parents strongly cautioned) : Some material may be inappropriate for children under 13.**
- PGR (Parental Guidance Recommended) : These are not necessarily unsuitable for children, but viewer discretion is advised, and parents and guardians are encouraged to supervise younger viewers.**
- R (Restricted) : Under 17 requires accompanying adult**
- NC17 (NC-17) : No one 17 and under admitted.**
- ADULT**

Note:

- If you have forgotten your password, see "Forgot Password" in the Troubleshooting Guide.

Setting Up the General Options

- With the unit in Stop mode, press the **MENU** button. Press the **◀/▶** buttons to select **SETTINGS**, then press the **ENTER** button.
- Press the **▲/▼** buttons to select **GENERAL**, then press the **▶** or **ENTER** button.
- Press the **▲/▼** buttons to select the desired item, then press the **▶** or **ENTER** button.

Setting Up the Support Options

Support option enable you to check your DVD player information such as the model code, Software Version, The serial and version numbers can be found on the back side of your DVD-Player.

- With the unit in Stop mode, press the **MENU** button. Press the **◀/▶** buttons to select **SETTINGS**, then press the **ENTER** button.
- Press the **▲/▼** buttons to select **SUPPORT**, then press the **▶** or **ENTER** button.
- Select **PRODUCT INFORMATION**, then press the **▶** or **ENTER** button.

Reference

Troubleshooting

Before requesting service (troubleshooting), please check the following.

Problem	Action
5.1 channel sound is not being reproduced. (DVD-C550K)	<ul style="list-style-type: none">5.1 channel sound is reproduced only when the following conditions are met :<ol style="list-style-type: none">1) The DVD player is connected with the proper Amplifier2) The disc is recorded with 5.1 channel sound.Check whether the disc being played has the "5.1 ch" mark on the outside.Check if your audio system is connected and working properly.In a SETUP Menu, is the Audio Output set Bitstream?
The screen is blocked.	<ul style="list-style-type: none">Press the ■/▶/II button (in front panel) for more than 5 seconds under no disc inside. All setting will revert to factory settings.
Forgot password.	<ul style="list-style-type: none">Press the ■/▶/II button (in front panel) for more than 5 seconds under no disc inside. All settings including the password will revert to the factory settings. Don't use this unless absolutely necessary.
No HDMI output	<ul style="list-style-type: none">Check the Video output is HDMI enabled.Check the connection between the TV and the HDMI jack of DVD player.See if the TV supports this 480p/ 576p/720p/1080i/1080p DVD player.
Abnormal HDMI output screen.	<ul style="list-style-type: none">If snow noise appears on the screen, it means that TV does not support HDCP (High-bandwidth Digital Content Protection).
HDMI output Jitter	<ul style="list-style-type: none">Check your TV system setup correctly.The screen Jitter phenomenon may occur when frame rate is converted from 50Hz to 60 Hz for 720p/1080i/ 1080p HDMI (High Definition Multimedia Interface) Output.Please refer to the user's manual of your TV.

Specifications

Memo

General	Power Requirements	AC110~240V, 50/60Hz
	Power Consumption	6W
	Weight	DVD-C500 : 1.2 Kg
		DVD-C550/DVD-C550K : 1.5 Kg
	Dimensions	DVD-C500 : 360mm(W) X 207mm(D) X 42mm(H)
		DVD-C550/DVD-C550K : 430mm(W) X 207mm(D) X 42mm(H)
	Operating Temperature Range	+5°C to +35°C
	Operating Humidity Range	10 % to 75 %
Video Output	Composite Video	1 channel : 1.0 Vp-p (75 Ω load)
	Component Video	Y : 1.0 Vp-p (75 Ω load) Pr : 0.70 Vp-p (75 Ω load) Pb : 0.70 Vp-p (75 Ω load)
	HDMI	480p, 576p, 720p, 1080p, 1080i
Audio Output	Output terminal	RCA
	Maximum Output Level	2Vrms
	Frequency Response	20 Hz to 20 kHz
	Digital Audio Out	Coaxial terminal (S/PDIF)
	5.1 Channel (DVD-C550K)	F/L, F/R, R/L, R/R, CT, S/W

Memo

Contact SAMSUNG WORLD WIDE

If you have any questions or comments relating to Samsung products, please contact the SAMSUNG customer care center.

Region	Area	Contact Center ☎	Web Site
North America	Canada	1-800-SAMSUNG (726-7864)	www.samsung.com/ca
	Mexico	01-800-SAMSUNG (726-7864)	www.samsung.com/mx
	U.S.A	1-800-SAMSUNG (726-7864)	www.samsung.com/us
	Argentina	0800-333-3733	www.samsung.com/ar
	Brazil	0800-124-421, 4004-0009	www.samsung.com/br
	Chile	800-SAMSUNG (726-7864)	www.samsung.com/cl
Latin America	Nicaragua	00-1800-5077267	www.samsung.com/latin
	Honduras	800-7919267	www.samsung.com/latin
	Costa Rica	0800-234-7267	www.samsung.com/latin
	Ecuador	1-800-10-7267	www.samsung.com/latin
	El Salvador	800-6225	www.samsung.com/latin
	Guatemala	1-800-299-0013	www.samsung.com/latin
	Jamaica	1-800-234-7267	www.samsung.com/latin
	Panama	800-7267	www.samsung.com/latin
	Puerto Rico	1-800-682-3180	www.samsung.com/latin
	Rep. Dominica	1-800-751-2676	www.samsung.com/latin
Europe	Trinidad & Tobago	1-800-SAMSUNG (726-7864)	www.samsung.com/latin
	Venezuela	0-800-100-5303	www.samsung.com/latin
	Colombia	01-800012112	www.samsung.com/co
	Belgium	02 201 2418	www.samsung.com/be (Dutch)
	Czech Republic	800-SAMSUNG (800-26786)	www.samsung.com/cz
	Denmark	8-SAMSUNG (726864)	www.samsung.com/dk
	Finland	30-1000-1000	www.samsung.com/fi
	France	01 4853 0000	www.samsung.com/fr
	Germany	01905-SAMSUNG (726-7884 € 0,14/Min)	www.samsung.de
	Hungary	06-80-SAMSUNG (726-7864)	www.samsung.com/hu
CIS	Italy	800-SAMSUNG (726-7864)	www.samsung.com/it
	Luxembourg	02 261 03 710	www.samsung.com/lu
	Netherlands	0900-SAMSUNG (0900-7267864) (F 0,10/Min)	www.samsung.com/nl
	Norway	3-SAMSUNG (7267864)	www.samsung.com/no
	Poland	0 801 1SAMSUNG (172678), 022-607-93-33	www.samsung.com/pl
	Portugal	8080-SAMSUNG (726-7864)	www.samsung.com/pt
	Slovakia	800-SAMSUNG (726-7864)	www.samsung.com/sk
	Spain	902-1-SAMSUNG (902 172 678)	www.samsung.com/es
	Sweden	0771 726 7868 (SAMSUNG)	www.samsung.com/se
	UK	0845-SAMSUNG (7267864)	www.samsung.com/uk
Asia Pacific	Ireland	0818 717 100	www.samsung.com/ie
	Austria	0810-SAMSUNG (7267864, € 0,07/min)	www.samsung.com/at
	Switzerland	0848-SAMSUNG (7267864, CHF 0,08/min)	www.samsung.com/ch fr (French)
	Russia	8-800-555-55-55	www.samsung.ru
	Kazakhstan	8-10-800-502-55-500	www.samsung.com/kz
	Uzbekistan	8-10-800-500-55-500	www.samsung.com/uz
	Kyrgyzstan	00-800-500-55-500	www.samsung.com/ke
	Tadzhikistan	8-10-800-500-55-500	
	Ukraine	8-800-502-0000	www.samsung.ua
	Belarus	810-800-500-55-500	
Middle East & Africa	Moldova	00-800-500-55-500	
	Lithuania	8-800-77777	www.samsung.comlt
	Latvia	8000-7267	www.samsung.comlv
	Estonia	800-7267	www.samsung.comee
	Australia	1300 352 603	www.samsung.comau
	New Zealand	0800 SAMSUNG (0800 726 786)	www.samsung.comnz
	China	400-810-5855, 010-6475 1860	www.samsung.comcn
	Hong Kong	3698-6698	www.samsung.comhk
	India	3030 8282, 1800 110011, 1800 3000 8282	www.samsung.comin
	Indonesia	0800-112-8888	www.samsung.comid
Middle East & Africa	Japan	0120-327-527	www.samsung.comjp
	Malaysia	1800-88-9999	www.samsung.commy
	Philippines	1-800-10-SAMSUNG (726-7864), 1-800-3-SAMSUNG (726-7864), 1-800-8-SAMSUNG (726-7864), 02-5805777	www.samsung.comph
	Singapore	1800-SAMSUNG (726-7864)	www.samsung.comsg
	Thailand	1800-29-3232, 02-689-3232	www.samsung.comth
	Taiwan	0800-329-999	www.samsung.comtw
	Vietnam	1 800 588 889	www.samsung.comvn
	Turkey	444 77 11	www.samsung.comtr
	South Africa	0860-SAMSUNG (726-7864)	www.samsung.comza
	U.A.E	800-SAMSUNG (726-7864), 8000-4726	www.samsung.comae