MOVIDRIVE® MOVITRAC®31C MOVIDYN®

Addendum to the Operating Instructions

Touch Guard for Flat-Pack Braking Resistors (Panel Type)

Edition 12/98

- This additional information does not replace the detailed operating instructions!
- Equipment may only be installed by qualified electrical personnel in compliance with the applicable accident prevention regulations and operating instructions!



Touch Guard for Flat-Pack Braking Resistors (Panel Type)

A touch guard is now available for flat-pack (panel type) braking resistors.

Touch guard	BS003	B\$005
Part number	813 151 1	813 152 X
For braking resistor types	BW200-003 / BW100-003	BW200-005 / BW100-005 / BW047-005

To mount the touch guard a DIN rail is available as accessory equipement from SEW (part numbernummer 822 194 4)..



00571AEN

Fig.1: Opening the touch guard

Mounting Instructions:

- 1. Mount the touch guard in an appropriate manner, e.g. DIN rail mounting.
- 2. Open the housing cover.
- 3. Place the braking resistor on the lugs provided.
- 4. Feed the connecting cable though one of the three openings.
- 5. Close the housing cover and snap into place, the braking resistor is fixed in position by the closing cover.
- 6. Connect the cable to the $MOVIDRIVE^{\mbox{\tiny (P)}}$, $MOVITRAC^{\mbox{\tiny (P)}}$ 31C oder $MOVIDYN^{\mbox{\tiny (P)}}$ unit.

SEW-EURODRIVE GmbH & Co + P.O. Box 3023 + D-76642 Bruchsal + Tel. +49-7251 75-0 + Fax +49-7251 75-1970 + Telex 7 822 391