

DMXPEN – Recording User Manual

**REC - step 1**

9 VDC 500 mA

- a. insert microSD on the socket
- b. insert M/M DMX gender changer
- c. supply DMXPEN
- d. be sure that was on standby (clearly sky blue)

**REC - step 2**

- e. insert DMXPEN provided with the adapter to the console DMX Out. The led light flashing sky blue indicating the correct DMX reception

**REC - step 3**

3 sec.

- f. hold DMXPEN switch for 3sec

**REC - step 4**

start the show

- g. led light flashing red indicating recording in progress.
- h. start the show playback on on the console

**REC - step 5**

stop REC

- i. press DMXPEN switch to stop recording. The led light steady sky blue (standby).

**REC - step 6**

- l. remove DMXPEN
- m. remove the adapter