


### TYPICAL GAIN DIAGRAM vs FREQUENCY



# SMS - 2.4 x 3 - 9

WLAN Base Station Antenna 2400-2485 MHz



Installation Manual

## DESCRIPTION

Base station antenna conceived for W-LAN system. The radiant element is a Teflon® PCB to guarantee high power and low losses and it is protected by ASA radome. It's supplied with an aluminium bracket for an easy installation on the mast. The antenna is made of 3 separate sectors covering 120° each. When both sectors work in the same time they can cover 360° horizontal.

## **SPECIFICATIONS**

### **Electrical Data**

Type : Multi Sector Dipole Array

Frequency Range : 2400-2485 MHz for W-LAN system

Impedance :  $50 \Omega$  Unbalanced

3 dB Beamwidth Horizontal : H-plane 122° at 2442.5 MHz 3 dB Beamwidth Vertical : E-plane 28° at 2442.5 MHz

Radiation Angle : 0°

Front to Back Ratio : ≥ 11 dB

Isolation : ≥ 30 dB (between any two port)

Polarization : Linear Vertical Gain : 7.2 dBd - 9.3 dBi

V.S.W.R. in Bandwidth :  $\leq 1.4:1$ 

Max Power : 20 Watts (CW) at 50° C Feed System / Position : direct DC-ground / Base


Connector type : 3 x N-female

#### **Mechanical Data**

Housing Materials : Aluminium, Stainless Steel, PCB Radome Material : Thermoplastic UV stabilized Wind Load / Resistance : 60 N at 150 Km/h / 200 Km/h

Wind Surface : 0.05 m²
Height (approx.) : 600 mm
Radome diameter : Ø136 mm
Weight (approx.) : 1250 gr
Operating Temperature : -40° C to 80° C
Mounting Mast : Ø 35-54 mm

#### TYPICAL S.W.R. RESPONSE



## **MOUNTING INSTRUCTIONS**

