



Preface


Firstly thanks a lot for using Ainol digital products--NOVO 7 Advanced Tablet PC, sincerely hope you can enjoy it. This manual will introduce the feature of this product that allows you to fully understand how to use it. For your ease to operate the device as soon as possible, please read the instructions before using the machine so that you can properly use it.

- 1、 It is based on Android 2.3 operating system that supports wireless Internet
- 2、 It is with 7.0-inch high-definition LCD touch screen, 800 x480 Resolution
- 3、 It has 0.3MP Front Camera and 2.0 MP Back Camera
- 4、 It supports 5 points capacitive touch screen +button operation
- 5、 The CPU is Cortex-A10; GPU is Mali-400.
- 6、 The picture used in manual may be different from UI in the device, please subject to the device!

Content

Preface.....	02	Audio Record.....	18
Accessory.....	04	Gallery.....	18
Keystroke Operation.....	05	Camera.....	19
Note.....	07	Video Player.....	20
Basic Operation.....	09	File manager.....	22
App-Installer.....	14	Music player.....	23
Calculator.....	15	HDMI/TV output.....	24
Browser.....	15	TF card	24
Calendar.....	16	Mobile storage function.....	25
Setting	16	Recharge	26
Clock.....	17	FAQ.....	27
Search.....	17	Product specification.....	29

Accessories: If there is any change, we will advise



Novo 7 Advanced



保修手册



合格证



说明书



耳机




USB数据线



电源适配器

1、Keystroke Operation



1 : Volume -

2 : Volume +

3 : Power on/off

4 : DC Interface

5 : Reset

6 : TF/Microsoft Card

7 : USB port

8 : MIC


9 : HDMI Interface

10 : Earphone port

11 : Camera

12 : Speaker

Operation of remote control



1 : Exit

2 : Volume decrease

3 : Back to previous program

4 : Confirm

5 : Turn left button

6 : Forward to next program

7 : Display/pause

8 : Volume increase

9 : Turn right button

Main function

- 7.0 inch high-definition LCD touch screen, 800 X480 resolution ;
- Support Android 2.3 operating system;
- Support APK application and installation
- Support 1080P full HD format video play;
- Support G-Sensor for screen rotation function;
- Support IR remote control operation;
- Support audio play format:MP3, WAV, (APE, FLAC, AAC, OGG need to install third-party software);
- Support TF card, capacity is 2GB-4GB-8GB-16GB;
- Support multi-format video play;
- Support JPG, BMP, PNG, GIF format picture browsing;
- Built-in microphone, can support ultra-long recording;
- Energy-saving setting, brightness freely adjustable, can set up automatic shutdown;
- Support and compatible for WIN2000, WINXP, VISTA, WIN7 system;
- Support e-book and bookmark functions;
- Support firmware upgrade;
- Support multi-task, can read eBook while listening to music

II、 Note

This manual contains important safety measures and the information to use the product correctly.

In order to avoid using improperly, please read the manual carefully before using it.

Never use the device in extremely cold, hot, dusty and moist environment

- Please avoid the device falling down, being hit strongly and suffering severe vibration.
Otherwise, it would lead to the damage or abnormal display of the TFT Screen.
- Battery life will vary as the conditions and environment of use vary
- Please charge the battery in time if any following conditions:
 - A. The system warns that the power is low
 - B. There is no response when operating the keys
- When the device is formatting, uploading or downloading documents do not disconnect it suddenly. Otherwise it will probably lead to player failure. We are not responsible for any document losses incurred by damage and repair the machine or other reasons. Please use it as the manual and copy the important data in time. If you have any questions,

please contact the dealer. Do not disassemble the machine independently. Otherwise, you will lose the warranty that our company is committed to. The user will be responsible for the entire problem caused by disassembling the machine without permission.

- Because the difference of calculating the capacity, the player system firmware and FLASH memory FAT partition table should occupy a certain space. There might be some discrepancies from the local logo of memory capacity and the memory capacity connected to PC.



Depending on the firmware version and FLASH category used by the machine

- At present, there are many viruses in the computer. It is easily damage the local documents and firmware program by the virus. Please step up HIV prevention. If it has HIV infection, lead to the players not available. You can upgrade the firmware in the computer after you ensure that it has no virus, and then formatted it to solve the problem.
- There might be some differences in different software and hardware of the product performance and functionality. Thus changes will not notice. The company reserves the right to improve the product..

III、Basic Operation

- Power On/ OFF


Power On: turned off status, press the power button for 3 seconds, the unit will enter the main interface after the boot.
(Slightly longer boot time, please be patient.)

Off: power status, press the power button for 3 seconds, the pop-up interface, select "Shut Down" option, click to shutdown; clicking on "quiet mode" option can turn on or off the sound, press the power button to close screen, press again to open screen, drag lock up  can unlock and return to the main interface.  Home: Click it to return Home



  Volume + and -

 Esc button



 Operation menu

 Function Key

 Windows switch

Main Screen operation:

Wireless Internet: click on "Google search" in the main interface, then input the contents with the pop-up keyboard input.

After the input is complete, click  to enter website. Click the  on main screen or the menu button on the device, the below interface will display:



Add: Click to add shortcuts to various functions, widgets (such as the analog clock, etc.), folders, or wallpaper to the main interface. The device can delete or move the main screen icon which has been added. In the main screen, press any of the

icons, you can drag to the position you want (move) or delete the icon after the Delete Icon appear on right of the screen, then drag it to Dustbin.

Wallpaper: Click to reset wallpaper.

Search: Click to enter and search content.

Notice: Click to view the system notifications, such as SD card, click to View all notice at the top of the main interface. Then the notice will no longer appears


Settings: Click to enter the system setup menu, such as below shows: :

1、Wireless and network: Tap this can be as follows:


Wi-Fi: to check Wi-Fi network that is using.

Wi-Fi settings: Tap Options, the system will show all the nearby Wi-Fi network to the Wi-Fi network in the receiving list after automatically scans, tap the "Add a Wi-Fi network," pop-up dialog box, the user set

SSID and security can be added the target network to a Wi-Fi network list. Then Click on any network in Wi-Fi network list, in a secure authentication (wireless password, etc.) and click connect to this network is set to the current Internet



network

Wi-Fi Scanning: Tap the menu button  in the Wi-Fi setup interface, click "Scan" in the pop-up menu to scan and refresh the Wi-Fi networks, click the option "Advanced" to enter advanced settings Wi-Fi interface, the user can set with WIFI such as WIFI sleep policy according to their needs.

2、 Sound: This can be set into the silent mode, volume, notification tone, key Sound, screen locked tone

3、 Display: Enter this can set the screen brightness, automatically rotate screen, animation, screen out.

4、 The location and security: To set my location, screen unlock pattern and password options

5、 The application: Management applications

6、 Accounts and synchronization: Set the background data and automatically synchronize

7、 Privacy: The user can remove personal settings for this operation. Click "restore factory settings" option to restore the machine to factory state.

8、 SD card and internal memory: The user can tap into it and view the SD card capacity, SD card uninstall, format, free



space view of the related operations.

9、 The language and keyboard: The system can be set into the language and input relevant information.


10、 Voice input and output: Enter this can set from the text to speech.

11、 Accessibility: No


12、 The date and time: This setting can be turned on automatically from the network date, time functions and manually set the date / time zone / time / format.


13、 About this device: View state of the machine, electricity usage, legal information, hardware type, firmware version of MID and internal version.


Function menu key


Click  this function button, full-featured pop-up menu, such as below:

This window shows all the features of the machine icon, click on

any icon to access the relevant function interface, click on the main interface key  to return to the main interface.


Click  this function button, full-featured pop-up menu, such as above:



This window shows all the features of the machine icon, click on any icon to access the relevant function interface, click on the main interface key  to return to the main interface.

IV、AppInstaller

This device supports APK installation, uninstall and search, click the icon to access the relevant interface.

Enter in the search column "/ mnt / sdcard", "/ mnt / flash" click on the search icon  to see all third-party APK program,;

Click "install" option , install the program , click cancel to return the previous directory:

Install / Uninstall: Touch to install, uninstall APK program.

Select all: Tap to select all search out the APK file.

Unselect all: Touch to all APK file is not selected.

Fresh: Tap to refresh the current page.

About: Touch to view information on the current install.




V、Calculator

In the main menu interface, click the "calculator" option, you can enter the calculator display screen, click on the numbers and operators, can be "add, subtract, multiply, divide,"

VI、Browser

Under the main menu click " Browser "enter into the internet interface , the default home page of this device is " Google ", Click the web address window it will prompt the keyboard , here will introduce how to change the input method number to words . The interface is following picture:



When you finished the input website , click the  icon to show or hide the keyboard, Click  icon enter the webpage, click the  icon when browse the webpage pop-up the following menu operations.



新窗口

Open the new windows



书签

Enter the current URL into the history of memory and Internet browsing interface



窗口

Pop-up the page management window



刷新

Refresh the current page



前进

In contrast with the back button functionality



更多

Available on the web some of the operations of other

VII、Calendar

In the main menu screen click on "calendar" option, you can access the calendar display. Then view or set it

IX、Setting

Under the main menu click the "setting" option can enter the system menu setting interface

X、Clock

In the main menu interface, click the "clock" option, enter the clock display.



Alarm: Click it to set the alarm



Photo view: Click it to automatically view photos



Music: Click it to enter the play list





Home: Click it to go back the main interface

XI、Search

Under the main menu click the "search" into the following interface as following picture:



VI、 Audio Record

Under the state of main menu, select "Record" option to enter the Record interface, Click  button to start record. Click  button will stop record and save it automatically .

XII、 Galley

On the main screen click on "Gallery" option, you can enter the picture thumbnail interface, the point of selection of an image file into the picture browsing interface. Click anywhere on the screen to show or hide the picture settings menu, drag around the screen, can be switched on or left image:



Zoom icon: Click to enlarge or shrink the current image directly

Click on the "Slide" option, you can slide the picture gallery in a way to play.

Click the "Settings" option, you can enter the picture menu page, enter the feature to see pictures for more information on the picture to rotate, crop, delete, and share.

XII、Camera


In the main menu interface, click the "camera" option, you can enter the camera interface



Click it to change to video



Click it to change to photo-taking


Enter to the camera interface, click the icon  , can be photographed and saved automatically. Top right of screen, click the small icon to view the photos taken. On the right corner of the interface, click to show or hide the camera settings menu.



Click to set the exposure, photo quality, and camera.



Switch the front and back camera

Enter into the video screen, click the icon  , can be video, click again to pause and automatically saved. Click the small icon in the upper right corner, the recorded video can be played; in the video shown on the right corner of the interface click to show or hide the video settings menu.



Click to restore the default settings (as shown).




Click to set the screen effect of the video




Switch the front and back camera

XII I、Video Player

On the main screen click on "media player" option, you can access the video files list interface, the point of a video can be selected into the video player interface. Click anywhere on the screen can show or hide the video set icon, and click to set.



Return icon,



Esc, return the previous interface



Previous video



Rewind



Pause



Fast forward



Setting button, when you click will appear the following picture:



Breakpoint play icon



Play mode



Track icon



Subtitle



Zoom Icon




Brightness



Check the video information

Ⅱ、File Management



In the "File Manager" module, will show the internal memory and SD card that lists all the files, click it to enter one by one, will be listed under the current folder.



Click to display the device list



Click to enter the multiple choice / open mode



Click to display the Edit menu, the "cut, copy, paste, delete"



Click to display the sort menu



Click to return to the parent directory.



Click to show list of files into thumbnails.




Click to view a brief description of each function



Click to close the file manager, returned to the main menu interface

XIII、 Music Player

In the main menu interface, click the "Music Player" into the file list interface, select any music to play.



Click the icon to return to the Now Playing list.



Shuffle icon: Click to open or close the Shuffle



Click the icon to set the "repeat the current song, repeat all songs, repeat off", etc.



Click the icon to play on last song.




Click to pause and play the current song.



Click to play the next song



In the music player interface, click the icon  or press the Menu button, you can set the pop-music menu, click on "music library, party shuffle, playlist, delete" to enter the setting interface.

XIII、HDMI Output

HDMI cable is only one line with connected TVs with the machine corresponding to HDMI, TV transferred to HDMI, the machine interface in the optional output of a mode setting function, you can switch to the HDMI output. Into the "Output Settings" function interface, click the "LCD screen" option; you can go back to the main screen.

XIV、TF Card



1. The TF card inserted in accordance with icons to the player's cards bad
2. If you want to unplug the TF card, first make sure players do not currently operate on the card, and then look at his hand soft reduction card, TF card will automatically pop up at this time
3. The use of TF card, please use the machine to TF card on the computer format, to ensure that the file format is FAT32 of this system is fully compatible with FAT32 file format

4. If you have plug TF card on the machine can be seen TF card has been used capacity and available capacity

Note: as far as possible in the off state TF card is inserted or removed in order to avoid loss of programs or data errors.

XIV. Mobile storage function.

The device for high-speed USB2.0 interface, the standard removable disk function, support for Windows98 (need to install the driver), Windows2000/XP/Vista (do not need to install the driver) system, use the USB cable (please try to use the first wife Ainol data line) connected with the PC after (wait a few minutes), the player is displayed as on-line mode; The use of removable storage functionality,

Copy files / folders

Download files from your computer to the player, just simply want to download the file / folder onto your player can move the disk can be the same; you can put players inside the file transfer to your computer

Delete a file / folder

Select File / folder on the keyboard, press the "Delete (delete)" key for file / folder deletion. Click "OK" to delete,

Note: In the MP3 and computer data exchange, not to unplug USB cable, otherwise it will result in loss of control buttons, and even loss of machine processes;

Use after the Windows desktop right-click the bottom right corner of the "" icon, according to the computer prompts, security, disconnect the USB connection.

XX、Recharge

You can connect to the computer's USB port for Charging by using USB cable or charger to recharge the unit when the main interface screen, the dynamic charging icon appears in the middle, After charging, the charging icon appears over the cell and to stop charging (The first two will need 8 hours to fully activate the battery);

XX I、FAQ

The machine could not be power on

Check if the battery is empty.

Check it again after connects the power adapter.

If you still cannot power on after charging, please contact our sales.

No sound is available when playing.

Please check if the volume is set to 0.

Please check if the earphone' s connection is a problem.

Serious noise

Please check whether the earphone plug is clean, dirt can lead to noise. Check is the music files have broken. Try to determine the other music. If the file has been damaged, it will lead to very serious tone of the noise or jump.

Garbled screen

Please check whether it has set the correct language option, the language chosen can set in the (set) => (language selection)

The files cannot be downloading

Confirmed the connection between the computer and the player is proper

Confirm whether the memory is full of storage space.

Confirm whether there is any damage in the USB cable.

Special attention

When the official announcement was the latest upgrade software, upgrade software, MP4 actual operation methods, and user interface may be discrepancies with the manual and the official release date of the statement on the website there is a need for users to go to official website to download

XXII、Product Specification

Model Number	NOVO 7 Advanced
Power adapter	DC 5V 2A
Screen Size	7.0 inch HD LCD with 5 points capacitive touch screen
Screen res.	800*480
USB	High speed USB 2.0
Micro SD card	2GB~4GB~8GB~16GB
OS	Android 3.2
WIFI	802.11b/g/n
Audio format	Support MP3,WAV,(APE,FLAC,AAC,OGG need install the third software)
Video format	Support MOV,MKV,AVI,TS,TP,M2TS,VOB,DAT,MPEG,MP4,PMP,3GP,FLV,WMV,ASF etc.
Photo format	JPG、BMP、PNG、GIF
Ebook format	TXT、LRC、(PDF,EPUB,FB2 need install the third software)

Record	MP3
Temperature	Working temperature: -10~45 degree
Battery	3.7V 4000mAh
Support system	Win2000/XP/VISTA/Win7

Enjoy Life Enjoy AINOL

*ainol 艾诺

GadgetFreakz

Simply Mad About Gadgets

