# **Quick Reference Guide**



■ 本機は日本国内用です。国外での使用に対するサービスは致しかねます。
 ■ This product is designed for use in Japan.

Panasonic cannot provide service for this product if used outside Japan.

• The number after the button shows the location of the button described in the previous page.

#### Base unit (VE-GP50)

#### To make a call

Lift the handset. →Dial.

#### To receive a call

When the phone rings...  $\rightarrow$  Lift the handset.

To place the current call on hold

Press (17) during a call.

(You can place the handset on the base unit.)

#### To retrieve the held call

- If you have returned the handset on the base unit, lift the handset.
- If you have not returned the handset on the base unit, press \_\_\_\_\_ again.
- To transfer the held call to the personal phone
  Press ( 16) during a call. ( →When you use multiple personal phones, press 1 6 (Intercom No.).) →Place the handset on the base unit when the other party answers.

#### To use TAM (Telephone Answering Machine)

When you leave home, press ((8)) to turn on the indicator.

(To deactivate, press 留守) again to turn off the indicator.)

➡ When receiving a call while TAM is activated, it answers the call automatically in Japanese, and records the incoming messages.

Then, the ( indicator starts flashing.

 $\rightarrow$  When you return home, press B to play back the messages.

The () indicator turns off and the answering mode is deactivated.

After playing back the messages, press **\*** to erase the messages or press **#** to keep the messages.

To play back the messages while TAM is deactivated, press

\*Up to 50 messages can be recorded for approx. 12 minutes in total.

#### To hear recorded messages while away from home (Remote control) Preparation before you leave home

Store a remote control number.

With the handset placed on the base unit, press <sup>₩/₩</sup> #006.→Enter the desired

4-digit number. → Press (決定), then press () ((the press () (the press

#### To hear messages

Dial your home phone number.  $\rightarrow$  While the outgoing message is played back...

→ Enter your remote control number.

→Announcement → Press 2...→You will hear recorded messages if any.

#### NOTE

This operation can be made only from telephones which can send DTMF signals.

#### Personal phone (KX-FKN512)

#### To make a call

Lift the personal phone from the charger and press  $\Re$  (**4**).  $\rightarrow$  Dial......To end the call, place the personal phone on the charger or press (**1**).

#### To receive a call

When the phone rings...  $\rightarrow$  Lift the personal phone from the charger or press  $\mathcal{F}$ .  $\rightarrow$  Talk......To end the call, place the personal phone on the charger or press  $\mathcal{T}$ .

#### To make a call using the speakerphone (Hands-free talk)

Press 👹 (∏). → Dial.→ Talk to the microphone......To end the call, place the personal phone on the charger or press ().

#### To receive a call with the speakerphone (Hands-free talk)

When the phone rings... → Press <sup>20+10</sup>/<sub>(☉</sub>.
 → Talk to the microphone..... To end the call, press <sup>10</sup>/<sub>(☉</sub>.

To place the current call on hold Press () (5) during a call.

## To retrieve the held call Press (7%) or (R).

### To transfer the held call to the base unit Press (m) (14) during a call. (→When you use multiple personal phones, press (0).) →Place the personal phone on the charger, or press (19) when the other party answers.

#### To transfer the held call to another personal phone

Press ( during a call.  $\rightarrow$  Press (1) - 6 (Intercom No.). $\rightarrow$  Place the personal phone on the charger, or press () when the other party answers.