

Video Cassette Recorder
VR 888

PHILIPS

Video Cassette Recorder
VR 888

Technical Specifications (VR 888/55)

General	
Format	: VHS
Video Heads	: 4
Audio Heads	: 2
Tape Speed	: SP / LP / (PAL) SP / SLP (NTSC)
Tape Mechanism	: Full Loading
Dimension (W X H X D)	: 400 X 94 X 330 mm.
Weight	: Approx. 4 kg.
Video Systems	: PAL / MESECAM / NTSC 3.58 / NTSC 4.43 PAL 60 (NTSC Playback on PAL TV)
Modulator Channel	: G, I, K, CH 32-40 Preset at CH 36
Tuner Range	: BG / DK / I / KI / M / Hyperband VHF Low 43-108 MHz
Stereo	: NICAM I / BG 2 CS BG (German Stereo)
Mains Voltage	: 110-240V
Mains Frequency	: 50 / 60 Hz
Audio	
Audio in/out	: Cinch / Cinch (Stereo)
Signal-to-noise Ratio	: better than 43 dB.
Frequency Response	: 20Hz to 20kHz
Video	
Tuner	: Frequency Synthesized Tuner
Video in/out	: Cinch / Cinch
Antenna terminal in/out	: Coaxial 75 ohm
Signal-to-noise Ratio	: better than 43 dB.
On Screen Display	: English, Chinese & Russian
Resolution	: Better than 240 lines
Accessories	
RF Cable	: 1 pc.
Remote Control	: 1 pc. (including batteries)

<http://www.philips.com>



VR 888/55

Feature Contents

- 6 Head - 4 Video & 2 Audio**
 The DA 4 Head design ensures a perfect still, interference free slow motion & frame-by-frame advance picture while another 2 heads are added to provide high quality Stereo HiFi sound both in Playback & Recording. By connecting the audio output to a HiFi Audio System, you will be able to enjoy superb sound for the complete Home cinema experience.
 - Plug & Play Set-up**
 Easier and faster tuner setup of the VCR after connecting the set to the mains and via RF cable or AV cable to the television set. By switching on the set, automatically the installation menu will start and step-by-step, the user will be instructed to give input for the VCR installation.
 - Multi Hyperband CATV Tuner**
 The Tuner in the VCR allows reception of all Super band and Hyper band channels which includes most if not all Cable TV channels in use today.
 The reception frequency covers 42 Mhz up to 470 Mhz in the VHF band and from 470 Mhz up to 870 Mhz in the UHF band.
 - Super Multisystem with NTSC Record & Playback**
 This Multisystem VCR will be able to record and playback PAL, MESECAM and NTSC signals. This enables playback of a huge selection of videos from around the world and record programmes in many countries.
 - Lighted Multibrand TV Remote Control**
 This unique Remote Control will control most brands of colour television for the power On/Off, channel Up/Down as well as Volume Up/Down. By pushing a button, the main function on the remote control are illuminated by a red led. This is very convenient in a dark environment as the Remote Control functions are now clearly visible.
 - Incredible Picture Chip**
 Through advanced circuit design and the Audio / Video signal processing, the Picture Performance of this VCR is truly INCREDIBLE. By utilizing the Incredible Picture Chip, an all-in-one control system as well as an automatic adjustment process, the very Best Picture Performance has been guaranteed. Automatic adjustments are also made when worn or noisy Rental tapes are played back, ensuring the very Best Picture Performance for every occasion.
 - Show View / G-Code ***
 This new feature provides a very easy means of performing your timer recording. Key in a code, which is available in most newspapers or magazines, via the remote control. The VCR is ready to perform any unattended recording. Each TV programme will have its unique set of code.
 - Nicam + German 2CS**
 Now you can view your favourite TV programmes with digital-clear high quality stereo sound. This is made possible through the NICAM module in the VCR. If the TV programme is transmitted in dual language, you may also select the language you want. This gives you the possibility to enjoy your programme through a second language should you not understand the primary language. You will also attain high quality stereo sound should the programme be transmitted in German 2CS format.
 - Quick Timer Programming**
 By pressing buttons on Remote Control Unit, direct programming will be operated. It is so easy and quick.
 - Video Index Search System (VISS)**
 At the start of each recording, an index code is written automatically enabling the VCR to identify the start of the programmes. Easy scanning of the tape to the starting point of each programme. Full playback control and easy editing of own video tapes.
 - A/V Front In Socket**
 This feature provide a high quality and convenient connection from other VCR or camcorder to your VCR for the purpose of dubbing onto your VCR.
 - Trilingual On Screen Display**
 Operation is made even easier by this function, which clearly shows you the status and settings of the VCR on your TV screen. On Screen Display is also used for step-by-step programming recordings, so you can see what you're doing at every stage and confirm it error free. The choice of languages available are English, Chinese & Russian.
- Subject to modification without notice**
 * Show View / G-Code is a trademark applied for by Gemstar Development Corporation. The Show View / G-Code system is manufactured under license from Gemstar Development Corporation.

6 Head Video Cassette Recorder

- Multi Hyperband CATV Tuner
- Plug & Play Set-up
- Super Multisystem with NTSC Record & Playback
- Lighted Multibrand TV Remote Control
- Quick Timer Programming
- Incredible Picture Chip - Best Performance & Reliability

head **Hi-Fi** STEREO
NICAM

Hyperband
CATV Tuner

Lighted
Multi Remote

Plug&Play
Incredible Picture

SHOWVIEW / G-CODE

Super**Multi** PAL / MESECAM / NTSC^{3.58}
BG · DK · I · K1 · M^{4.43}



(VR 888/55)



Let's make things better.



PHILIPS

Let's make things better.



PHILIPS