

INSTALLATION INSTRUCTIONS FOR PART 99-7330

APPLICATIONS

KIA Spectra/Spectra 5 2007-2009

99-7330


KIT FEATURES

- Recessed DIN Mount Radio Provision with Pocket
- ISO Mount Radio Provision with Pocket



KIT COMPONENTS

A) Radio Housing B) ISO Brackets C) Trim Plate





1-800-221-0932



www.metraonline.com

© COPYRIGHT 2007-2009

METRA ELECTRONICS CORPORATION



99-7330

TABLE OF CONTENTS

<u>Dash Disassembly</u>
- KIA Spectra/Spectra 5 2007-2009
<u>Kit Assembly</u>
- DIN Mount Radio Provision with Pocket
- ISO Mount Radio Provision with Pocket
Final Assembly

*Note:

Refer also to the instructions included with the aftermarket radio.



KNOWLEDGE IS POWER

Enhance your installation and fabrication skills by enrolling in the most recognized and respected mobile electronics school in our industry. Log onto www.installerinstitute.com or call 800-354-6782 for more information and take steps toward a better tomorrow.





99-7330 DASH DISASSEMBLY

KIA SPECTRA/SPECTRA 5 2007-2009

- Disconnect the negative battery terminal to prevent an accidental short circuit.
- 2 Unclip and remove the trim panel surrounding the radio and including the a/c vents. (Figure A)
- 3 Remove (4) Phillips screws securing the radio. Unplug and remove radio. (Figure B)

Continue to kit assembly.








99-7330 KIT ASSEMBLY


RECESSED DIN MOUNT RADIO PROVISION WITH POCKET

*Note: Refer also to the instructions included with the aftermarket radio.

- 1 Slide the DIN cage into the Radio Housing and secure by bending the metal locking tabs outward. (Figure A)
- 2 Slide the aftermarket radio into the DIN cage/housing assembly until it snaps into place. (Figure B)

Continue to final assembly.








99-7330 KIT ASSEMBLY


ISO MOUNT RADIO PROVISION WITH POCKET

*Note: Refer also to the instructions included with the aftermarket radio.

- 1 Align the holes from the ISO snap in brackets with the holes in the side of the radio and mount the brackets to the radio using screws supplied with the radio. (Figure A)
- 2 Slide the radio/bracket assembly into the radio housing until the assembly snaps into place. (Figure B)
- 3 Snap the ISO trim plate onto the radio and housing assembly. (Figure B)


Continue to final assembly.







FINAL ASSEMBLY



- (A) Strip wire ends back 1/2"
- B) Twist ends together
- C) Solder
- D) Tape
- 1 Locate the factory wiring harness in the dash. Metra recommends using the proper mating adapter and making connections as shown. (Isolate and individually tape off the ends of any unused wires to prevent electrical short circuit.)
- **2** Re-connect the negative battery terminal and test the unit for proper operation.
- 3 Reassemble radio and dash assemblies in reverse order of disassembly.

FINAL WIRING CONNECTIONS

Make wiring connections using the EIA color code chart shown below and the instructions included with the head unit. Metra recommends making connections as shown below; Strip, Splice, Solder, Tape. Isolate and individually tape off ends of any unused wires to prevent electrical short circuit.

METRA / EIA WIRING CODE

12V Ignition / Acc	Red	Right Front (+)	Gray
12V Batt / Memory	Yellow	Right Front (-)	Gray/ Black
Ground	Black*	Left Front (+)	White
Power Antenna	Blue	Left Front (-)	White / Black
Amp Turn-On	Blue / White	Right Rear (+)	Violet
Amp Ground	Black / White	Right Rear (-)	Violet / Black
Illumination	Orange	Left Rear (+)	Green
Dimmer	Orange / White	Left Rear (-)	Green / Black

^{*}NOTE: When a Black wire is not present, ground radio to vehicle chassis.

All colors may not be present on all leads due to manufacturer's specifications.



99-7330

NOTES

99-7330 INSTRUCTIONS





1-800-221-0932 **—** www.metraonline.com