

Philips
Digital Cable Receiver

DCR2022



Digital Cable Television

More channels in superior quality

In combination with a subscription of your cable TV provider you will be able to receive many new TV channels in digital quality.

Better

- Dolby Digital 5.1 audio output for full surround sound
- 2 SCART connectors for connecting your TV and other source
- Fast Zapp, change from channel to channel within 1 second
- Low-power mode with less than 1W consumption
- Channels and installation menu can be locked by a PIN code
- High-quality SCART cable is included

More

- Access to Pay-TV channels and free-to-air services

Easier

- Direct teletext button on the remote control
- Fast and automatic installation of new channels
- Euphoria User Interface simplifies navigation through menus
- 7-day Electronic Program Guide for listing of programs
- The STB is initiating recording on to your VCR or DVD+RW

PHILIPS
sense and simplicity

Specifications

Tuner/Reception/Transmission

- **DVB:** Cable
- **Demodulation type:** MPEG-2 DVB compliant, QAM
- **Input frequency range:** 950-2150MHz, 51 - 858 MHz
- **Symbol rate:** 3-6.9Ms/s

Connectivity

- **Cable antenna interface:** RF in - IEC 169-2, RF out - IEC 169-2
- **TV scart out:** Audio L/R, CVBS, RGB, S-Video (for LCD projector)
- **VCR scart in:** Audio L/R, CVBS, RGB
- **Audio Output - Analog:** Audio L/R (cinch)
- **Audio Output - Digital:** Coaxial (cinch)

Convenience

- **Child Protection:** Child Lock+Parental Control
- **Ease of Installation:** Autoinstall
- **Events timer/reminder:** 10
- **Favorite list radio programs:** 3
- **Favorite list TV programs:** 3
- **Parental control:** Lock with PIN code, Child timer
- **Programmable Events:** 1
- **Recording:** Record failure alarm, Record header message
- **Signal strength indication**
- **User Interface:** 7 day Electronic program Guide, Automatic program list update, Multiple subtitles supported, Now & Next ESG, On Screen Display on TV, TV and Radio mode

Video Decoding

- **Compression Format:** MPEG-2 MP@ML (std definition)
- **Conditional access system:** Irdeto (card not

- supplied), Subscription needed for pay-TV
- **De-scrambling:** Smart Card reader
- **Resolution:** up to 720 x 576 interlaced
- **Aspect Ratio:** 16:9, 4:3 Letterbox, 4:3 Pan Scan

Audio Decoding

- **Compression format:** MPEG layer I/II
- **Sound system:** Dolby Digital, AC3 downmixed to stereo, Stereo, Mono

System Specifications

- **CPU speed:** 60 MHz
- **Flash memory size:** 2 MB
- **Ram size:** 8 MB SDRAM

Power

- **Low power mode (ECO):** <1 W
- **Power consumption:** 10 W
- **Power supply:** 220-240V
- **Standby power consumption:** <7 W

Technical specifications

- **Operating temperature range:** 0 to +40 °C
- **Storage temperature range:** -20 to +60 °C

Dimensions

- **Product dimensions (W x H x D):** 238 x 42 x 145 mm
- **Carton dimensions (WxDxH):** 320x85x295 mm
- **Weight:** 0.98 kg
- **Weight incl. Packaging:** 1,780 kg

Accessories

- **Included Accessories:** High quality SCART cable, Mains cord, Remote Control, User Manual, Quick install guide, Safety & warranty booklet
- **Batteries:** 2 x AA

Product highlights

Dolby Digital surround

Because Dolby Digital, the world's leading digital multi-channel audio standards, make use of the way the human ear naturally processes sound, you experience superb quality surround sound audio with realistic spatial cues.

Direct teletext via the remote

A button which you can also find on your TV remote to have direct access to teletext

2 SCART connectors

2 SCART sockets allow you to connect to 2 devices at the same time. One for the TV, and the other either to a recording product (e.g. VCR or DVD recorder) for recording of TV programs, or to a video playback device (e.g. DVD player or Blu-ray player). Simply connect the SCART sockets on the product to the SCART socket on the desired devices, by a SCART cable. Video signals would then pass through onto the other device for viewing or recording.

Fast Zapp

Time it takes to go one channel up/down

Access to Pay TV services

More and more top quality content are being broadcasted these days, but the only way to access these premium channels is to subscribe to the services from the local Pay-TV operators. Insert the operator's smart card into the set top box, and it will descramble the encrypted signals that are being broadcasted by the Pay-TV operators.

Automatic installation

New channels are quite often being added to the broadcasting network during the digital switchover. To ensure that you always have the access to all available channels, it is important that the product is able to scan and install new channels automatically. A very sensitive tuner in the product is scanning through the broadcasting network for new channels whenever the product is switched off. Whenever a new service is detected, it will be automatically updated and saved onto the channel list.

Euphoria User Interface

Easy navigation through the menu structure.

Low power mode

Parental lock

Channels and installation menu can be locked by PIN code

Free SCART cable

high quality SCART cable

Electronic Program Guide 7d

You want to know what are the programs available today and for the next 7 days, so that you can avoid missing your favorite shows by planning your evenings or making pre-scheduled recordings. The data is broadcasted by the program broadcaster, and when this data is available, this product compiles the information and list them in the menu for your easy use reference. Simply enter the menu, or press the EPG button on the remote control to access the program guide. The EPG will provide you with an overview, listing the program information for the upcoming 7 days.

VCR management

Having a second SCART connector in the box enables you to connect a VCR/DVD+RW and manage the recordings you want to make in the STB..



Issue date 2008-04-19

Version: 1.0.4

12 NC: 8670 000 30864
EAN: 87 12581 34109 1

© 2008 Koninklijke Philips Electronics N.V.
All Rights reserved.

Specifications are subject to change without notice.
Trademarks are the property of Koninklijke Philips Electronics N.V. or their respective owners.

www.philips.com