

PT-1610 Mounting Instructions

16V AC, 10VA Transformer

INSTRUCTIONS

MOUNTING ON A METAL BOX:

- 1. Secure gang box to wall or ceiling stud.
- 2. Remove a conduit knockout from the gang box.
- 3. Pass transformer wires through knockout hole to inside of box.
- (Locking screw must be removed to pass flange through hole.)
- 4. Secure transformer to box with locking screw of appropriate length. Two screws are provided.
- 5. Connect incoming AC power to two BLACK wires. Connect GREEN wire to ground.
- 6. Ensure that all connections meet local and NEC 725 standards.



MOUNTING IN A PLASTIC TWO GANG BOX

- 1. Secure gang box to stud.
- 2. Open a plastic locking tab from the gang box.
- 3. Pass AC wires through hole to inside of box.
- 4. Connect incoming AC power to two BLACK wires. Connect GREEN wire to ground.
- 5. Connect low voltage AC power to the two screw terminals.
- 6. Run low voltage wire through a different locking tab then to the 110V AC wires.
- 7. Ensure that all connections meet local and NEC 725 standards.
- 8. Locate transformer inside the box, then cover with a blank plastic faceplate.





(425) 455-0510 FAX (425) 455-0071

(800) 832-3765 E-MAIL: tech-serv@aiphone.com

PT-1610 Inst. 0200 #99106