

6 head HiFi Stereo VCR

VR685

6 head HiFi Stereo VCR

- **Stereo HiFi - NICAM**
- **Audio Stereo Cinch** outputs to connect to your HiFi system and enjoy a complete Home Cinema System
- **Front AV Cinch** input with Synchro-Edit for an easy connection with your Camcorder
- **One-Button** automatic installation including automatic time download and correction
- **FollowTV** sorts the channels in the same order as your TV
- **Digital Studio Picture Control** for an excellent picture quality
- **Easy-to-read** big VCR Display

**TURBO
DRIVE**

SHOWVIEW

VIDEOplus+



Let's make things better.



PHILIPS

Product Information

Reception

- Tuning: PLL, CH - FREQ entry, 99 presets
- Tuning / Install Features: Automatic Search, Manual Search / Store
- Automatic Time / Date Download: PDC, Text (Time)

User Interface

- Special Features: Child Lock
- Picture Improvement System: Digital Studio Picture Control, Edge Noise Canceller
- Audio Record System: FM Audio, Linear
- Audio Record Level: Automatic
- TV Related Functions: FollowTV, Direct Record

Programming

- Number of Events: 6 / month
- Programming Mode: OTR, Remote
- Record Control & Transmitter Identification: PDC, VPS
- Programming System: Daily / Weekly
- Automatic Sat. Recording: From EXT2
- Record Speed: Long Play, Standard Play

Tape Deck

- Number of Video / FM Audio/Erase Heads: 4 / 2 / 0
- Play: +1x, -1x
- Playback Features: Perfect Still, Multiple Search Speeds, Variable Slow Motion Speed
- Index Search: Next / Previous index search
- Tape Length Recognition: Automatic
- Tape Counter: Linear relative, Linear time used
- Automatic Functions at Tape End: Rewind after Play – Eject after Record
- Winding / Rewinding Time (E180): 100 sec.
- Head Cleaning Mode: Automatic, Manual

Connectors Rear

- EXT1: Black, Euro CVBS In & Out
- EXT2: Blue, Euro CVBS In & Out, Euro Decoder, RGB loop through
- Audio Connectors Rear: Cinch Stereo Out
- Antenna In & Out: 75 Ohms (IECtype)
- Mains Connector: Standard (IECtype)

Connectors Front

- Audio / Video Connectors Front: Cinch CVBS in, Cinch stereo in

General

- Voltage / Frequency: 198-264V / 50Hz
- Backup Presets: 1yr
- Backup Clock, Timer Events & Calendar: 7hrs
- Power Cons. in Play / Std-By / Low Power Std-By: 16W / 9.5W / <6W
- Remote Control: RT184
- Equipment Supplied: Antenna cable, Mains cord, Batteries
- Set Size – W x D x H (mm): 380 x 260 x 93
- Packaging – W x D x H (mm): 450 x 382 x 180
- Weight including / excluding package in kg: 5.5 / 3.6

Product Highlights

• Digital Studio Picture Control

Thanks to a digital Noise-Reduction Circuit, you are sure to obtain the best picture quality with any kind of tape.

• Automatic Time Download

At the first installation, your VCR will automatically download the time. Your VCR will be the clock reference in your home, as the time is readjusted every day. You don't even have to worry anymore about changing from summer to winter time!

• Child Lock

Now there is no way that your children can see a movie without your permission. Just don't forget to hide the remote control!

• Follow TV

You can now automatically arrange your VCR channels in the same order as your TV.

• Direct Record

Record instantly what you see on your TV just by pressing one button. You don't have to worry anymore about selecting the right channel on your VCR.

• TURBO DRIVE

Enjoy the ease of use and the comfort of one of the fastest VCR decks in the world.

• Automatic Head Cleaning

Clean heads ensure an optimum picture quality. Each time you put a tape in your VCR, the heads will be cleaned automatically.

	/02	/07	/13	/16	/39	/58
Full (UHF+VHF) Tuner	x	x	x	x	x	x
TV System Off Air	PAL B/G	PAL I	PAL B/G	PAL B/G	PAL B/G-I, SECAM B/G-L/L'	PAL B/G-D/K, SECAM B/G-D/K
Sound System Off Air	Mono, German Stereo	Mono, NICAM	Mono, German Stereo, NICAM	Mono, German Stereo, NICAM	Mono, German Stereo, NICAM	Mono, German Stereo, NICAM
Programming System	ShowView™	VideoPlus™	ShowView™	ShowView™	ShowView™	ShowView™
Record/Playback Std	PAL	PAL	PAL	PAL	PAL-SEC-MESEC	PAL-MESEC
Additional Playback Std	NTSC	NTSC	NTSC	NTSC	NTSC	NTSC
Modulator System	PAL G	PAL I	PAL G	PAL G	-	PAL G/K
Modulator Range	Ch 21 - 55	Ch 21 - 55	Ch 21 - 55	Ch 21 - 55	-	Ch 21 - 55
Modulator Feature	-	Auto Seek	-	-	-	-
Modulator Preadjustment	Ch 36	Ch 35	Ch 36	Ch 36	-	Ch 36
OSD Menu Languages	Dutch, French, German, Italian	English	English, Swedish, Danish, Finnish	Dutch, French, Spanish, Portuguese	Dutch, French, German, Italian	Czech, English, Hungarian, Polish, Russian
Delivery Menu Language	German	English	English	Dutch	French	English
Remote RT184 /	101	101	101	101	104	101

Subject to modification without notice

ShowView and VideoPlus are Trademarks of Gemstar Development Group